


EXPLODED VIEW / PARTS LIST

Parts list

NO.	PART NO.	DESCRIPTION	Q'TY	NO.	PART NO.	DESCRIPTION	Q'TY
1	-	*Unused number	-	10-7	074-2248-40	OUTLET SOCKET	1
1-1	940-8790-70	ES-ASSY(for PF3731BA)	1	10-8	074-2248-30	OUTLET SOCKET	1
	940-8790-41	ES-ASSY(for PF3732BA)		10-9	074-2249-04	OUTLET SOCKET	1
1-2	013-9745-00	TOUCH PANEL	1	10-10	074-2248-60	OUTLET SOCKET	1
1-3	379-0491-02	TFT	1	10-11	060-8162-90	BLUETOOTH MODUL	1
1-4	335-9939-02	MOLDED PART	1	10-12	074-8017-91	OUTLET SOCKET	1
1-5	335-9938-02	MOLDED PART	1	10-13	331-5533-03	PRESSED PART	1
1-6	346-0314-11	LEATHER SHEET	1	10-14	331-5534-01	PRESSED PART	1
1-7	335-9937-00	MOLDED PART	1	10-15	331-5586-01	PRESSED PART	1
1-8	331-3038-50	EARTH PLATE	1	10-16	778-3006-00	TAP-SCREW	2
1-9	331-5532-03	PRESSED PART	1	10-17	714-2606-8B	MACHINE SCREW	1
1-10	947-0863-02	KNOB ASSY	2	10-18	076-0569-02	PLUG	1
1-11	.990-1009A	SW PWB ASSY(3658B7-77)	1	11	816-3135-55	FLAT WIRE	1
1-12	716-0878-50	SPECIAL SCREW	5	12	816-3105-55	FLAT WIRE	1
1-13	716-0778-52	SPECIAL SCREW	8	13	816-3167-57	FLAT WIRE	1
2	-	*Unused number	-	14	854-4667-52	EXTENSION LEAD	1
2-1	-----	MAIN PWB	1	15	276-1136-81	SETPLATE(for PF3731BA)	1
2-2	076-6021-60	PLUG	1		276-1136-82	SETPLATE(for PF3732BA)	
2-3	074-2248-80	OUTLET SOCKET	1	16	714-2614-8B	MACHINE SCREW	2
2-4	074-1261-00	OUTLET SOCKET	1	17	714-2606-8B	MACHINE SCREW	6
2-5	051-2077-00	IC	1	18	716-0878-50	SPECIAL SCREW	13
2-6	092-2260-00	ANT-RECEPT	1	19	714-2604-8B	MACHINE SCREW	14
2-7	092-2259-00	ANT-RECEPT(for PF3732BA)	1	20	778-3006-51	TAP SCREW	4
2-8	941-0260-01	XM TUNER(for PF3732BA)	1	21	.440-3679A	SD CARD(3679A0-40)	1
2-9	331-5535-04	BRKT-C	1	22	347-9373-00	PAPER PART	1
2-10	778-3006-00	TAP-SCREW	2	23	020-3066-00	DC-MOTOR	1
3	311-2084-11	LOWER CASE	1	24	732-2614-1B	SEMS SCREW	2
4	310-2026-12	UPPER CASE	1	25	290-0919-00	XM LABEL(for PF3732BA)	1
5	309-2002-01	FRONT PLATE	1	26	-----	LABEL (HD certification)(075400-290)	1
6	313-2194-12	HEAT SINK	1	27	290-0548-68	QR CODE LABEL(FR61) (for PF3731BA)	1
7	331-5531-01	PRESSED PART	1		290-0548-69	QR CODE LABEL(FR71) (for PF3732BA)	1
8	929-5400-80	CD-MECH-MODULE	1	28	347-9381-00	PROTECT-SHEET	1
9	347-9449-02	PROTECTOR	1	29	290-0920-00	LABEL(XM) (for PF3732BA)	1
10	.990-1028A	NAVI PWB ASSY(3731A7-78)	1	30	345-6717-00	GASKET(for PF3732BA)	1
10-1	-----	CPU PWB	1	31	347-9492-00	PAPER PART	4
10-2	076-6030-60	PLUG	1	32	-	N/A(LABEL)	-
10-3	074-2248-80	OUTLET SOCKET	1	33	-----	N/A(BSMI LABEL)	-
10-4	076-6023-07	PLUG	1				
10-5	074-1302-28	OUTLET SOCKET	1				
10-6	074-4105-00	OUTLET SOCKET	1				



ELECTRICAL PARTS LIST

MAIN PWB(B1) section : for PF-3731B-A

* Neither the part numbers of parts on which software is written, nor part numbers of parts for which replacement is prohibited in the production process are listed in the parts list.

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
ANT100	092-2260-00	ANT-RECEPT(3P)	C250	046-1042-78	0.1uF K B	C430	043-5600-90	0.10uF
C100	166-1201-50	12pF CH	C251	042-4033-90	6.3V 220uF	C431	168-1042-38	50V 0.1uF K
C102	046-1022-58	50V 1000pF	C252	045-1007-50	10 +/-0.5pF CH	C501	046-1042-78	0.1uF K B
C103	046-1022-58	50V 1000pF	C253	045-1007-50	10 +/-0.5pF CH	C502	165-1073-35	16V 100uF
C104	045-3901-50	39pFJ CH	C254	168-1052-78	16V 1uF K	C505	168-1052-78	16V 1uF K
C105	045-1211-50	120pFJ CH	C255	046-1042-78	0.1uF K B	C506	168-1052-78	16V 1uF K
C106	045-1501-50	15pFJ CH	C256	043-0552-90	6.3V 47uF M	C545	046-6822-58	6800pF K B
C107	045-2211-50	220pFJ CH	C257	046-1042-78	0.1uF K B	C546	046-1042-78	0.1uF K B
C108	046-3922-58	3900pF K B	C258	046-1042-78	0.1uF K B	C547	046-6822-58	6800pF K B
C109	046-1022-58	50V 1000pF	C259	046-1042-78	0.1uF K B	C548	046-1042-78	0.1uF K B
C110	046-1032-78	0.01uF K B	C260	046-1042-78	0.1uF K B	C549	043-0562-90	10V 0.22uF
C111	046-1032-78	0.01uF K B	C261	046-4712-58	470pF K B	C550	043-0602-90	10uF
C112	045-5096-50	5pF +/-0.25pF CH	C262	178-2255-79	2.2uF	C551	043-0562-90	10V 0.22uF
C113	046-3322-58	3300pF K B	C263	178-2255-79	2.2uF	C552	168-1052-78	16V 1uF K
C114	046-2232-78	0.022uF K B	C264	166-2201-50	22pF CH	C553	046-1042-78	0.1uF K B
C115	046-1022-58	50V 1000pF	C265	166-2201-50	22pF CH	C555	046-2222-58	2200pF K B
C116	046-2232-78	0.022uF K B	C269	045-4701-50	47pF CH	C558	046-2222-58	2200pF K B
C117	046-2232-78	0.022uF K B	C270	045-4701-50	47pF CH	C560	046-1042-78	0.1uF K B
C118	046-2232-78	0.022uF K B	C271	045-4701-50	47pF CH	C561	043-7402-90	16V 22uF
C119	046-2232-78	0.022uF K B	C272	045-4701-50	47pF CH	C562	043-7402-90	16V 22uF
C120	043-0562-90	10V 0.22uF	C275	046-1042-78	0.1uF K B	C567	043-7402-90	16V 22uF
C121	046-2232-78	0.022uF K B	C276	046-1042-78	0.1uF K B	C568	043-7402-90	16V 22uF
C122	043-0563-90	16V 47uF	C279	178-2255-79	2.2uF	C573	043-7402-90	16V 22uF
C124	045-2201-50	22pFJ CH	C280	178-2255-79	2.2uF	C574	042-4015-91	25V 470uF
C128	045-2201-50	22pFJ CH	C281	166-2201-50	22pF CH	C575	043-7503-90	4.7uF
C131	045-4796-50	4.7pFJ CH	C282	166-2201-50	22pF CH	C576	043-7503-90	4.7uF
C132	046-1042-78	0.1uF K B	C283	043-6401-90	16V 10uF	C577	043-7503-90	4.7uF
C164	033-0000-05	1/16W 0 ohm	C300	166-2711-50	270pF CH	C579	043-0554-90	25V 10uF
C165	033-0000-05	1/16W 0 ohm	C301	166-2711-50	270pF CH	D100	001-9013-90	BA891
C177	046-1022-58	50V 1000pF	C302	178-2732-78	0.027uF	D101	001-9013-90	BA891
C203	168-4752-98	4.7uF K	C303	178-2732-78	0.027uF	D400	001-2412-90	RR264M-400
C204	168-4752-98	4.7uF K	C304	178-2732-78	0.027uF	D401	001-2403-90	M1F60
C205	046-1042-78	0.1uF K B	C305	178-2732-78	0.027uF	D402	001-2403-90	M1F60
C206	046-1042-78	0.1uF K B	C306	166-5611-50	560pF CH	D503	001-2403-90	M1F60
C207	046-1042-78	0.1uF K B	C307	166-5611-50	560pF CH	D504	001-2403-90	M1F60
C208	046-1042-78	0.1uF K B	C308	166-2201-50	22pF CH	D505	001-2633-90	1SS388-TPL3,F
C209	046-1042-78	0.1uF K B	C309	166-2201-50	22pF CH	D506	001-2633-90	1SS388-TPL3,F
C210	045-8097-50	8pF +/-0.5pF CH	C310	166-2201-50	22pF CH	IC101	-----	TEF7000(Tuner)
C211	045-1007-50	10 +/-0.5pF CH	C311	166-2201-50	22pF CH			(Thermal pad)
C212	046-1042-78	0.1uF K B	C312	166-5611-50	560pF CH			(402590-051)
C214	168-4752-98	4.7uF K	C313	166-5611-50	560pF CH	IC200	-----	SAF7741HV/N127
C216	046-1042-78	0.1uF K B	C314	166-2711-50	270pF CH			(DSP)
C217	168-4752-98	4.7uF K	C315	166-2711-50	270pF CH			(Thermal pad)
C218	046-1042-78	0.1uF K B	C316	168-2242-58	0.22uF K			(674710-051)
C219	046-1042-78	0.1uF K B	C317	168-2242-58	0.22uF K	IC301	051-2077-00	TB2959HQ
C220	046-1042-78	0.1uF K B	C318	168-2242-58	0.22uF K	IC302	051-3034-90	NJM4558V
C221	043-0559-90	6.3V 22uF	C321	042-4007-90	50V 10uF M	IC303	051-3034-90	NJM4558V
C222	168-1052-78	16V 1uF K	C322	168-1052-78	16V 1uF K	IC401	051-5418-08	S-80827CNMC-
C223	046-1042-78	0.1uF K B	C323	043-0574-90	25V 1.0uF			B8M-T2
C224	046-1042-78	0.1uF K B	C328	042-0630-50	16V 100uF	IC402	051-5418-08	S-80827CNMC-
C225	046-1042-78	0.1uF K B	C329	168-1042-78	16V 0.1uF K			B8M-T2
C226	046-1042-78	0.1uF K B	C330	ADZ0292	6.3V 220uF	IC500	-----	BD00C0AWFP
C227	046-1042-78	0.1uF K B	C331	168-2242-58	0.22uF K			(Voltage regulator)
C228	046-1042-78	0.1uF K B	C332	168-1052-78	16V 1uF K			(Thermal pad)
C229	046-1042-78	0.1uF K B	C334	168-2242-58	0.22uF K			(358290-051)
C230	046-3322-58	3300pF K B	C335	046-1042-78	0.1uF K B	IC502	051-3639-90	AP3405DS
C231	046-1022-58	50V 1000pF	C336	046-1042-78	0.1uF K B	IC503	051-3767-90	BD00GC0EEFJ-
C232	042-4015-90	16V 470uF	C400	165-1053-65	50V 1uF			ME2
C233	046-3322-58	3300pF K B	C402	168-2222-55	2200pF K	J680	074-2248-80	80P
C234	046-1022-58	50V 1000pF	C403	168-2222-55	2200pF K	L100	010-2198-62	0.27uH
C235	046-1042-78	0.1uF K B	C404	168-2222-55	2200pF K	L101	010-3406-56	3.3uH J
C236	046-1022-58	50V 1000pF	C405	168-2222-55	2200pF K	L102	010-3406-46	0.47uH J
C237	046-1022-58	50V 1000pF	C406	168-2222-55	2200pF K	L103	010-3439-51	1.8uH
C239	046-1042-78	0.1uF K B	C407	168-2222-55	2200pF K	L104	010-3406-42	0.22uH
C241	046-6812-58	680pF K B	C408	168-2222-55	2200pF K	L105	010-3104-54	600 ohm/100MHz
C242	046-6812-58	680pF K B	C409	168-2222-55	2200pF K	L106	010-2290-52	330uH
C243	046-6812-58	680pF K B	C424	042-4441-10	25V 4700uF	L107	010-2290-52	330uH
C244	046-6812-58	680pF K B	C426	168-1032-55	0.01uF K	L200	010-3105-62	1k ohm/100MHz
C245	046-1042-78	0.1uF K B	C427	165-1063-35	16V 10uF	L201	010-3104-54	600 ohm/100MHz
C247	165-2263-15	6.3V 22uF	C428	043-5600-90	0.10uF	L202	010-3104-54	600 ohm/100MHz
C248	046-4732-78	0.047uF K B	C429	043-5600-90	0.10uF	L203	010-3104-54	600 ohm/100MHz

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
L204	010-3104-54	600 ohm/100MHz	R200	033-1031-15	1/16W 10k ohm J	R433	033-0000-05	1/16W 0 ohm
L205	010-3104-54	600 ohm/100MHz	R201	033-1011-15	1/16W 100 ohm J	R434	032-0221-65	1/16W 68k ohm F
L206	010-3104-54	600 ohm/100MHz	R202	119-2201-15	1/10W 22 ohm	R435	033-0000-05	1/16W 0 ohm
L207	010-3104-54	600 ohm/100MHz	R203	033-1021-15	1/16W 1k ohm J	R436	032-0221-09	1/16W 33k ohm F
L208	119-1001-15	1/10W 10 ohm	R204	033-1011-15	1/16W 100 ohm J	R437	032-0221-53	1/16W 18k ohm F
L209	010-3104-54	600 ohm/100MHz	R205	033-1031-15	1/16W 10k ohm J	R439	116-3321-15	1/4W 3.3k ohm
L210	010-3104-54	600 ohm/100MHz	R206	033-1031-15	1/16W 10k ohm J	R441	116-4721-15	1/4W 4.7k ohm
L211	010-3104-54	600 ohm/100MHz	R207	033-1021-15	1/16W 1k ohm J	R442	033-1031-15	1/16W 10k ohm J
L212	010-3104-54	600 ohm/100MHz	R208	033-1021-15	1/16W 1k ohm J	R535	032-0225-98	1/16W 18k ohm
L213	010-3104-54	600 ohm/100MHz	R209	033-1021-15	1/16W 1k ohm J	R536	032-0225-00	1/16W 150k ohm
L214	010-3104-54	600 ohm/100MHz	R210	033-1021-15	1/16W 1k ohm J	R537	032-0225-67	1/16W 16k ohm
L215	010-3104-54	600 ohm/100MHz	R218	032-0140-89	1/10W 47k ohm F			0.5%
L216	010-3104-54	600 ohm/100MHz	R219	032-0140-89	1/10W 47k ohm F	R538	032-0225-98	1/16W 18k ohm
L217	010-3104-54	600 ohm/100MHz	R220	033-1011-15	1/16W 100 ohm J	R539	033-1041-15	1/16W 100k ohm J
L218	010-3104-54	600 ohm/100MHz	R221	033-1011-15	1/16W 100 ohm J	R540	032-0221-09	1/16W 33k ohm F
L219	010-3104-54	600 ohm/100MHz	R224	032-0140-89	1/10W 47k ohm F	R541	032-0221-83	1/16W 3.3k ohm F
L220	010-3104-54	600 ohm/100MHz	R225	032-0140-89	1/10W 47k ohm F	R542	032-0221-83	1/16W 3.3k ohm F
L221	010-3104-54	600 ohm/100MHz	R226	032-0210-53	1/10W 15k ohm 1%	R543	032-0221-09	1/16W 33k ohm F
L222	010-3105-62	1k ohm/100MHz	R227	032-0210-53	1/10W 15k ohm 1%	R544	033-1041-15	1/16W 100k ohm J
L223	010-3105-62	1k ohm/100MHz	R231	033-0000-05	1/16W 0 ohm	R549	116-4791-15	1/4W 4.7 ohm
L224	010-3103-55	120 ohm/100MHz	R234	033-0000-05	1/16W 0 ohm	R552	116-4791-15	1/4W 4.7 ohm
L225	010-3103-55	120 ohm/100MHz	R235	033-0000-05	1/16W 0 ohm	R553	032-0217-55	1/3W 0.016 ohm
L226	010-3103-55	120 ohm/100MHz	R241	033-1011-15	1/16W 100 ohm J	R554	032-0225-60	1/16W 22k ohm +/-
L227	010-3103-55	120 ohm/100MHz	R243	033-1011-15	1/16W 100 ohm J			0.5%
L301	010-3104-54	600 ohm/100MHz	R245	119-2201-15	1/10W 22 ohm	R555	032-0225-81	1/16W 4.7k ohm
L302	010-3104-54	600 ohm/100MHz	R246	033-1011-15	1/16W 100 ohm J			0.5%
L402	010-2285-82	390 ohm/100MHz	R247	033-1011-15	1/16W 100 ohm J	R556	032-0225-68	1/16W 5.6k ohm +/-
L403	010-8064-00	144uH	R248	033-1011-15	1/16W 100 ohm J			0.5%
L404	010-2285-82	390 ohm/100MHz	R249	033-1011-15	1/16W 100 ohm J	R558	032-0224-50	1/2W 0.008 ohm F
L501	010-3531-52	4.7uH	R250	033-1031-15	1/16W 10k ohm J	R560	032-0221-83	1/16W 3.3k ohm F
L502	010-3531-52	4.7uH	R251	032-0210-53	1/10W 15k ohm 1%	R561	032-0221-34	1/16W 51k ohm F
L503	010-3414-92	2.2uH	R252	032-0210-53	1/10W 15k ohm 1%	R562	032-0221-11	1/16W 5.6k ohm F
L504	010-2285-82	390 ohm/100MHz	R253	119-3311-15	1/10W 330 ohm	R564	033-2711-15	1/16W 270 ohm J
L601	010-3104-50	30 ohm/100MHz	R254	033-0000-05	1/16W 0 ohm	R565	033-2021-15	1/16W 2k ohm
L602	010-3104-50	30 ohm/100MHz	R255	033-0000-05	1/16W 0 ohm	R566	033-2021-15	1/16W 2k ohm
L603	010-3104-50	30 ohm/100MHz	R300	119-1031-15	1/10W 10k ohm	R567	033-2711-15	1/16W 270 ohm J
P400	074-1261-00	OUTLET SOCKET	R301	119-1031-15	1/10W 10k ohm	R572	033-1031-15	1/16W 10k ohm J
P610	076-6021-60	10P	R302	119-1031-15	1/10W 10k ohm	R576	119-3321-15	1/10W 3.3k ohm
Q200	125-7007-90	Si5441BDC-TI-E3	R303	119-1031-15	1/10W 10k ohm	R577	117-1031-15	1/8W 10k ohm
Q404	190-2071-00	2SA2071	R304	119-1031-15	1/10W 10k ohm	R578	116-2221-15	1/4W 2.2k ohm
Q405	192-4081-00	2SC4081	R305	119-1031-15	1/10W 10k ohm	R579	116-2221-15	1/4W 2.2k ohm
Q406	192-4081-00	2SC4081	R306	119-4741-15	1/10W 470k ohm	R581	119-4731-15	1/10W 47k ohm
Q407	190-1586-00	2SA1586 O,Y,G	R307	119-4741-15	1/10W 470k ohm	R582	032-0221-50	1/16W 43k ohm F
Q507	192-4081-00	2SC4081	R308	119-4741-15	1/10W 470k ohm	R583	032-0210-06	1/10W 8.2k ohm F
Q508	125-2027-91	DTC114EUA	R309	119-4741-15	1/10W 470k ohm	R584	033-0000-05	1/16W 0 ohm
Q509	125-2027-91	DTC114EUA	R310	119-1031-15	1/10W 10k ohm	R585	032-0221-07	1/16W 56k ohm F
Q510	125-8044-90	SH8K15GZETB	R311	119-1031-15	1/10W 10k ohm	R587	032-0221-11	1/16W 5.6k ohm F
Q511	125-8044-90	SH8K15GZETB	R312	119-2221-15	1/10W 2.2k ohm	R588	032-0221-11	1/16W 5.6k ohm F
Q513	190-2071-00	2SA2071	R313	119-2221-15	1/10W 2.2k ohm	R616	119-0000-05	1/10W 0 ohm JW
R101	033-1811-15	1/16W 180 ohm J	R314	119-2221-15	1/10W 2.2k ohm	R617	119-0000-05	1/10W 0 ohm JW
R102	033-3311-15	1/16W 330 ohm J	R316	032-0140-50	1/10W 10k ohm F	R618	119-0000-05	1/10W 0 ohm JW
R103	033-4741-15	1/16W 470k ohm J	R317	119-3331-15	1/10W 33k ohm	R619	033-0000-05	1/16W 0 ohm
R104	033-1201-15	1/16W 12 ohm	R322	116-8211-15	1/4W 820 ohm	R620	033-0000-05	1/16W 0 ohm
R105	033-5601-15	1/16W 56 ohm J	R323	116-1021-15	1/4W 1k ohm	R621	033-0000-05	1/16W 0 ohm
R108	033-2231-15	1/16W 22k ohm J	R364	119-2221-15	1/10W 2.2k ohm	RN200	050-0140-51	1/32W 22 ohm x4J
R109	033-3921-15	1/16W 3.9k ohm J	R400	116-4721-15	1/4W 4.7k ohm	T100	010-4100-50	0.215uH
R110	033-0000-05	1/16W 0 ohm	R401	116-5621-15	1/4W 5.6k ohm	TH501	002-0335-50	SMD1812P050TF
R111	033-0000-05	1/16W 0 ohm	R418	116-4721-15	1/4W 4.7k ohm			/30
R113	033-4741-15	1/16W 470k ohm J	R420	116-1831-15	1/4W 18k ohm	X200	061-3589-80	FA-238 41.6MHz
R114	033-1051-15	1/16W 1M ohm J	R421	119-1031-15	1/10W 10k ohm	ZD100	060-8107-50	SURGE
R115	033-1051-15	1/16W 1M ohm J	R422	116-1121-15	1/4W 1.1k ohm			PROTECTOR
R148	033-0000-05	1/16W 0 ohm	R423	119-2721-15	1/10W 2.7k ohm	ZD400	001-4912-90	SM5S22A-HE3/2D
R149	033-0000-05	1/16W 0 ohm	R425	119-5621-15	1/10W 5.6k ohm	ZD401	001-4301-28	HZU5.1B1
R151	033-1811-15	1/16W 180 ohm J	R426	119-1021-15	1/10W 1k ohm	PWB	039-4611-00	PWB(WITHOUT
R152	033-1811-15	1/16W 180 ohm J	R430	032-0221-09	1/16W 33k ohm F			COMPONENTS)
R175	033-0000-05	1/16W 0 ohm	R431	032-0221-09	1/16W 33k ohm F			
R176	033-0000-05	1/16W 0 ohm	R432	032-0221-09	1/16W 33k ohm F			

MAIN PWB(B1) section : for PF-3732B-A

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
ANT100	092-2260-00	ANT-RECEPT(3P)	C251	042-4033-90	6.3V 220uF	C502	165-1073-35	16V 100uF
ANT900	092-2259-00	ANT-RECEPT(1P)	C252	045-1007-50	10 +/-0.5pF CH	C505	168-1052-78	16V 1uF K
C100	166-1201-50	12pF CH	C253	045-1007-50	10 +/-0.5pF CH	C506	168-1052-78	16V 1uF K
C102	046-1022-58	50V 1000pF	C254	168-1052-78	16V 1uF K	C545	046-6822-58	6800pF K B
C103	046-1022-58	50V 1000pF	C255	046-1042-78	0.1uF K B	C546	046-1042-78	0.1uF K B
C104	045-3901-50	39pFJ CH	C256	043-0552-90	6.3V 47uF M	C547	046-6822-58	6800pF K B
C105	045-1211-50	120pFJ CH	C257	046-1042-78	0.1uF K B	C548	046-1042-78	0.1uF K B
C106	045-1501-50	15pFJ CH	C258	046-1042-78	0.1uF K B	C549	043-0562-90	10V 0.22uF
C107	045-2211-50	220pFJ CH	C259	046-1042-78	0.1uF K B	C550	043-0602-90	10uF
C108	046-3922-58	3900pF K B	C260	046-1042-78	0.1uF K B	C551	043-0562-90	10V 0.22uF
C109	046-1022-58	50V 1000pF	C261	046-4712-58	470pF K B	C552	168-1052-78	16V 1uF K
C110	046-1032-78	0.01uF K B	C262	178-2255-79	2.2uF	C553	046-1042-78	0.1uF K B
C111	046-1032-78	0.01uF K B	C263	178-2255-79	2.2uF	C555	046-2222-58	2200pF K B
C112	045-5096-50	5pF +/-0.25pF CH	C264	166-2201-50	22pF CH	C558	046-2222-58	2200pF K B
C113	046-3322-58	3300pF K B	C265	166-2201-50	22pF CH	C560	046-1042-78	0.1uF K B
C114	046-2232-78	0.022uF K B	C269	045-4701-50	47pF CH	C561	043-7402-90	16V 22uF
C115	046-1022-58	50V 1000pF	C270	045-4701-50	47pF CH	C562	043-7402-90	16V 22uF
C116	046-2232-78	0.022uF K B	C271	045-4701-50	47pF CH	C567	043-7402-90	16V 22uF
C117	046-2232-78	0.022uF K B	C272	045-4701-50	47pF CH	C568	043-7402-90	16V 22uF
C118	046-2232-78	0.022uF K B	C275	046-1042-78	0.1uF K B	C573	043-7402-90	16V 22uF
C119	046-2232-78	0.022uF K B	C276	046-1042-78	0.1uF K B	C574	042-4015-91	25V 470uF
C120	043-0562-90	10V 0.22uF	C279	178-2255-79	2.2uF	C575	043-7503-90	4.7uF
C121	046-2232-78	0.022uF K B	C280	178-2255-79	2.2uF	C576	043-7503-90	4.7uF
C122	043-0563-90	16V 47uF	C281	166-2201-50	22pF CH	C577	043-7503-90	4.7uF
C124	045-2201-50	22pFJ CH	C282	166-2201-50	22pF CH	C579	043-0554-90	25V 10uF
C128	045-2201-50	22pFJ CH	C283	043-6401-90	16V 10uF	C901	046-1022-58	50V 1000pF
C131	045-4796-50	4.7pFJ CH	C300	166-2711-50	270pF CH	C902	046-1022-58	50V 1000pF
C132	046-1042-78	0.1uF K B	C301	166-2711-50	270pF CH	C903	046-1022-58	50V 1000pF
C164	033-0000-05	1/16W 0 ohm	C302	178-2732-78	0.027uF	C905	043-5703-90	50V 0.001uF
C165	033-0000-05	1/16W 0 ohm	C303	178-2732-78	0.027uF	C906	043-7701-90	2.2uF
C177	046-1022-58	50V 1000pF	C304	178-2732-78	0.027uF	C907	042-4025-90	16V 47uF
C203	168-4752-98	4.7uF K	C305	178-2732-78	0.027uF	C909	046-1042-78	0.1uF K B
C204	168-4752-98	4.7uF K	C306	166-5611-50	560pF CH	C910	046-1042-78	0.1uF K B
C205	046-1042-78	0.1uF K B	C307	166-5611-50	560pF CH	C911	046-1022-58	50V 1000pF
C206	046-1042-78	0.1uF K B	C308	166-2201-50	22pF CH	C912	046-1022-58	50V 1000pF
C207	046-1042-78	0.1uF K B	C309	166-2201-50	22pF CH	C916	045-1011-50	100pFJ CH
C208	046-1042-78	0.1uF K B	C310	166-2201-50	22pF CH	C917	045-1801-50	18pFJ CH
C209	046-1042-78	0.1uF K B	C311	166-2201-50	22pF CH	C918	045-1801-50	18pFJ CH
C210	045-8097-50	8pF +/-0.5pF CH	C312	166-5611-50	560pF CH	C923	043-4306-90	1uF
C211	045-1007-50	10 +/-0.5pF CH	C313	166-5611-50	560pF CH	C924	168-1052-78	16V 1uF K
C212	046-1042-78	0.1uF K B	C314	166-2711-50	270pF CH	C927	046-1022-58	50V 1000pF
C214	168-4752-98	4.7uF K	C315	166-2711-50	270pF CH	C928	046-1022-58	50V 1000pF
C216	046-1042-78	0.1uF K B	C316	168-2242-58	0.22uF K	D100	001-9013-90	BA891
C217	168-4752-98	4.7uF K	C317	168-2242-58	0.22uF K	D101	001-9013-90	BA891
C218	046-1042-78	0.1uF K B	C318	168-2242-58	0.22uF K	D400	001-2412-90	RR264M-400
C219	046-1042-78	0.1uF K B	C321	042-4007-90	50V 10uF M	D401	001-2403-90	M1F60
C220	046-1042-78	0.1uF K B	C322	168-1052-78	16V 1uF K	D402	001-2403-90	M1F60
C221	043-0559-90	6.3V 22uF	C323	043-0574-90	25V 1.0uF	D503	001-2403-90	M1F60
C222	168-1052-78	16V 1uF K	C328	042-0630-50	16V 100uF	D504	001-2403-90	M1F60
C223	046-1042-78	0.1uF K B	C329	168-1042-78	16V 0.1uF K	D505	001-2633-90	1SS388-TPL3,F
C224	046-1042-78	0.1uF K B	C330	ADZ0292	6.3V 220uF	D506	001-2633-90	1SS388-TPL3,F
C225	046-1042-78	0.1uF K B	C331	168-2242-58	0.22uF K	FE900	941-0260-01	TUNER PACK
C226	046-1042-78	0.1uF K B	C332	168-1052-78	16V 1uF K	IC101	-----	TEF7000(Tuner)
C227	046-1042-78	0.1uF K B	C334	168-2242-58	0.22uF K			(Thermal pad)
C228	046-1042-78	0.1uF K B	C335	046-1042-78	0.1uF K B			(402590-051)
C229	046-1042-78	0.1uF K B	C336	046-1042-78	0.1uF K B	IC200	-----	SAF7741HV/N127
C230	046-3322-58	3300pF K B	C400	165-1053-65	50V 1uF			(DSP)
C231	046-1022-58	50V 1000pF	C402	168-2222-55	2200pF K			(Thermal pad)
C232	042-4015-90	16V 470uF	C403	168-2222-55	2200pF K			(674710-051)
C233	046-3322-58	3300pF K B	C404	168-2222-55	2200pF K	IC301	051-2077-00	TB2959HQ
C234	046-1022-58	50V 1000pF	C405	168-2222-55	2200pF K	IC302	051-3034-90	NJM4558V
C235	046-1042-78	0.1uF K B	C406	168-2222-55	2200pF K	IC303	051-3034-90	NJM4558V
C236	046-1022-58	50V 1000pF	C407	168-2222-55	2200pF K	IC401	051-5418-08	S-80827CNMC-
C237	046-1022-58	50V 1000pF	C408	168-2222-55	2200pF K			B8M-T2
C239	046-1042-78	0.1uF K B	C409	168-2222-55	2200pF K	IC402	051-5418-08	S-80827CNMC-
C241	046-6812-58	680pF K B	C424	042-4441-10	25V 4700uF			B8M-T2
C242	046-6812-58	680pF K B	C426	168-1032-55	0.01uF K	IC500	-----	BD00COAWFP
C243	046-6812-58	680pF K B	C427	165-1063-35	16V 10uF			(Voltage regulator)
C244	046-6812-58	680pF K B	C428	043-5600-90	0.10uF			(Thermal pad)
C245	046-1042-78	0.1uF K B	C429	043-5600-90	0.10uF			(358290-051)
C247	165-2263-15	6.3V 22uF	C430	043-5600-90	0.10uF	IC502	051-3639-90	AP3405DS
C248	046-4732-78	0.047uF K B	C431	168-1042-38	50V 0.1uF K	IC503	051-3767-90	BD00GC0EEFJ-
C250	046-1042-78	0.1uF K B	C501	046-1042-78	0.1uF K B			ME2

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
IC900	051-3374-90	NJM2386ADL3-05-TE1	R110	033-0000-05	1/16W 0 ohm	R430	032-0221-09	1/16W 33k ohm F
IC901	051-3764-90	BD00HA5EEFJ-ME2	R111	033-0000-05	1/16W 0 ohm	R431	032-0221-09	1/16W 33k ohm F
J680	074-2248-80	80P	R113	033-4741-15	1/16W 470k ohm J	R432	032-0221-09	1/16W 33k ohm F
L100	010-2198-62	0.27uH	R114	033-1051-15	1/16W 1M ohm J	R433	033-0000-05	1/16W 0 ohm
L101	010-3406-56	3.3uH J	R115	033-1051-15	1/16W 1M ohm J	R434	032-0221-65	1/16W 68k ohm F
L102	010-3406-46	0.47uH J	R148	033-0000-05	1/16W 0 ohm	R435	033-0000-05	1/16W 0 ohm
L103	010-3439-51	1.8uH	R149	033-0000-05	1/16W 0 ohm	R436	032-0221-09	1/16W 33k ohm F
L104	010-3406-42	0.22uH	R151	033-1811-15	1/16W 180 ohm J	R437	032-0221-53	1/16W 18k ohm F
L105	010-3104-54	600 ohm/100MHz	R152	033-1811-15	1/16W 180 ohm J	R439	116-3321-15	1/4W 3.3k ohm
L106	010-2290-52	330uH	R175	033-0000-05	1/16W 0 ohm	R441	116-4721-15	1/4W 4.7k ohm
L107	010-2290-52	330uH	R176	033-0000-05	1/16W 0 ohm	R442	033-1031-15	1/16W 10k ohm J
L200	010-3105-62	1k ohm/100MHz	R200	033-1031-15	1/16W 10k ohm J	R535	032-0225-98	1/16W 18k ohm
L201	010-3104-54	600 ohm/100MHz	R201	033-1011-15	1/16W 100 ohm J	R536	032-0225-00	1/16W 150k ohm
L202	010-3104-54	600 ohm/100MHz	R202	119-2201-15	1/10W 22 ohm	R537	032-0225-67	1/16W 16k ohm 0.5%
L203	010-3104-54	600 ohm/100MHz	R203	033-1021-15	1/16W 1k ohm J	R538	032-0225-98	1/16W 18k ohm
L204	010-3104-54	600 ohm/100MHz	R204	033-1011-15	1/16W 100 ohm J	R539	033-1041-15	1/16W 100k ohm J
L205	010-3104-54	600 ohm/100MHz	R205	033-1031-15	1/16W 10k ohm J	R540	032-0221-09	1/16W 33k ohm F
L206	010-3104-54	600 ohm/100MHz	R206	033-1031-15	1/16W 10k ohm J	R541	032-0221-83	1/16W 3.3k ohm F
L207	010-3104-54	600 ohm/100MHz	R207	033-1021-15	1/16W 1k ohm J	R542	032-0221-83	1/16W 3.3k ohm F
L208	119-1001-15	1/10W 10 ohm	R208	033-1021-15	1/16W 1k ohm J	R543	032-0221-09	1/16W 33k ohm F
L209	010-3104-54	600 ohm/100MHz	R209	033-1021-15	1/16W 1k ohm J	R544	033-1041-15	1/16W 100k ohm J
L210	010-3104-54	600 ohm/100MHz	R210	033-1021-15	1/16W 1k ohm J	R549	116-4791-15	1/4W 4.7 ohm
L211	010-3104-54	600 ohm/100MHz	R218	032-0140-89	1/10W 47k ohm F	R552	116-4791-15	1/4W 4.7 ohm
L212	010-3104-54	600 ohm/100MHz	R219	032-0140-89	1/10W 47k ohm F	R553	032-0217-55	1/3W 0.016 ohm
L213	010-3104-54	600 ohm/100MHz	R220	033-1011-15	1/16W 100 ohm J	R554	032-0225-60	1/16W 22k ohm +/- 0.5%
L214	010-3104-54	600 ohm/100MHz	R221	033-1011-15	1/16W 100 ohm J	R555	032-0225-81	1/16W 4.7k ohm 0.5%
L215	010-3104-54	600 ohm/100MHz	R224	032-0140-89	1/10W 47k ohm F	R556	032-0225-68	1/16W 5.6k ohm +/- 0.5%
L216	010-3104-54	600 ohm/100MHz	R225	032-0140-89	1/10W 47k ohm F	R558	032-0224-50	1/2W 0.008 ohm F
L217	010-3104-54	600 ohm/100MHz	R226	032-0210-53	1/10W 15k ohm 1%	R560	032-0221-83	1/16W 3.3k ohm F
L218	010-3104-54	600 ohm/100MHz	R227	032-0210-53	1/10W 15k ohm 1%	R561	032-0221-34	1/16W 51k ohm F
L219	010-3104-54	600 ohm/100MHz	R231	033-0000-05	1/16W 0 ohm	R562	032-0221-11	1/16W 5.6k ohm F
L220	010-3104-54	600 ohm/100MHz	R234	033-0000-05	1/16W 0 ohm	R564	033-2711-15	1/16W 270 ohm J
L221	010-3104-54	600 ohm/100MHz	R235	033-0000-05	1/16W 0 ohm	R565	033-2021-15	1/16W 2k ohm
L222	010-3105-62	1k ohm/100MHz	R241	033-1011-15	1/16W 100 ohm J	R566	033-2021-15	1/16W 2k ohm
L223	010-3105-62	1k ohm/100MHz	R243	033-1011-15	1/16W 100 ohm J	R567	033-2711-15	1/16W 270 ohm J
L224	010-3103-55	120 ohm/100MHz	R245	119-2201-15	1/10W 22 ohm	R572	033-1031-15	1/16W 10k ohm J
L225	010-3103-55	120 ohm/100MHz	R246	033-1011-15	1/16W 100 ohm J	R576	119-3321-15	1/10W 3.3k ohm
L226	010-3103-55	120 ohm/100MHz	R247	033-1011-15	1/16W 100 ohm J	R577	117-1031-15	1/8W 10k ohm
L227	010-3103-55	120 ohm/100MHz	R248	033-1011-15	1/16W 100 ohm J	R578	116-2221-15	1/4W 2.2k ohm
L301	010-3104-54	600 ohm/100MHz	R249	033-1011-15	1/16W 100 ohm J	R579	116-2221-15	1/4W 2.2k ohm
L302	010-3104-54	600 ohm/100MHz	R250	033-1031-15	1/16W 10k ohm J	R581	119-4731-15	1/10W 47k ohm
L402	010-2285-82	390 ohm/100MHz	R251	032-0210-53	1/10W 15k ohm 1%	R582	032-0221-50	1/16W 43k ohm F
L403	010-8064-00	144uH	R252	032-0210-53	1/10W 15k ohm 1%	R583	032-0210-06	1/10W 8.2k ohm F
L404	010-2285-82	390 ohm/100MHz	R253	119-3311-15	1/10W 330 ohm	R584	033-0000-05	1/16W 0 ohm
L501	010-3531-52	4.7uH	R254	033-0000-05	1/16W 0 ohm	R585	032-0221-07	1/16W 56k ohm F
L502	010-3531-52	4.7uH	R255	033-0000-05	1/16W 0 ohm	R587	032-0221-11	1/16W 5.6k ohm F
L503	010-3414-92	2.2uH	R300	119-1031-15	1/10W 10k ohm	R588	032-0221-11	1/16W 5.6k ohm F
L504	010-2285-82	390 ohm/100MHz	R301	119-1031-15	1/10W 10k ohm	R616	119-0000-05	1/10W 0 ohm JW
L601	010-3104-50	30 ohm/100MHz	R302	119-1031-15	1/10W 10k ohm	R617	119-0000-05	1/10W 0 ohm JW
L602	010-3104-50	30 ohm/100MHz	R303	119-1031-15	1/10W 10k ohm	R618	119-0000-05	1/10W 0 ohm JW
L603	010-3104-50	30 ohm/100MHz	R304	119-1031-15	1/10W 10k ohm	R619	033-0000-05	1/16W 0 ohm
L902	010-3104-53	220 ohm/100MHz	R305	119-1031-15	1/10W 10k ohm	R620	033-0000-05	1/16W 0 ohm
L904	010-3104-53	220 ohm/100MHz	R306	119-4741-15	1/10W 470k ohm	R621	033-0000-05	1/16W 0 ohm
P400	074-1261-00	OUTLET SOCKET	R307	119-4741-15	1/10W 470k ohm	R905	032-0162-50	1/10W 0.51 ohm
P610	076-6021-60	10P	R308	119-4741-15	1/10W 470k ohm	R910	033-3311-15	1/16W 330 ohm J
Q200	125-7007-90	Si5441BDC-TI-E3	R309	119-4741-15	1/10W 470k ohm	R913	033-1021-15	1/16W 1k ohm J
Q404	190-2071-00	2SA2071	R310	119-1031-15	1/10W 10k ohm	R915	033-1021-15	1/16W 1k ohm J
Q405	192-4081-00	2SC4081	R311	119-1031-15	1/10W 10k ohm	R918	033-1021-15	1/16W 1k ohm J
Q406	192-4081-00	2SC4081	R312	119-2221-15	1/10W 2.2k ohm	R921	033-1021-15	1/16W 1k ohm J
Q407	190-1586-00	2SA1586 O,Y,G	R313	119-2221-15	1/10W 2.2k ohm	R923	033-0000-05	1/16W 0 ohm
Q507	192-4081-00	2SC4081	R314	119-2221-15	1/10W 2.2k ohm	R924	033-3301-15	1/16W 33 ohm J
Q508	125-2027-91	DTC114EUA	R316	032-0140-50	1/10W 10k ohm F	R925	033-3301-15	1/16W 33 ohm J
Q509	125-2027-91	DTC114EUA	R317	119-3331-15	1/10W 33k ohm	R926	033-1011-15	1/16W 100 ohm J
Q510	125-8044-90	SH8K15GZETB	R322	116-8211-15	1/4W 820 ohm	R930	033-0000-05	1/16W 0 ohm
Q511	125-8044-90	SH8K15GZETB	R323	116-1021-15	1/4W 1k ohm	R931	032-0221-50	1/16W 43k ohm F
Q513	190-2071-00	2SA2071	R364	119-2221-15	1/10W 2.2k ohm	R932	032-0210-06	1/10W 8.2k ohm F
R101	033-1811-15	1/16W 180 ohm J	R400	116-4721-15	1/4W 4.7k ohm	R933	033-0000-05	1/16W 0 ohm
R102	033-3311-15	1/16W 330 ohm J	R401	116-5621-15	1/4W 5.6k ohm	R934	119-0000-05	1/10W 0 ohm JW
R103	033-4741-15	1/16W 470k ohm J	R418	116-4721-15	1/4W 4.7k ohm	R935	119-0000-05	1/10W 0 ohm JW
R104	033-1201-15	1/16W 12 ohm	R420	116-1831-15	1/4W 18k ohm	RN200	050-0140-51	1/32W 22 ohm x4J
R105	033-5601-15	1/16W 56 ohm J	R421	119-1031-15	1/10W 10k ohm	T100	010-4100-50	0.215uH
R108	033-2231-15	1/16W 22k ohm J	R422	116-1121-15	1/4W 1.1k ohm			
R109	033-3921-15	1/16W 3.9k ohm J	R423	119-2721-15	1/10W 2.7k ohm			
			R425	119-5621-15	1/10W 5.6k ohm			
			R426	119-1021-15	1/10W 1k ohm			

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
TH501	002-0335-50	SMD1812P050TF /30	ZD100	060-8107-50	SURGE PROTECTOR	ZD401	001-4301-28	HZU5.1B1
X200	061-3589-80	FA-238 41.6MHz	ZD400	001-4912-90	SM5S22A-HE3/2D	PWB	039-4611-00	PWB(WITHOUT COMPONENTS)

SW PWB(B2) section

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
D1300	001-7141-90	VFHR1111C- 4BY2A-TR RED	D1318	001-7141-90	VFHR1111C- 4BY2A-TR RED	R109	032-0210-75	1/10W 820 ohm F
D1301	001-7141-90	VFHR1111C- 4BY2A-TR RED	D1319	001-7141-90	VFHR1111C- 4BY2A-TR RED	R110	119-0000-05	1/10W 0 ohm JW
D1302	001-7141-90	VFHR1111C- 4BY2A-TR RED	D1320	001-7141-90	VFHR1111C- 4BY2A-TR RED	R111	119-0000-05	1/10W 0 ohm JW
D1303	001-7141-90	VFHR1111C- 4BY2A-TR RED	D1321	001-7141-90	VFHR1111C- 4BY2A-TR RED	R112	119-0000-05	1/10W 0 ohm JW
D1304	001-7141-90	VFHR1111C- 4BY2A-TR RED	D1322	001-7141-90	VFHR1111C- 4BY2A-TR RED	R113	119-0000-05	1/10W 0 ohm JW
D1305	001-7141-90	VFHR1111C- 4BY2A-TR RED	J101	074-2248-30	30P	R114	032-0210-75	1/10W 820 ohm F
D1306	001-7141-90	VFHR1111C- 4BY2A-TR RED	J102	074-2240-60	10P	R115	032-0210-51	1/10W 750 ohm F
D1307	001-7141-90	VFHR1111C- 4BY2A-TR RED	R100	032-0210-55	1/10W 2.2k ohm F	R116	032-0210-75	1/10W 820 ohm F
D1316	001-7109-92	SML-311UTT86 RED	R101	032-0210-55	1/10W 2.2k ohm F	R117	032-0210-51	1/10W 750 ohm F
D1317	001-7109-92	SML-311UTT86 RED	R102	032-0210-55	1/10W 2.2k ohm F	R118	032-0221-55	1/16W 1.5k ohm F
			R103	032-0210-55	1/10W 2.2k ohm F	R119	032-0210-51	1/10W 750 ohm F
			R104	032-0221-55	1/16W 1.5k ohm F	SW100	016-0018-37	VR W/SHAFT
			R105	032-0210-75	1/10W 820 ohm F	SW101	016-0018-37	VR W/SHAFT
			R106	032-0210-75	1/10W 820 ohm F	SW102	013-6201-53	SKPMAPE010
			R107	032-0210-75	1/10W 820 ohm F	SW103	013-6201-53	SKPMAPE010
			R108	032-0210-75	1/10W 820 ohm F	SW104	013-6201-53	SKPMAPE010
						SW105	013-6201-53	SKPMAPE010
						SW106	013-6202-52	SKPMBJE010
						PWB	039-4282-00	PWB(WITHOUT COMPONENTS)

△

NAVI PWB(B3) section

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
C103	046-1042-78	0.1uF K B	C150	046-1042-78	0.1uF K B	C331	046-1042-78	0.1uF K B
C104	043-0577-90	6.3V 1.0uF	C151	046-1042-78	0.1uF K B	C332	046-1042-78	0.1uF K B
C106	046-1022-58	50V 1000pF	C152	046-1042-78	0.1uF K B	C333	046-1042-78	0.1uF K B
C109	046-1042-78	0.1uF K B	C153	046-1042-78	0.1uF K B	C334	046-1042-78	0.1uF K B
C110	046-1042-78	0.1uF K B	C154	046-1042-78	0.1uF K B	C335	046-1042-78	0.1uF K B
C111	046-1042-78	0.1uF K B	C201	046-1022-58	50V 1000pF	C336	046-1042-78	0.1uF K B
C112	046-1042-78	0.1uF K B	C202	046-1042-78	0.1uF K B	C337	046-1042-78	0.1uF K B
C113	046-1042-78	0.1uF K B	C203	046-1042-78	0.1uF K B	C338	043-0577-90	6.3V 1.0uF
C114	046-1022-58	50V 1000pF	C204	045-1201-50	12pFJ CH	C339	043-0577-90	6.3V 1.0uF
C115	046-1042-78	0.1uF K B	C205	045-1201-50	12pFJ CH	C340	043-0577-90	6.3V 1.0uF
C116	046-1022-58	50V 1000pF	C206	045-6097-50	6pF +/-0.5pF CH	C341	046-1042-78	0.1uF K B
C117	046-1042-78	0.1uF K B	C207	045-6097-50	6pF +/-0.5pF CH	C342	046-1042-78	0.1uF K B
C118	046-1042-78	0.1uF K B	C219	046-1042-78	0.1uF K B	C343	046-1042-78	0.1uF K B
C119	046-1042-78	0.1uF K B	C220	046-1022-58	50V 1000pF	C344	046-1042-78	0.1uF K B
C120	046-1042-78	0.1uF K B	C221	046-1042-78	0.1uF K B	C345	046-1042-78	0.1uF K B
C121	046-1042-78	0.1uF K B	C222	046-1022-58	50V 1000pF	C346	046-1042-78	0.1uF K B
C122	046-1042-78	0.1uF K B	C223	046-1042-78	0.1uF K B	C347	046-1042-78	0.1uF K B
C123	046-1042-78	0.1uF K B	C224	046-1022-58	50V 1000pF	C348	046-1042-78	0.1uF K B
C124	046-1022-58	50V 1000pF	C226	045-1501-50	15pFJ CH	C349	046-1042-78	0.1uF K B
C125	046-1022-58	50V 1000pF	C228	046-1042-78	0.1uF K B	C350	046-1042-78	0.1uF K B
C126	046-1042-78	0.1uF K B	C233	043-0587-90	50V 18pF	C351	046-1042-78	0.1uF K B
C127	046-1042-78	0.1uF K B	C301	046-1032-78	0.01uF K B	C352	046-1042-78	0.1uF K B
C128	046-1042-78	0.1uF K B	C302	043-6200-90	6.3V 10uF	C353	046-1042-78	0.1uF K B
C129	046-1042-78	0.1uF K B	C303	043-6200-90	6.3V 10uF	C354	046-1042-78	0.1uF K B
C130	046-1042-78	0.1uF K B	C304	043-0577-90	6.3V 1.0uF	C355	046-1042-78	0.1uF K B
C131	046-1042-78	0.1uF K B	C305	043-0577-90	6.3V 1.0uF	C356	046-1042-78	0.1uF K B
C132	046-1042-78	0.1uF K B	C306	046-1042-78	0.1uF K B	C357	046-1042-78	0.1uF K B
C133	046-1042-78	0.1uF K B	C308	046-1042-78	0.1uF K B	C358	046-1042-78	0.1uF K B
C134	046-1042-78	0.1uF K B	C309	046-1042-78	0.1uF K B	C359	046-1042-78	0.1uF K B
C135	046-1042-78	0.1uF K B	C311	046-1042-78	0.1uF K B	C360	046-1042-78	0.1uF K B
C136	046-1042-78	0.1uF K B	C312	046-1042-78	0.1uF K B	C361	046-1042-78	0.1uF K B
C137	046-1042-78	0.1uF K B	C313	046-1042-78	0.1uF K B	C362	046-1042-78	0.1uF K B
C138	046-1022-58	50V 1000pF	C314	046-1042-78	0.1uF K B	C363	046-1042-78	0.1uF K B
C139	046-1022-58	50V 1000pF	C315	046-1042-78	0.1uF K B	C364	046-1042-78	0.1uF K B
C140	046-1042-78	0.1uF K B	C317	046-1042-78	0.1uF K B	C365	046-1042-78	0.1uF K B
C141	046-1042-78	0.1uF K B	C318	046-1042-78	0.1uF K B	C366	046-1042-78	0.1uF K B
C142	046-1042-78	0.1uF K B	C320	046-1042-78	0.1uF K B	C367	046-1042-78	0.1uF K B
C143	046-1042-78	0.1uF K B	C323	046-1042-78	0.1uF K B	C368	046-1042-78	0.1uF K B
C144	046-1042-78	0.1uF K B	C324	046-1042-78	0.1uF K B	C369	046-1042-78	0.1uF K B
C145	046-1042-78	0.1uF K B	C326	046-1042-78	0.1uF K B	C370	046-1042-78	0.1uF K B
C146	046-1042-78	0.1uF K B	C327	046-1042-78	0.1uF K B	C371	046-1042-78	0.1uF K B
C147	046-1022-58	50V 1000pF	C328	046-1042-78	0.1uF K B	C372	178-1062-88	10uF
C148	046-1042-78	0.1uF K B	C329	046-1042-78	0.1uF K B	C373	046-1042-78	0.1uF K B
C149	046-1022-58	50V 1000pF	C330	046-1042-78	0.1uF K B	C374	043-7201-90	6.3V 100uF

REF NO.	PART NO.	DESCRIPTION
C375	046-1042-78	0.1uF K B
C376	046-1032-78	0.01uF K B
C377	046-1022-58	50V 1000pF
C378	046-1022-58	50V 1000pF
C379	046-1042-78	0.1uF K B
C380	046-1042-78	0.1uF K B
C381	046-1042-78	0.1uF K B
C382	046-1042-78	0.1uF K B
C383	046-1042-78	0.1uF K B
C384	046-1042-78	0.1uF K B
C385	046-1032-78	0.01uF K B
C386	046-1042-78	0.1uF K B
C387	043-0577-90	6.3V 1.0uF
C388	046-1032-78	0.01uF K B
C389	046-1032-78	0.01uF K B
C390	046-1032-78	0.01uF K B
C413	046-1042-78	0.1uF K B
C501	046-1032-78	0.01uF K B
C502	178-1062-88	10uF
C503	046-1032-78	0.01uF K B
C505	046-3332-78	0.033uF K B
C506	046-1032-78	0.01uF K B
C507	046-1042-78	0.1uF K B
C508	046-1042-78	0.1uF K B
C509	043-6200-90	6.3V 10uF
C510	046-1032-78	0.01uF K B
C511	046-1042-78	0.1uF K B
C514	043-6200-90	6.3V 10uF
C516	045-1007-50	10 +/-0.5pF CH
C517	045-1007-50	10 +/-0.5pF CH
C518	046-1032-78	0.01uF K B
C520	045-5096-50	5pF +/-0.25pF CH
C620	046-1042-78	0.1uF K B
C621	046-1042-78	0.1uF K B
C622	043-7402-90	16V 22uF
C623	046-1042-78	0.1uF K B
C627	043-6400-90	16V 4.7uF K
C628	043-6200-90	6.3V 10uF
C629	046-1042-78	0.1uF K B
C630	046-1042-78	0.1uF K B
C632	168-1052-78	16V 1uF K
C633	168-1052-78	16V 1uF K
C701	045-8097-50	8pF +/-0.5pF CH
C702	045-8097-50	8pF +/-0.5pF CH
C703	046-1032-78	0.01uF K B
C705	042-4033-90	6.3V 220uF
C706	046-1042-78	0.1uF K B
C707	046-1042-78	0.1uF K B
C708	046-1042-78	0.1uF K B
C709	046-1042-78	0.1uF K B
C710	168-4752-98	4.7uF K
C711	046-1042-78	0.1uF K B
C715	178-1232-78	0.012uF
C716	046-1042-78	0.1uF K B
C801	178-1062-88	10uF
C802	046-2232-78	0.022uF K B
C806	046-1042-78	0.1uF K B
C807	043-0548-50	10V 2.2uF
C808	046-1022-58	50V 1000pF
C809	178-1062-88	10uF
C810	046-2222-58	2200pF K B
C811	046-6822-58	6800pF K B
C812	046-1042-78	0.1uF K B
C814	046-1042-78	0.1uF K B
C815	178-1062-88	10uF
C816	046-1042-78	0.1uF K B
C817	046-3332-78	0.033uF K B
C818	046-1042-78	0.1uF K B
C819	178-1062-88	10uF
C820	043-0605-90	10V 2.2uF
C821	043-0577-90	6.3V 1.0uF
C822	046-1042-78	0.1uF K B
C823	178-1062-88	10uF
C830	045-2201-50	22pFJ CH
C833	178-1062-88	10uF

REF NO.	PART NO.	DESCRIPTION
C902	046-1042-78	0.1uF K B
C903	168-1042-38	50V 0.1uF K
C912	168-1042-38	50V 0.1uF K
C1002	168-1032-55	0.01uF K
C1004	178-1062-88	10uF
C1008	046-1032-78	0.01uF K B
C1015	046-1042-78	0.1uF K B
C1016	046-1042-78	0.1uF K B
C1017	043-6404-90	16V 10uF
C1018	043-7200-90	6.3V 47uF
C1020	046-1042-78	0.1uF K B
C1021	046-1042-78	0.1uF K B
C1022	046-1042-78	0.1uF K B
C1023	046-1042-78	0.1uF K B
C1118	166-6097-50	6pF +/-0.5pF CH
C1121	166-6097-50	6pF +/-0.5pF CH
C1123	046-3322-58	3300pF K B
C1124	046-3322-58	3300pF K B
C1125	046-3322-58	3300pF K B
C1126	046-1042-78	0.1uF K B
C1135	045-1011-50	100pFJ CH
C1136	045-1007-50	10 +/-0.5pF CH
C1137	045-1007-50	10 +/-0.5pF CH
C1140	043-6404-90	16V 10uF
C1141	046-1022-58	50V 1000pF
C1143	168-1042-38	50V 0.1uF K
C1144	168-3342-58	0.33uF K
C1145	168-1042-38	50V 0.1uF K
C1146	168-1042-38	50V 0.1uF K
C1147	046-1022-58	50V 1000pF
C1148	046-1022-58	50V 1000pF
C1149	168-1042-38	50V 0.1uF K
C1150	168-1042-38	50V 0.1uF K
C1153	046-1042-78	0.1uF K B
C1161	168-1042-38	50V 0.1uF K
C1165	043-6404-90	16V 10uF
C1166	046-3322-58	3300pF K B
C1167	043-7402-90	16V 22uF
C1201	043-5600-90	0.10uF
C1202	043-7402-90	16V 22uF
C1203	043-0559-90	6.3V 22uF
C1204	043-7402-90	16V 22uF
C1205	046-1042-78	0.1uF K B
C1206	046-1042-78	0.1uF K B
C1209	046-1042-78	0.1uF K B
C1210	178-1062-88	10uF
C1211	043-7402-90	16V 22uF
C1213	168-1052-78	16V 1uF K
C1215	043-0566-90	50V 2.2uF K
C1216	043-0566-90	50V 2.2uF K
C1218	043-0559-90	6.3V 22uF
C1219	043-0559-90	6.3V 22uF
C1223	043-0559-90	6.3V 22uF
C1226	043-6404-90	16V 10uF
C1244	046-3332-78	0.033uF K B
C1245	046-1045-59	0.1uF Z F
C1249	168-1052-78	16V 1uF K
C1250	043-6404-90	16V 10uF
C1265	046-1042-78	0.1uF K B
C1266	168-1052-78	16V 1uF K
C1268	AAZ0264	16V 1uF
C1272	046-1042-78	0.1uF K B
C1273	168-1052-78	16V 1uF K
C1275	168-1052-78	16V 1uF K
C1276	168-1052-78	16V 1uF K
C1313	046-1022-58	50V 1000pF
C1314	043-0554-90	25V 10uF
C1315	046-1022-58	50V 1000pF
C1316	043-0554-90	25V 10uF
C1317	168-1052-78	16V 1uF K
C1318	043-0554-90	25V 10uF
C1319	046-1022-58	50V 1000pF
C1320	043-0554-90	25V 10uF
C1321	043-0554-90	25V 10uF
C1322	046-1022-58	50V 1000pF

REF NO.	PART NO.	DESCRIPTION
C1323	045-2201-50	22pFJ CH
C1325	168-1042-38	50V 0.1uF K
C1327	043-6400-90	16V 4.7uF K
C1328	168-1052-78	16V 1uF K
C1329	168-1052-78	16V 1uF K
C1330	168-1042-38	50V 0.1uF K
C1404	043-7700-90	50V 4.7uF
C1405	ADZ0265	35V 47uF
C1406	043-7700-90	50V 4.7uF
C1429	043-7700-90	50V 4.7uF
C1430	168-1042-38	50V 0.1uF K
C1431	168-1832-55	0.018uF K
C1432	043-0605-90	10V 2.2uF
C1434	168-1042-38	50V 0.1uF K
C1435	046-1022-58	50V 1000pF
C1436	045-1011-50	100pFJ CH
C1437	045-1011-50	100pFJ CH
C1438	168-1032-55	0.01uF K
C1439	046-1022-58	50V 1000pF
C1440	043-7700-90	50V 4.7uF
C1441	ADZ0265	35V 47uF
C1442	168-1042-38	50V 0.1uF K
C1501	ADZ0265	35V 47uF
C1502	168-1042-38	50V 0.1uF K
C1506	045-1011-50	100pFJ CH
C1507	043-0570-90	16V 2.2uF K
C1508	043-0574-90	25V 1.0uF
C1511	046-2232-78	0.022uF K B
C1512	046-6832-78	0.068uF K B
C1513	046-4732-78	0.047uF K B
C1514	043-0574-90	25V 1.0uF
C1515	043-7702-90	1.0uF
C1516	043-0566-90	50V 2.2uF K
C1517	168-1042-38	50V 0.1uF K
C1518	168-6832-78	0.068uF K
C1519	043-7702-90	1.0uF
C1521	043-6404-90	16V 10uF
C1523	166-3311-50	330pF CH
C1524	043-6404-90	16V 10uF
C1525	043-6404-90	16V 10uF
C1526	168-6832-78	0.068uF K
C1527	168-6832-78	0.068uF K
C1528	043-6404-90	16V 10uF
C1538	043-0566-90	50V 2.2uF K
C1601	046-1022-58	50V 1000pF
C1602	046-1022-58	50V 1000pF
C1603	046-1022-58	50V 1000pF
C1604	046-1022-58	50V 1000pF
C1606	046-1022-58	50V 1000pF
C1608	046-1022-58	50V 1000pF
C1610	046-1022-58	50V 1000pF
C1612	046-1022-58	50V 1000pF
C1613	168-1052-78	16V 1uF K
C1614	046-1042-78	0.1uF K B
C1615	168-1052-78	16V 1uF K
C1616	178-1062-88	10uF
C1619	168-1022-55	1000pF K
CN1601	074-2249-04	SOCKET(4P)
D1	001-2640-90	D1FJ4
D2	001-2640-90	D1FJ4
D702	001-2630-90	1SS420-TPL3,F
D904	001-2630-90	1SS420-TPL3,F
D905	001-2630-90	1SS420-TPL3,F
D906	001-2630-90	1SS420-TPL3,F
D907	001-2630-90	1SS420-TPL3,F
D908	001-2630-90	1SS420-TPL3,F
D909	001-2630-90	1SS420-TPL3,F
D911	001-4910-91	DF5A5.6F
D912	001-4910-91	DF5A5.6F
D1002	001-1304-90	DAN202U
D1003	001-1325-90	1SS387
D1103	001-4910-91	DF5A5.6F
D1104	001-4910-91	DF5A5.6F
D1109	001-2630-90	1SS420-TPL3,F
D1111	001-2412-90	RR264M-400

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
D1112	001-0580-90	1SS352			DFT2G	L1205	010-3104-50	30 ohm/100MHz
D1114	001-2412-90	RR264M-400	IC1009	051-7222-60	MC74VHC1G08	L1206	010-3548-50	2.2uH
D1116	001-2630-90	1SS420-TPL3,F			DFT2G	L1210	010-3548-50	2.2uH
D1117	001-2651-90	RSX101M-30TR	IC1010	051-7281-60	MC74VHC1G14	L1301	BMZ0211	BLM18PG121
D1501	001-2630-90	1SS420-TPL3,F			DFT2G			SN1D
D1502	001-2630-90	1SS420-TPL3,F	IC1104	051-7563-90	NLV27WZ16	L1303	010-3126-52	470ohm
D1503	001-2640-90	D1FJ4			DFT2G	L1401	BAZ0381	56uH
D1504	001-2620-90	RB060L-40	IC1106	051-3776-90	NJM2815GM1-51A	L1402	010-3523-50	CDRH5D28RHPNP
D1505	001-2640-90	D1FJ4	IC1201	-----	SC183CULTRT			-220MC
FL1301	BMZ0251	BK20104L121-T			(PAD)	L1503	010-3502-90	10uH
FL1302	010-3303-50	BK20104M601-T			(358800-051)	L1505	010-3502-90	10uH
FL1303	010-3303-50	BK20104M601-T	IC1203	-----	BD3572FP	L1506	010-3502-90	10uH
FL1304	010-3303-50	BK20104M601-T			(thermal pad)	L1601	010-3127-91	220 ohm/100MHz
FL1305	010-3303-50	BK20104M601-T			(358790-051)	NF1103	060-3117-51	CKD510JB1E223
FL1306	010-3303-50	BK20104M601-T	IC1210	051-3328-90	S-1323B18NB-			ST
FL1307	010-3303-50	BK20104M601-T			N8D-TF	NF1104	060-3117-51	CKD510JB1E223
IC101	-----	DRA624AIZKKQ1	IC1211	051-3519-90	NJU7771F05-TE2			ST
		(App DSP)	IC1212	-----	SC183CULTRT	NF1601	010-3303-90	120 ohm/100MHz
		(BGA type)			(PAD)			x4
		(676300-051)			(358800-051)	P1103	076-6023-07	7P
IC102	-----	MT41K128M16JT	IC1213	051-3519-90	NJU7771F05-TE2	P1104	074-1302-28	28P
		-125E-IT:K	IC1214	-----	BD00IA5EEFJ-ME2	P1201	076-6030-60	10P
		(thermal pad)			(LDO REG)	P1203	076-0569-02	2P
		(933920-051)			(Exposed Pad)	Q601	191-1197-50	2SB1197K Q,R
IC102	-----	K4B2G1646Q-			(376390-051)	Q602	191-1197-50	2SB1197K Q,R
		BPH9	IC1301	051-6761-80	S-8412AAA7I-	Q603	125-2046-91	DTC114EUBTL
		(DDR3 SDRAM)			TCBB30	Q604	125-2046-91	DTC114EUBTL
		(FBGA)	IC1401	-----	BD81A04EFV-M	Q701	125-2046-91	DTC114EUBTL
		(933903-051)			(Thermal pad)	Q901	192-4081-00	2SC4081
IC103	-----	K4B2G1646Q-			(611390-051)	Q902	192-4081-00	2SC4081
		BPH9	IC1501	-----	OZ528ILN-B1-0-TR	Q1001	125-0035-91	DTA114EUBTL
		(DDR3 SDRAM)			(Thermal pad)	Q1003	125-2046-91	DTC114EUBTL
		(FBGA)			(394090-051)	Q1004	125-0035-91	DTA114EUBTL
		(933903-051)	IC1601	051-6112-90	BU21024FV-ME2	Q1006	125-2046-91	DTC114EUBTL
IC103	-----	MT41K128M16JT	J601	074-2248-40	SOCKET(40P)	Q1010	191-1197-50	2SB1197K Q,R
		-125E-IT:K	J901	074-2248-80	80P	Q1011	125-2046-91	DTC114EUBTL
		(thermal pad)	J902	074-2248-30	30P	Q1106	190-1576-60	2SA1576UBTL
		(933920-051)	J1001	074-8017-91	16P	Q1107	125-2046-91	DTC114EUBTL
IC104	-----	MX29GL640EBTI	J1101	074-4105-00	SOCKET(4P)	Q1109	190-1576-60	2SA1576UBTL
		-70G	J1301	074-2248-60	60P	Q1110	192-4081-00	2SC4081
		(FLASH MICOM)	L200	010-3126-52	470ohm	Q1111	192-4081-00	2SC4081
		(Software should be	L301	BMZ0211	BLM18PG121	Q1205	125-2046-91	DTC114EUBTL
		written on			SN1D	Q1206	125-7011-90	RSR025P03TL
		production)	L302	BMZ0211	BLM18PG121	Q1408	125-8032-90	RVQ040N05 TR
		(982690-051)			SN1D	Q1409	192-4081-00	2SC4081
IC201	051-5460-90	R3132Q30EA8-	L303	BMZ0211	BLM18PG121	Q1410	192-4081-00	2SC4081
		TR-F			SN1D	Q1411	125-2046-91	DTC114EUBTL
IC202	051-6934-90	MF1341S2313	L304	BMZ0211	BLM18PG121	Q1502	CA11433	2SA1576AT106R
IC206	051-5460-90	R3132Q30EA8-			SN1D	Q1505	CA11433	2SA1576AT106R
		TR-F	L305	BMZ0211	BLM18PG121	Q1507	CA11433	2SA1576AT106R
IC501	-----	AK8859VN-L			SN1D	Q1508	192-4081-00	2SC4081
		(Video-Decoder)	L501	BMZ0211	BLM18PG121	Q1513	125-2046-91	DTC114EUBTL
		(Thermal pad)			SN1D	Q1514	125-2046-92	DTC124EUBTL
		(647790-051)	L502	010-3417-90	10uH	R101	033-0000-05	1/16W 0 ohm
IC603	051-3579-90	S1112B15MCL6	L503	BMZ0211	BLM18PG121	R102	033-0000-05	1/16W 0 ohm
		ATFG			SN1D	R103	033-0000-05	1/16W 0 ohm
IC604	051-3766-90	BD00HC5EEFJ-	L504	010-3125-90	120 ohm/100MHz	R104	032-0225-53	1/16W 49.9 ohm
		ME2	L604	010-3104-50	30 ohm/100MHz	R105	033-3301-15	1/16W 33 ohm J
IC701	051-5449-90	BU4229G	L605	010-3104-50	30 ohm/100MHz	R106	033-1031-15	1/16W 10k ohm J
IC702	052-0329-20	UPD70F3333GC	L606	010-3104-50	30 ohm/100MHz	R109	033-3301-15	1/16W 33 ohm J
		(A)-UEU-AX	L607	010-3104-50	30 ohm/100MHz	R110	033-3301-15	1/16W 33 ohm J
IC801	051-3067-90	NJM14558V	L701	010-2279-50	4.7uH	R111	033-3301-15	1/16W 33 ohm J
IC803	060-8162-90	BT MODULE	L802	010-3127-91	220 ohm/100MHz	R112	033-3301-15	1/16W 33 ohm J
		(UGXZD-105A)	L804	BMZ0211	BLM18PG121	R113	033-1031-15	1/16W 10k ohm J
IC804	051-6533-90	AK7756VF			SN1D	R115	033-3301-15	1/16W 33 ohm J
IC901	051-7222-60	MC74VHC1G08	L902	010-3104-50	30 ohm/100MHz	R116	033-1031-15	1/16W 10k ohm J
		DFT2G	L1002	BMZ0211	BLM18PG121	R124	033-1001-15	1/16W 10 ohm J
IC1003	CUZ0502	TC7WH123FKF			SN1D	R125	033-1001-15	1/16W 10 ohm J
IC1004	051-5408-08	S-80921CNMC-	L1101	BEZ0122	DLP11SN900HL	R126	032-0221-90	1/16W 240 ohm 1%
		G8RT2G			2L	R127	032-0221-90	1/16W 240 ohm 1%
IC1005	051-7222-60	MC74VHC1G08	L1105	010-3442-50	LBM2016T3R3J	R128	032-0221-98	1/16W 120 ohm 1%
		DFT2G	L1201	010-3104-50	30 ohm/100MHz	R129	032-0221-99	1/16W 100 ohm 1%
IC1007	051-7222-60	MC74VHC1G08	L1202	010-3104-50	30 ohm/100MHz	R130	032-0221-99	1/16W 100 ohm 1%
		DFT2G	L1203	010-3104-50	30 ohm/100MHz	R131	032-0221-99	1/16W 100 ohm 1%
IC1008	051-7202-90	MC74VHC1G32	L1204	010-3104-50	30 ohm/100MHz	R132	032-0221-99	1/16W 100 ohm 1%

REF NO.	PART NO.	DESCRIPTION
R133	032-0221-99	1/16W 100 ohm 1%
R134	032-0221-99	1/16W 100 ohm 1%
R135	032-0221-99	1/16W 100 ohm 1%
R136	032-0221-99	1/16W 100 ohm 1%
R138	033-1031-15	1/16W 10k ohm J
R140	033-3301-15	1/16W 33 ohm J
R141	033-3301-15	1/16W 33 ohm J
R142	033-3301-15	1/16W 33 ohm J
R143	033-0000-05	1/16W 0 ohm
R201	033-3301-15	1/16W 33 ohm J
R202	033-3301-15	1/16W 33 ohm J
R203	033-4721-15	1/16W 4.7k ohm J
R204	033-3301-15	1/16W 33 ohm J
R205	033-3301-15	1/16W 33 ohm J
R206	033-3301-15	1/16W 33 ohm J
R207	033-3301-15	1/16W 33 ohm J
R208	033-3301-15	1/16W 33 ohm J
R209	033-3301-15	1/16W 33 ohm J
R210	032-0221-95	1/16W 2.7k ohm F
R211	033-3301-15	1/16W 33 ohm J
R212	033-0000-05	1/16W 0 ohm
R213	033-3301-15	1/16W 33 ohm J
R214	033-3301-15	1/16W 33 ohm J
R215	033-3301-15	1/16W 33 ohm J
R216	033-3301-15	1/16W 33 ohm J
R217	033-3301-15	1/16W 33 ohm J
R218	032-0221-01	1/16W 47 ohm F
R219	033-0000-05	1/16W 0 ohm
R220	033-0000-05	1/16W 0 ohm
R222	033-0000-05	1/16W 0 ohm
R224	033-3301-15	1/16W 33 ohm J
R225	033-3301-15	1/16W 33 ohm J
R227	033-1031-15	1/16W 10k ohm J
R229	033-3301-15	1/16W 33 ohm J
R230	033-3301-15	1/16W 33 ohm J
R231	033-3301-15	1/16W 33 ohm J
R232	033-0000-05	1/16W 0 ohm
R236	033-1031-15	1/16W 10k ohm J
R237	033-1031-15	1/16W 10k ohm J
R238	033-1031-15	1/16W 10k ohm J
R239	033-0000-05	1/16W 0 ohm
R240	033-0000-05	1/16W 0 ohm
R241	033-3301-15	1/16W 33 ohm J
R242	033-1031-15	1/16W 10k ohm J
R244	033-0000-05	1/16W 0 ohm
R245	033-0000-05	1/16W 0 ohm
R246	033-0000-05	1/16W 0 ohm
R247	033-3301-15	1/16W 33 ohm J
R250	033-0000-05	1/16W 0 ohm
R252	033-3301-15	1/16W 33 ohm J
R254	033-3301-15	1/16W 33 ohm J
R255	033-1031-15	1/16W 10k ohm J
R256	033-4721-15	1/16W 4.7k ohm J
R257	033-4721-15	1/16W 4.7k ohm J
R258	033-3321-15	1/16W 3.3k ohm J
R259	033-3321-15	1/16W 3.3k ohm J
R260	033-0000-05	1/16W 0 ohm
R261	033-0000-05	1/16W 0 ohm
R262	032-0221-32	1/16W 220k ohm F
R263	033-4721-15	1/16W 4.7k ohm J
R264	033-4721-15	1/16W 4.7k ohm J
R265	033-4721-15	1/16W 4.7k ohm J
R267	033-0000-05	1/16W 0 ohm
R269	033-0000-05	1/16W 0 ohm
R272	033-3301-15	1/16W 33 ohm J
R273	033-0000-05	1/16W 0 ohm
R276	033-0000-05	1/16W 0 ohm
R277	033-0000-05	1/16W 0 ohm
R278	033-0000-05	1/16W 0 ohm
R279	033-0000-05	1/16W 0 ohm
R282	033-0000-05	1/16W 0 ohm
R283	033-0000-05	1/16W 0 ohm
R286	033-1031-15	1/16W 10k ohm J
R287	033-1041-15	1/16W 100k ohm J
R288	033-1031-15	1/16W 10k ohm J

REF NO.	PART NO.	DESCRIPTION
R289	033-1031-15	1/16W 10k ohm J
R290	033-1031-15	1/16W 10k ohm J
R291	033-0000-05	1/16W 0 ohm
R292	033-3301-15	1/16W 33 ohm J
R294	033-3301-15	1/16W 33 ohm J
R295	033-0000-05	1/16W 0 ohm
R296	033-1031-15	1/16W 10k ohm J
R297	033-1031-15	1/16W 10k ohm J
R304	032-0221-99	1/16W 100 ohm 1%
R305	032-0221-99	1/16W 100 ohm 1%
R307	033-0000-05	1/16W 0 ohm
R401	033-1021-15	1/16W 1k ohm J
R402	033-1021-15	1/16W 1k ohm J
R408	033-1031-15	1/16W 10k ohm J
R411	033-1031-15	1/16W 10k ohm J
R412	033-1031-15	1/16W 10k ohm J
R413	033-1031-15	1/16W 10k ohm J
R417	033-1031-15	1/16W 10k ohm J
R422	033-1031-15	1/16W 10k ohm J
R424	033-1031-15	1/16W 10k ohm J
R425	033-1031-15	1/16W 10k ohm J
R428	033-1031-15	1/16W 10k ohm J
R430	033-1031-15	1/16W 10k ohm J
R501	033-8201-15	1/16W 82 ohm J
R504	032-0221-88	1/16W 30 ohm F
R505	033-4701-15	1/16W 47 ohm J
R506	032-0221-72	1/16W 470 ohm F
R507	032-0221-61	1/16W 6.8k ohm F
R627	033-4731-15	1/16W 47k ohm J
R628	033-3911-15	1/16W 390 ohm J
R633	033-1041-15	1/16W 100k ohm J
R634	033-1031-15	1/16W 10k ohm J
R635	033-1031-15	1/16W 10k ohm J
R636	033-5611-15	1/16W 560 ohm J
R637	033-5611-15	1/16W 560 ohm J
R638	033-1041-15	1/16W 100k ohm J
R640	032-0221-51	1/16W 4.7k ohm F
R641	032-0221-56	1/16W 22k ohm F
R642	032-0221-83	1/16W 3.3k ohm F
R651	033-0000-05	1/16W 0 ohm
R701	032-0221-61	1/16W 6.8k ohm F
R702	033-4731-15	1/16W 47k ohm J
R703	033-1041-15	1/16W 100k ohm J
R704	033-1041-15	1/16W 100k ohm J
R705	033-4731-15	1/16W 47k ohm J
R706	033-1041-15	1/16W 100k ohm J
R707	033-1041-15	1/16W 100k ohm J
R708	033-1041-15	1/16W 100k ohm J
R709	033-1021-15	1/16W 1k ohm J
R710	033-4731-15	1/16W 47k ohm J
R711	033-1011-15	1/16W 100 ohm J
R712	033-1011-15	1/16W 100 ohm J
R713	033-1011-15	1/16W 100 ohm J
R714	033-1011-15	1/16W 100 ohm J
R715	033-1011-15	1/16W 100 ohm J
R716	033-1011-15	1/16W 100 ohm J
R717	033-4731-15	1/16W 47k ohm J
R718	033-1031-15	1/16W 10k ohm J
R720	032-0221-74	1/16W 10k ohm 1%
R721	032-0221-74	1/16W 10k ohm 1%
R722	033-0000-05	1/16W 0 ohm
R723	033-0000-05	1/16W 0 ohm
R724	033-3331-15	1/16W 33k ohm J
R725	033-3331-15	1/16W 33k ohm J
R726	033-0000-05	1/16W 0 ohm
R727	033-0000-05	1/16W 0 ohm
R728	119-3331-15	1/10W 33k ohm
R729	033-4731-15	1/16W 47k ohm J
R730	033-0000-05	1/16W 0 ohm
R731	033-1011-15	1/16W 100 ohm J
R732	033-1041-15	1/16W 100k ohm J
R733	033-1041-15	1/16W 100k ohm J
R734	033-1041-15	1/16W 100k ohm J
R735	033-1041-15	1/16W 100k ohm J
R736	033-1021-15	1/16W 1k ohm J

REF NO.	PART NO.	DESCRIPTION
R737	033-1021-15	1/16W 1k ohm J
R738	033-1041-15	1/16W 100k ohm J
R739	033-4721-15	1/16W 4.7k ohm J
R740	033-4731-15	1/16W 47k ohm J
R741	033-4731-15	1/16W 47k ohm J
R742	033-1011-15	1/16W 100 ohm J
R743	033-1041-15	1/16W 100k ohm J
R745	033-1041-15	1/16W 100k ohm J
R747	033-4731-15	1/16W 47k ohm J
R748	032-0210-26	1/10W 82 ohm F
R749	032-0210-26	1/10W 82 ohm F
R750	032-0210-00	1/10W 330 ohm F
R751	032-0210-00	1/10W 330 ohm F
R752	033-4731-15	1/16W 47k ohm J
R753	033-0000-05	1/16W 0 ohm
R755	033-0000-05	1/16W 0 ohm
R756	033-4731-15	1/16W 47k ohm J
R763	033-1041-15	1/16W 100k ohm J
R764	033-1041-15	1/16W 100k ohm J
R765	033-4731-15	1/16W 47k ohm J
R801	033-1041-15	1/16W 100k ohm J
R802	032-0221-08	1/16W 1k ohm F
R803	032-0221-79	1/16W 1.2k ohm F
R804	032-0221-33	1/16W 20k ohm F
R805	033-1031-15	1/16W 10k ohm J
R806	033-1031-15	1/16W 10k ohm J
R807	032-0221-51	1/16W 4.7k ohm F
R808	033-0000-05	1/16W 0 ohm
R809	033-1031-15	1/16W 10k ohm J
R811	033-0000-05	1/16W 0 ohm
R812	033-1011-15	1/16W 100 ohm J
R813	033-1011-15	1/16W 100 ohm J
R818	033-0000-05	1/16W 0 ohm
R828	033-0000-05	1/16W 0 ohm
R831	033-1011-15	1/16W 100 ohm J
R837	033-1011-15	1/16W 100 ohm J
R838	033-1031-15	1/16W 10k ohm J
R839	033-0000-05	1/16W 0 ohm
R840	032-0221-62	1/16W 8.2k ohm F
R841	033-1031-15	1/16W 10k ohm J
R844	119-0000-05	1/10W 0 ohm JW
R845	119-0000-05	1/10W 0 ohm JW
R847	032-0221-95	1/16W 2.7k ohm F
R853	033-1031-15	1/16W 10k ohm J
R854	033-1031-15	1/16W 10k ohm J
R855	033-0000-05	1/16W 0 ohm
R856	032-0221-01	1/16W 47 ohm F
R860	033-0000-05	1/16W 0 ohm
R861	033-0000-05	1/16W 0 ohm
R862	033-0000-05	1/16W 0 ohm
R863	033-1011-15	1/16W 100 ohm J
R942	033-3301-15	1/16W 33 ohm J
R943	033-3301-15	1/16W 33 ohm J
R949	033-3301-15	1/16W 33 ohm J
R951	033-1031-15	1/16W 10k ohm J
R954	033-1011-15	1/16W 100 ohm J
R955	033-1011-15	1/16W 100 ohm J
R956	033-1011-15	1/16W 100 ohm J
R957	033-1031-15	1/16W 10k ohm J
R958	033-1031-15	1/16W 10k ohm J
R960	116-2221-15	1/4W 2.2k ohm
R961	033-4731-15	1/16W 47k ohm J
R962	033-0000-05	1/16W 0 ohm
R1007	033-3301-15	1/16W 33 ohm J
R1008	033-3301-15	1/16W 33 ohm J
R1009	033-3301-15	1/16W 33 ohm J
R1010	033-3301-15	1/16W 33 ohm J
R1011	033-3301-15	1/16W 33 ohm J
R1012	033-1011-15	1/16W 100 ohm J
R1014	033-4731-15	1/16W 47k ohm J
R1032	032-0221-75	1/16W 47k ohm F
R1033	033-4731-15	1/16W 47k ohm J
R1036	033-1031-15	1/16W 10k ohm J
R1037	033-1041-15	1/16W 100k ohm J
R1038	033-4721-15	1/16W 4.7k ohm J

REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION	REF NO.	PART NO.	DESCRIPTION
R1039	033-1031-15	1/16W 10k ohm J	R1462	033-2231-15	1/16W 22k ohm J	RN110	050-0156-59	1/16W 33 ohm x4
R1040	033-4731-15	1/16W 47k ohm J	R1463	032-0221-56	1/16W 22k ohm F	RN112	050-0156-59	1/16W 33 ohm x4
R1041	033-4731-15	1/16W 47k ohm J	R1464	032-0210-88	1/10W 5.1k ohm F	RN113	050-0156-59	1/16W 33 ohm x4
R1042	033-4731-15	1/16W 47k ohm J	R1466	032-0221-59	1/16W 220 ohm F	RN114	050-0156-59	1/16W 33 ohm x4
R1043	033-1011-15	1/16W 100 ohm J	R1467	032-0221-75	1/16W 47k ohm F	RN115	050-0156-59	1/16W 33 ohm x4
R1045	033-4731-15	1/16W 47k ohm J	R1468	032-0221-59	1/16W 220 ohm F	RN116	050-0156-59	1/16W 33 ohm x4
R1050	033-1031-15	1/16W 10k ohm J	R1469	033-5121-15	1/16W 5.1k ohm	RN117	050-0156-59	1/16W 33 ohm x4
R1051	033-5611-15	1/16W 560 ohm J	R1470	033-2231-15	1/16W 22k ohm J	RN201	050-0156-59	1/16W 33 ohm x4
R1053	033-2221-15	1/16W 2.2k ohm J	R1471	032-0221-10	1/16W 15k ohm F	RN203	050-0156-59	1/16W 33 ohm x4
R1114	119-1021-15	1/10W 1k ohm	R1472	032-0221-74	1/16W 10k ohm 1%	RN204	050-0156-59	1/16W 33 ohm x4
R1115	119-1021-15	1/10W 1k ohm	R1473	032-0221-56	1/16W 22k ohm F	RN205	050-0156-59	1/16W 33 ohm x4
R1121	119-1021-15	1/10W 1k ohm	R1474	032-0221-56	1/16W 22k ohm F	RN206	050-0156-59	1/16W 33 ohm x4
R1122	119-1031-15	1/10W 10k ohm	R1476	032-0221-06	1/16W 100k ohm F	RN207	050-0156-53	1/16W 0 ohm x4
R1124	033-1011-15	1/16W 100 ohm J	R1477	032-0221-56	1/16W 22k ohm F	RN208	050-0156-59	1/16W 33 ohm x4
R1125	033-1031-15	1/16W 10k ohm J	R1478	119-0000-05	1/10W 0 ohm JW	RN209	050-0156-59	1/16W 33 ohm x4
R1142	033-2221-15	1/16W 2.2k ohm J	R1481	119-0000-05	1/10W 0 ohm JW	RN210	050-0156-59	1/16W 33 ohm x4
R1143	033-0000-05	1/16W 0 ohm	R1482	119-0000-05	1/10W 0 ohm JW	RN211	050-0156-59	1/16W 33 ohm x4
R1145	116-1021-15	1/4W 1k ohm	R1483	033-2231-15	1/16W 22k ohm J	RN213	050-0156-59	1/16W 33 ohm x4
R1146	116-1021-15	1/4W 1k ohm	R1484	033-2231-15	1/16W 22k ohm J	RN214	050-0156-59	1/16W 33 ohm x4
R1147	116-1021-15	1/4W 1k ohm	R1485	033-2231-15	1/16W 22k ohm J	RN216	050-0156-59	1/16W 33 ohm x4
R1148	033-2221-15	1/16W 2.2k ohm J	R1487	032-0221-61	1/16W 6.8k ohm F	RN217	050-0156-78	1/16W 1k ohm x4
R1149	033-1031-15	1/16W 10k ohm J	R1488	032-0221-95	1/16W 2.7k ohm F	RN403	050-0156-57	1/16W 10k ohm x4
R1150	033-1031-15	1/16W 10k ohm J	R1501	033-4721-15	1/16W 4.7k ohm J	RN404	050-0156-57	1/16W 10k ohm x4
R1151	033-1021-15	1/16W 1k ohm J	R1504	119-2711-15	1/10W 270 ohm	RN501	050-0156-59	1/16W 33 ohm x4
R1152	033-2221-15	1/16W 2.2k ohm J	R1505	033-4721-15	1/16W 4.7k ohm J	RN502	050-0156-59	1/16W 33 ohm x4
R1153	033-1021-15	1/16W 1k ohm J	R1506	033-1031-15	1/16W 10k ohm J	RN702	050-0156-63	1/16W 47k ohm x4
R1154	033-5621-15	1/16W 5.6k ohm J	R1509	033-1031-15	1/16W 10k ohm J	RN703	050-0156-64	1/16W 100k ohm x4
R1155	033-1031-15	1/16W 10k ohm J	R1510	032-0221-59	1/16W 220 ohm F	RN901	050-0156-59	1/16W 33 ohm x4
R1156	033-3931-15	1/16W 39k ohm J	R1512	032-0221-59	1/16W 220 ohm F	RN918	050-0156-59	1/16W 33 ohm x4
R1157	119-3921-15	1/10W 3.9k ohm	R1514	032-0221-83	1/16W 3.3k ohm F	RN919	050-0156-59	1/16W 33 ohm x4
R1158	116-1011-15	1/4W 100 ohm	R1516	032-0210-02	1/10W 56k ohm 1%	RN922	050-0156-52	1/16W 100 ohm x4
R1159	033-1021-15	1/16W 1k ohm J	R1519	032-0210-58	1/10W 12k ohm F	RN923	050-0156-52	1/16W 100 ohm x4
R1160	033-2221-15	1/16W 2.2k ohm J	R1520	032-0210-17	1/10W 6.8k ohm F	RN924	050-0156-57	1/16W 10k ohm x4
R1161	033-0000-05	1/16W 0 ohm	R1521	033-0000-05	1/16W 0 ohm	RN925	050-0156-57	1/16W 10k ohm x4
R1166	033-3321-15	1/16W 3.3k ohm J	R1522	032-0210-88	1/10W 5.1k ohm F	RN1002	050-0156-63	1/16W 47k ohm x4
R1167	033-6821-15	1/16W 6.8k ohm J	R1523	032-0210-58	1/10W 12k ohm F	RN1301	050-0156-66	1/16W 47 ohm x4
R1168	033-4711-15	1/16W 470 ohm J	R1524	032-0210-59	1/10W 5.6k ohm F	RN1302	050-0140-67	1/32W 220 ohm x4J
R1172	116-1011-15	1/4W 100 ohm	R1525	032-0210-72	1/10W 1.8k ohm	RN1303	050-0140-67	1/32W 220 ohm x4J
R1177	033-1021-15	1/16W 1k ohm J			1%	RN1304	050-0140-67	1/32W 220 ohm x4J
R1188	032-0221-74	1/16W 10k ohm 1%	R1527	032-0210-40	1/10W 1.3k ohm F	RN1305	050-0140-67	1/32W 220 ohm x4J
R1211	032-0221-04	1/16W 10 ohm F	R1528	032-0210-88	1/10W 5.1k ohm F	RN1306	050-0140-67	1/32W 220 ohm x4J
R1220	032-0221-30	1/16W 150k ohm F	R1529	032-0210-88	1/10W 5.1k ohm F	RN1307	050-0140-67	1/32W 220 ohm x4J
R1221	032-0221-10	1/16W 15k ohm F	R1531	032-0210-57	1/10W 4.7k ohm F	SUP1101	001-4323-90	RCLAMP0502A
R1222	032-0221-06	1/16W 100k ohm F	R1533	032-0210-95	1/10W 2k ohm F	TH701	002-0315-00	TN10-3U153JT
R1232	032-0221-74	1/16W 10k ohm 1%	R1536	032-0210-16	1/10W 1.2k ohm F	TH1100	002-0335-50	SMD1812P050TF
R1233	032-0221-63	1/16W 12k ohm F	R1540	033-3321-15	1/16W 3.3k ohm J			/30
R1234	032-0221-96	1/16W 820 ohm 1%	R1543	033-2231-15	1/16W 22k ohm J	TH1202	002-0335-51	SMD1812P150TF
R1292	119-2731-15	1/10W 27k ohm	R1546	033-2231-15	1/16W 22k ohm J			/24
R1294	119-1231-15	1/10W 12k ohm	R1547	033-2231-15	1/16W 22k ohm J	VR1108	001-9213-50	EZJZ1V270EA
R1298	033-1001-15	1/16W 10 ohm J	R1550	033-2231-15	1/16W 22k ohm J	VR1109	001-9213-50	EZJZ1V270EA
R1334	119-1031-15	1/10W 10k ohm	R1557	033-3331-15	1/16W 33k ohm J	VR1110	001-9213-50	EZJZ1V270EA
R1335	033-3301-15	1/16W 33 ohm J	R1558	033-2231-15	1/16W 22k ohm J	VR1111	001-9213-50	EZJZ1V270EA
R1337	119-1031-15	1/10W 10k ohm	R1564	117-1021-15	1/8W 1k ohm	VR1112	001-9213-50	EZJZ1V270EA
R1340	119-1031-15	1/10W 10k ohm	R1569	117-0000-05	1/8W 0 ohm JW	VR1113	001-9213-50	EZJZ1V270EA
R1342	119-1031-15	1/10W 10k ohm	R1578	033-1031-15	1/16W 10k ohm J	VR1114	001-9213-50	EZJZ1V270EA
R1343	119-1031-15	1/10W 10k ohm	R1582	116-0000-05	1/4W 0 ohm JW	VR1116	001-9213-50	EZJZ1V270EA
R1344	119-1031-15	1/10W 10k ohm	R1603	032-0221-03	1/16W 22 ohm 1%	VR1117	001-9213-50	EZJZ1V270EA
R1365	033-1011-15	1/16W 100 ohm J	R1605	032-0221-03	1/16W 22 ohm 1%	VR1118	001-9213-50	EZJZ1V270EA
R1366	032-0221-91	1/16W 18 ohm F	R1607	032-0221-03	1/16W 22 ohm 1%	X201	061-3575-70	FA-238
R1370	119-4301-15	1/10W 43 ohm	R1608	032-0221-03	1/16W 22 ohm 1%			22.5792MHz
R1374	032-0221-91	1/16W 18 ohm F	R1609	AQZ0462	1/16W 330k ohm	X202	061-3609-90	FA-238 20MHz
R1375	119-1611-15	1/10W 160 ohm	R1610	AQZ0462	1/16W 330k ohm	X204	061-9227-90	32.768kHz
R1380	119-4301-15	1/10W 43 ohm	R1611	AQZ0462	1/16W 330k ohm	X501	061-3581-70	FA-238 24.576MHz
R1381	119-1611-15	1/10W 160 ohm	R1612	AQZ0462	1/16W 330k ohm	X701	061-3574-90	3.981312MHz
R1383	032-0221-15	1/16W 56 ohm	R1621	033-4721-15	1/16W 4.7k ohm J	ZD901	001-4305-20	UDZSTE-17 5.6B
R1384	032-0221-17	1/16W 180 ohm	R1622	033-3301-15	1/16W 33 ohm J	ZD902	001-4305-20	UDZSTE-17 5.6B
R1385	032-0221-17	1/16W 180 ohm	RN101	050-0156-53	1/16W 0 ohm x4	ZD903	001-4305-20	UDZSTE-17 5.6B
R1386	032-0221-15	1/16W 56 ohm	RN102	050-0156-53	1/16W 0 ohm x4	ZD1103	001-4305-32	UDZSTE-17 18B
R1387	032-0221-03	1/16W 22 ohm 1%	RN103	050-0156-53	1/16W 0 ohm x4	ZD1501	001-4305-23	UDZSTE-17 7.5B
R1454	032-0246-50	0.75W 0.2 ohm	RN104	050-0156-53	1/16W 0 ohm x4	ZD1601	001-4342-50	TFZFHTR6.2B
R1455	032-0246-50	0.75W 0.2 ohm	RN105	050-0156-53	1/16W 0 ohm x4	ZD1602	001-4342-50	TFZFHTR6.2B
R1457	033-2231-15	1/16W 22k ohm J	RN106	050-0156-53	1/16W 0 ohm x4	ZD1603	001-4342-50	TFZFHTR6.2B
R1459	119-4791-15	1/10W 4.7 ohm	RN107	050-0156-59	1/16W 33 ohm x4	ZD1604	001-4342-50	TFZFHTR6.2B
R1460	033-2231-15	1/16W 22k ohm J	RN108	050-0156-59	1/16W 33 ohm x4	PWB	039-4480-00	PWB(WITHOUT COMPONENTS)
R1461	033-2231-15	1/16W 22k ohm J	RN109	050-0156-59	1/16W 33 ohm x4			