

This exploded view diagram illustrates the components of the HP Z840 G2 system unit. The components are labeled as follows:

- DC1, DC2, RC1:** Power supply units.
- 351:** Power cord.
- 352, 353, 354:** Various cables and connectors.
- 355:** A small cable with a connector.
- 356:** A small cable with a connector.
- 357:** A small cable with a connector.
- 358 x5, 359 x5:** Screws for the front panel.
- 360:** The main system unit chassis.
- 361:** The front panel bezel.
- 362:** The rear panel bezel.
- 501, 502, 503, 504, 505, 506, 507:** A stack of hard drive bays.
- 364:** The internal drive tray assembly.
- 363:** A small cable with a connector.
- 365 x2:** Two screws for the drive tray.



MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						


Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
EXPLODED VIEW (UNIT) <M1MM>						
	DC1	E3A-0358-00	DC CORD		1	X1,M1,M2,K0
	DC2	E3A-0360-00	DC CORD		1	E1
	DGB1	CB-XJA055E01N	DIGITAL IO PWB ASSY	XJA-055E-01	1	E1
	DGB1	CB-XJA055X01N	DIGITAL IO PWB ASSY	XJA-055X-01	1	X1
	DGB1	CB-XJA055M01N	DIGITAL IO PWB ASSY	XJA-055M-01	1	M1,M2
	DGB1	CB-XJA055K00N	DIGITAL IO PWB ASSY	XJA-055K-00	1	K0
	MAB1	CB-XJ1221E01N	MAIN PWB ASSY	XJ1-221E-01	1	E1,X1,M1,M2
	MAB1	CB-XJ1221K00N	MAIN PWB ASSY	XJ1-221K-00	1	K0
	OPB1	CB-XJ7042K00N	OPERATION PWB ASSY	XJ7-042K-00	1	
	TUB1	XJH-190E-00	TUNER PWB ASSY	XJM-017E-00	1	E1,X1
	TUB1	XJH-189K-01	TUNER PWB ASSY	XJM-016K-01	1	M1,M2
	TUB1	XJH-192K-01	TUNER PWB ASSY	XJM-019K-02	1	K0
	VDB1	CB-XJ8044K00N	VIDEO PWB ASSY	XJ8-044K-00	1	
△	F1	FZB10AU-150	BLADE FUSE	15A	1	
	FC1	E3F-0111-00	FLAT CABLE		1	
	FC2	E3G-0068-00	FFC WIRE		1	
	FC3	EF0AA051503AC	FFC WIRE		1	
	FC4	EF0AD0560X4BC	FFC WIRE		1	
	FC5	EF0AD0550X4BC	FFC WIRE		1	
	FC6	E3G-0048-10	FFC WIRE		1	
	FPC1	E3J-0029-10	FPC		1	
	FPC2	E3J-0031-00	FPC		1	
	LCD1	B3H-0081-00	LCD ASSY		1	
	PA1	A6C-0063-0K	PANEL		1	E1,X1
	PA1	A6C-0063-0L	PANEL		1	M1,M2
	PA1	A6C-0063-0J	PANEL		1	K0
	PME1	A1A-0073-30	CHASSIS ASSY		1	
	RC1	QAL1553-001	REMOCON		1	X1,M1,M2
	TP1	W0C-0322-00	TOUCH PANEL		1	E1,X1,M1,M2
	TP1	W0C-0323-00	TOUCH PANEL		1	K0
	VME1	FD2-3A00NXN	DVD MECHA MODUL		1	
	WH1	E3F-0116-00	WIRING HARNESS		1	
	WH2	E3F-0112-00	WIRING HARNESS		1	
	A	LV45522-001A	SPECIAL SCREW		2	
	B	QYNTS2600ZA	NUT	M2.6	2	
	C	LV45701-003A	SPECIAL SCREW		12	
	D	LV45552-003A	SPECIAL SCREW		4	
	E	QYSDST2606ZA	TAP SCREW	M2.6 x 6mm	46	E1
	E	QYSDST2606ZA	TAP SCREW	M2.6 x 6mm	45	X1,M1,M2,K0
	F	QYSPSG3008ZA	TAP SCREW	M3 x 8mm	3	
	G	QYSDST2610ZA	TAP SCREW	M2.6 x 10mm	2	
	J	QYSPST2614ZA	TAP SCREW	M2.6 x 14mm	2	
	K	QYSDSF2608ZA	TAP SCREW	M2.6 x 8mm	1	
	L	N09-6490-05	STEPPED SCREW		2	
	M	N0Z-0200-00	SPECIAL SCREW		3	
	P	QYSDSG3006ZA	TAP SCREW	M3 x 6mm	2	
	R	QYSDST2606MA	TAP SCREW	M2.6 x 6mm	5	
	S	N09-6904-05	TAPTITE SCREW		1	
	T	QYSDST3006MA	TAP SCREW	M3 x 6mm	1	E1,X1,M1,M2
	217	E3A-0372-10	CORD W.CON.		1	E1,M1,M2
	217	E3A-0362-10	CORD W.CON.		1	X1,K0
	218	E3A-0421-00	CORD W.CON.		1	
	220	LV46006-002A	COOLING RUBBER		1	
	221	F0K-0264-00	FAN		1	
	224	G1B-0071-0G	CUSHION		2	
	230	F2K-0012-00	INS.COVER		3	
	232	LV45959-001A	CAP		2	
	233	F0G-0212-00	COVER		1	E1,X1,M1,M2
	235	A2C-0036-0G	SUB PANEL		1	E1
	235	A2C-0036-0H	SUB PANEL		1	X1
	235	A2C-0036-0J	SUB PANEL		1	M1,M2
	235	A2C-0036-0F	SUB PANEL		1	K0
	236	LV45134-003A	BLIND		1	
	237	B1K-0049-00	LIGHTING BOARD		1	
	238	G1D-0034-0B	CONDUCT CUSHION		3	E1,X1,M1,M2
	238	G1D-0034-0B	CONDUCT CUSHION		1	K0
	239	G1B-0278-00	CUSHION		1	
	240	F2A-0072-00	INS.SHEET		1	
	241	G1D-0034-0Y	CONDUCT CUSHION		1	
	243	G1D-0034-04	CONDUCT CUSHION		1	E1,X1,M1,M2
	244	G1D-0034-0D	CONDUCT CUSHION		1	
	245	G1G-0055-00	SHEET		1	E1,X1,M1,M2
	251	A2B-0103-02	DRESSING PANEL		1	
	252	A2B-0104-02	DRESSING PANEL		1	
	253	K2K-0235-00	KNOB ASSY	VOLUME	1	
	254	K2K-0236-16	KNOB ASSY	NAV	1	
	255	K2K-0237-01	KNOB ASSY	HOME	1	
	256	K2K-0238-11	KNOB ASSY	MENU	1	
	257	K2K-0239-11	KNOB ASSY	APPS	1	
	258	K2K-0240-10	KNOB ASSY	EJECT	1	
	259	B1K-0071-00	LIGHTING BOARD		1	
	260	J1K-0419-10	HOLDER		1	
	261	A4G-0078-02	REAR COVER		1	
	262	J2B-0381-01	BRACKET ASSY		1	
	263	F1C-0137-00	SHIELDING SHEET		1	
	264	B1A-0070-00	FRONT GLASS		1	
	273	F0K-0224-00	SHEET		2	
	274	F0K-0224-01	SHEET		2	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
280		F1K-0041-00	COVER SHEET		1	
282		G1D-0034-02	CONDUCT CUSHION		2	
351		E3A-0274-00	CORD W.PINJACK		1	X1,M1,M2
352		E3A-0364-00	USB CORD	BLACK	1	
353		E3A-0365-00	USB CORD	GRAY	1	
354		LV45939-001A	GPS BRACKET		1	
355		QAL1550-001	ANTENNA		1	
356		QAM1419-001	CAR CABLE		1	X1,M1,M2
357		QAN0137-001	MICROPHONE		1	
358		QYSSSP5008ZA	SCREW	M5 x 8mm	6	X1,M1,M2,K0
359		QYSTSP5008ZA	SCREW	M5 x 8mm	6	X1,M1,M2,K0
360		LV22876-001A	SLEEVE ASSY		1	E1,K0
361		B07-3237-41	ESCUTCHEON		1	
362		LV23141-001A	ESCUTCHEON		1	K0
363		LV45559-001A	W-FACED TAPE		1	K0
364		E3A-0067-00	ANTENNA CABLE		1	X1
365		LV45516-001A	LEVER		2	E1,K0
501		B5A-2483-00	INST.MANUAL	ENG	1	E1
501		B5A-2484-00	INST.MANUAL	ENG	1	X1,M1,M2
501		B5A-2482-00	INST.MANUAL	ENG	1	K0
502		B5A-2483-01	INST.MANUAL	FRE	1	E1
502		B5A-2484-01	INST.MANUAL	CHI(PEKIN)	1	M1
502		B5A-2300-03	INST.MANUAL	ARA(NAV)	1	M2
502		B5A-2482-01	INST.MANUAL	FRE	1	K0
503		B5A-2483-02	INST.MANUAL	GER	1	E1
503		B5A-2484-02	INST.MANUAL	ARA	1	M2
503		B5A-2482-02	INST.MANUAL	SPA	1	K0
504		B5A-2483-03	INST.MANUAL	DUT	1	E1
505		B5A-2483-04	INST.MANUAL	ITA	1	E1
506		B5A-2483-05	INST.MANUAL	SPA	1	E1
507		B5A-2483-06	INST.MANUAL	POR	1	E1
702		-----	AUDIO PWB ASSY	NO SERVICE PART	1	E1
702		-----	AUDIO PWB ASSY	NO SERVICE PART	1	X1
702		-----	AUDIO PWB ASSY	NO SERVICE PART	1	M1,M2
702		-----	AUDIO PWB ASSY	NO SERVICE PART	1	K0
704		-----	SUB PWB ASSY	NO SERVICE PART	1	E1,X1,M1,M2
710		-----	TOP PLATE	NO SERVICE PART	1	E1,X1,M1,M2
710		-----	TOP PLATE	NO SERVICE PART	1	K0
711		-----	BRACKET	NO SERVICE PART	1	
712		-----	BRACKET	NO SERVICE PART	1	
714		-----	SIDE PLATE	NO SERVICE PART	1	
715		-----	SIDE PLATE	NO SERVICE PART	1	
716		-----	SUB CHASSIS	NO SERVICE PART	1	
719		-----	HEAT SINK	NO SERVICE PART	1	
723		-----	REAR PANEL	NO SERVICE PART	1	E1
723		-----	REAR PANEL	NO SERVICE PART	1	X1,M1,M2
723		-----	REAR PANEL	NO SERVICE PART	1	K0
726		-----	BRACKET	NO SERVICE PART	1	
727		-----	BRACKET	NO SERVICE PART	1	
728		-----	SPACER(H)	NO SERVICE PART	1	
729		-----	SHEET	NO SERVICE PART	1	E1,X1,M1,M2
731		-----	BRACKET	NO SERVICE PART	1	
732		-----	BRACKET	NO SERVICE PART	1	
734		-----	CONDUCT CUSHION	NO SERVICE PART	1	E1,X1,M1,M2
745		-----	CUSHION	NO SERVICE PART	1	E1,X1
746		-----	SPACER	NO SERVICE PART	1	E1,X1
775		-----	HOLDER ASSY	NO SERVICE PART	1	

No.WA340

created date:2018-03-16




MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
EXPLODED VIEW (PANEL MECHA ASSY) <M2MM>						
PM1		T42-1368-04	MOTOR ASSY		1	
P		N09-6361-05	MACHINE SCREW	M2X2.5	6	
Q		N09-6363-05	MACHINE SCREW	M1.7X3.7	2	
R		N09-6375-05	MACHINE SCREW	M2X2.5	12	
S		N09-6376-05	MACHINE SCREW	M2X3.5	8	
T		N09-6377-05	MACHINE SCREW	M2X2.5	2	
U		N09-6378-05	TAPTITE SCREW	M2X2	2	
V		N09-6379-05	MACHINE SCREW	M2.6X4	4	
W		N19-2321-04	FLAT WASHER		5	
413		B09-0541-04	CAP		2	
418		D10-4895-32	SLIDER ASSY		1	
419		D10-4897-13	ARM ASSY		1	
420		D10-4899-03	LEVER		1	
421		D10-4900-03	LEVER		1	
423		D13-2394-04	GEAR		1	
424		D13-2395-04	GEAR		1	
425		D13-2396-04	GEAR		1	
426		D13-2397-03	RACK GEAR		1	
428		D14-1010-04	ROLLER		1	
429		D14-1011-14	ROLLER		2	
430		D19-0653-23	CLUTCH ASSY		1	
435		E39-1174-05	WIRING HARNESS		1	
454		G01-3288-04	TOR.COIL SPRING		1	
455		G01-3289-04	TOR.COIL SPRING		1	
456		G01-3290-04	EXTEN.SPRING		2	
457		G02-1539-04	FLAT SPRING		1	
459		G02-1544-04	FLAT SPRING		1	
460		G02-1545-04	FLAT SPRING		1	
472		J22-0444-13	MOUNTING ASSY		1	
482		J31-1075-14	COLLAR		2	
483		J31-1077-04	COLLAR		2	
486		J90-1126-13	GUIDE ASSY		1	
487		J90-1124-13	GUIDE ASSY		1	
488		J90-1128-03	RAIL		1	
489		J90-1129-23	RAIL		1	
490		J90-1130-23	RAIL		1	
491		J90-1131-03	GUIDE		1	
492		R31-0248-05	VARIABLE RESISTOR		1	
801	-----		CHAS.CALK.ASSY	NO SERVICE PART	1	
841	-----		SHEET	NO SERVICE PART	1	
866	-----		SHEET	NO SERVICE PART	2	

Block No.MJMM

- ★ W01-2067-08
- ▲ W01-1738-08
- W01-1743-08



MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
------	------------	-----------	------------	-------------	-----	-------

EXPLODED VIEW (DVD MECHANISM: FD2-3A00NXN) <MJMM>

VM1	CM-FD2-ALM	LOADING M ASSY		1
VT1	CM-FD2-ATM2	TM ASSY		1
A	LV44959-002A	SPECIAL SCREW		16
B	LV45727-001A	GEAR SCREW		2
C	QYSPSPU1425MA	SCREW	M1.4 x 2.5mm	2
D	VKZ4539-054	MINI SCREW		3
F	LV44586-001A	SPECIAL SCREW		1
4	LV45709-002A	CLAMP SPRING		1
7	LV23006-002A	GUIDE 2 L		1
8	LV23007-002A	GUIDE 2 R		1
9	LV11842-004A	DISC GUIDE		1
14	LV45704-001A	DAMPER SHAFT		4
15	LV45724-001A	RUBBER ROLLER		2
17	LV37652-002A	SHAFT GUIDE		1
18	LV39938-001A	GEAR RETAINER		1
19	LV45730-001A	ROLLER C WASHER		1
20	CM-FD2-AROS	RO SHAFT ASSY		1
21	LV45731-001A	ROLLER WASHER		1
22	LV45718-001A	ROLLER RETAINER		1
23	LV23003-002A	ROLLER HOLDER		1
24	LV45982-001A	ROLLER SPG R2		1
26	LV39932-003A	TRIGGER SLIDER		1
27	LV45715-001A	TRIGGER SPRING		1
28	LV23004-004A	SLIDER		1
29	LV39935-003A	SLIDER SPRING		1
31	LV39929-001A	DRIVE GEAR 4		1
32	LV39928-001A	DRIVE GEAR 3		3
33	LV39927-001A	DRIVE GEAR 2		1
34	LV39926-001A	DRIVE GEAR 1		1
35	LV23005-001A	GEAR HOLDER		1
36	LV39923-003A	UD LEVER		1
37	LV45983-001A	ROLLER SPG L2		1
38	LV39934-001A	DAMPER		4
39	LV45719-001A	PU FPC SHEET		1
802	-----	CLAMP ARM ASSY	NO SERVICE PART	1
805	-----	BOTTOM CHASSIS	NO SERVICE PART	1
806	-----	TOP CHASSIS	NO SERVICE PART	1
810	-----	CLAMPER CUSHION	NO SERVICE PART	1
811	-----	CL A CUSHION B	NO SERVICE PART	1
812	-----	CL A CUSHION A	NO SERVICE PART	1
825	-----	ROLLER ARM	NO SERVICE PART	1
830	-----	GEAR BKT	NO SERVICE PART	1
840	-----	SPACER(H)	NO SERVICE PART	2
841	-----	BOTTOM SHEET	NO SERVICE PART	1
842	-----	DVD MECHA PWB ASSY	NO SERVICE PART	1
847	-----	LOADING MOTOR	NO SERVICE PART	1
848	-----	SIN TWIST WIRE	NO SERVICE PART	1
849	-----	SIN TWIST WIRE	NO SERVICE PART	1
850	-----	WORM GEAR	NO SERVICE PART	1
851	-----	TM CHASSIS ASSY	NO SERVICE PART	1
852	-----	FEED MOTOR	NO SERVICE PART	1
853	-----	SPINDLE MOTOR	NO SERVICE PART	1
854	-----	SUB SHAFT	NO SERVICE PART	1
855	-----	SUB SHAFT SP	NO SERVICE PART	1
856	-----	DVD OPT.PICKUP	NO SERVICE PART	1
857	-----	PICKUP ARM	NO SERVICE PART	1
858	-----	PICKUP ARM SP	NO SERVICE PART	1
859	-----	SHAFT	NO SERVICE PART	1
860	-----	MAIN SHAFT SP 2	NO SERVICE PART	1
861	-----	MAIN SHAFT SP	NO SERVICE PART	1
862	-----	TM COVER MAIN	NO SERVICE PART	1
863	-----	TM COVER SUB	NO SERVICE PART	1
864	-----	ROLLER SHAFT	NO SERVICE PART	1
865	-----	ROLLER GEAR	NO SERVICE PART	1
866	-----	SCREW	NO SERVICE PART	1

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
MAIN PWB ASSY(XJ1-221x-0x) <XJ1>						
	IC31	MP9943AGQ	ANALOG IC		1	
	IC51	MP9943AGQ	ANALOG IC		1	
	IC52	TC7SH08FUJC	MOS IC		1	
	IC91	MP9942AGJ	ANALOG IC		1	
	IC92	TC7SH08FUJC	MOS IC		1	
	IC93	INA199B3DCK	ANALOG IC		1	
	IC94	BU7252FVM	MOS IC		1	
	IC131	MP9942AGJ	ANALOG IC		1	
	IC132	TC7SH08FUJC	MOS IC		1	
	IC133	INA199B3DCK	ANALOG IC		1	
	IC201	NJM2819ADL333	BIPOLAR IC		1	
	IC202	TC7SET04FUJC	MOS IC		1	
	IC205	XC6223B331P-G	ANALOG IC		1	
	IC301	W3F-0388-00	MCU IC		1	
	IC302	XC6120N282N-G	MOS IC		1	
	IC303	TC7SH08FUJC	MOS IC		1	
	IC304	BR24T32FVT-W	ROM IC		1	
	IC305	NJU7108F3	MOS IC		1	
	IC307	TC7SH08FUJC	MOS IC		1	E1,X1,M1,M2
	IC501	AK7738VQ	MOS IC		1	
	IC502	AK4388AET	ANALOG IC		1	
	IC503	AK4388AET	ANALOG IC		1	
	IC506	AK4388AET	ANALOG IC		1	
	IC507	XC6209B502P-G	MOS IC		1	
	IC508	BU33TD3WG	MOS IC		1	
	IC601	NJM4580CV	ANALOG IC		1	
	IC602	NJM2871BF05	ANALOG IC		1	
	IC721	TC7SH08FUJC	MOS IC		1	
	IC722	TC7SZ125FUJC	MOS IC		1	
	IC723	TC7SET08FUJC	MOS IC		1	
	IC731	TC7SH08FUJC	MOS IC		1	K0
	IC732	TC7SZ125FUJC	MOS IC		1	K0
	IC734	TC7SET08FUJC	MOS IC		1	K0
	IC871	NJW1341VC3	MOS IC		1	
	IC872	XC6209B502P-G	MOS IC		1	
	IC921	UBX-M8030-KT	MOS IC		1	
	IC923	XC6223B331P-G	ANALOG IC		1	
	IC924	BU18TD3WG	MOS IC		1	
	IC951	BD00KA5WFP	MOS IC		1	
	Q1	MCQ4435	FET		1	
	Q3	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q4	LSCR523EBFS8	TRANSISTOR		1	
	Q5	LSAR523EBFS8	TRANSISTOR		1	
	Q6	LTA014TEBFS8	DIGI TRANSISTOR		1	
	Q7	LSCR523EBFS8	TRANSISTOR		1	
	Q8	LSAR523EBFS8	TRANSISTOR		1	
	Q9	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q10	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q11	LSCR523EBFS8	TRANSISTOR		1	
	Q12	LSAR523EBFS8	TRANSISTOR		1	
	Q51	LTC044EEBFS8	DIGI TRANSISTOR		1	
	Q52	LTA014YEBFS8	DIGI TRANSISTOR		1	
	Q91	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q110	LTA014YEBFS8	DIGI TRANSISTOR		1	
	Q112	LSCR523EBFS8	TRANSISTOR		1	
	Q113	LSAR523EBFS8	TRANSISTOR		1	
	Q114	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q115	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q116	LTC044EEBFS8	DIGI TRANSISTOR		1	
	Q117	LTA014YEBFS8	DIGI TRANSISTOR		1	
	Q131	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q152	LSCR523EBFS8	TRANSISTOR		1	
	Q153	LSAR523EBFS8	TRANSISTOR		1	
	Q154	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q155	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q156	LTC044EEBFS8	DIGI TRANSISTOR		1	
	Q157	LTA014YEBFS8	DIGI TRANSISTOR		1	
	Q301	2SB1689	TRANSISTOR		1	
	Q302	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q303	LSAR523EBFS8	TRANSISTOR		1	
	Q304	LSAR523EBFS8	TRANSISTOR		1	
	Q305	LTC044EEBFS8	DIGI TRANSISTOR		1	
	Q306	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q307	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q312	LTA014TEBFS8	DIGI TRANSISTOR		1	
	Q313	LTC014EEBFS8	DIGI TRANSISTOR		1	
	Q314	LTC014EEBFS8	DIGI TRANSISTOR		1	
	Q315	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q316	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q317	LSCR523EBFS8	TRANSISTOR		1	
	Q318	LSAR523EBFS8	TRANSISTOR		1	
	Q319	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q501	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q502	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q801	RE1C002ZP	FET		1	E1,X1,M1,M2
	Q802	RE1C002ZP	FET		1	E1,X1,M1,M2
	Q803	LTC014YEBFS8	DIGI TRANSISTOR		1	E1,X1,M1,M2
	Q821	LSCR523UBFS8	TRANSISTOR		1	
	Q921	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q922	LTC014YEBFS8	DIGI TRANSISTOR		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	D1	RB080LAM-30	SCHOTTKY DIODE		1	
	D2	1SS355VM	DIODE		1	
	D3	UDZV16B	ZENER DIODE		1	
	D5	UDZV6.2B	ZENER DIODE		1	
	D6	UDZV6.2B	ZENER DIODE		1	
	D91	UDZV6.2B	ZENER DIODE		1	
	D92	DAP202UM	DIODE		1	
	D131	UDZV6.2B	ZENER DIODE		1	
	D201	GS1J-LTP	DIODE		1	
	D202	1SS355VM	DIODE		1	
	D301	1SS355VM	DIODE		1	
	D601	UDZV11B	ZENER DIODE		1	
	D602	UDZV11B	ZENER DIODE		1	
	D603	1SS355VM	DIODE		1	
	D721	UDZV5.6B	ZENER DIODE		1	
	D722	UDZV5.6B	ZENER DIODE		1	
	D732	UDZV5.6B	ZENER DIODE		1	K0
	D733	UDZV5.6B	ZENER DIODE		1	K0
	D734	1SS355VM	DIODE		1	K0
	D801	DAN202UM	DIODE		1	E1,X1,M1,M2
	D921	1SS355VM	DIODE		1	
	D951	1SS355VM	DIODE		1	
	C1	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C2	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C4	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C7	CD040CP1C222M	E CAPACITOR	2200uF 16V M	1	
	C31	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C32	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C33	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C34	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C35	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C36	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C37	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C38	CK73HXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C40	CC73HCH1H560J	C CAPACITOR	56pF 50V J	1	
	C41	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C43	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C44	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C48	CC73HCH1H220J	C CAPACITOR	22pF 50V J	1	
	C51	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C52	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C53	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C54	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C55	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C56	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C57	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C58	CK73HXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C60	CC73HCH1H560J	C CAPACITOR	56pF 50V J	1	
	C61	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C63	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C64	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C65	CC73HCH1H050C	C CAPACITOR	5pF 50V C	1	
	C66	CC73HCH1H050C	C CAPACITOR	5pF 50V C	1	
	C67	CC73HCH1H050C	C CAPACITOR	5pF 50V C	1	
	C69	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C70	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C91	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C92	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C93	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C94	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C95	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C96	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C97	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C98	CK73HXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C100	CC73HCH1H560J	C CAPACITOR	56pF 50V J	1	
	C101	CK730DT1C476K	C CAPACITOR	47uF 16V K	1	
	C103	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C104	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C105	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C110	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C111	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C112	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C113	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C114	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C131	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C132	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C133	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C134	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C135	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C136	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C137	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C138	CK73HXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C140	CC73HCH1H560J	C CAPACITOR	56pF 50V J	1	
	C141	CK730DT1C476K	C CAPACITOR	47uF 16V K	1	
	C143	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C144	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C145	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C150	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C151	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C152	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C154	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C201	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C202	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C203	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C204	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C210	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C211	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C251	CK730DT1C476K	C CAPACITOR	47uF 16V K	1	
	C252	CK730DT1C476K	C CAPACITOR	47uF 16V K	1	
	C253	CK730DT1C476K	C CAPACITOR	47uF 16V K	1	
	C254	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C255	CK730DT1C476K	C CAPACITOR	47uF 16V K	1	
	C256	CK730DT1C476K	C CAPACITOR	47uF 16V K	1	
	C257	CK730DT1C476K	C CAPACITOR	47uF 16V K	1	
	C258	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C261	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C262	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C263	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C303	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C304	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C305	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C306	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C307	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C308	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C309	CC73HCH1H330J	C CAPACITOR	33pF 50V J	1	
	C310	CC73HCH1H040C	C CAPACITOR	4pF 50V C	1	
	C311	CC73HCH1H080D	C CAPACITOR	8pF 50V D	1	
	C312	CC73HCH1H080D	C CAPACITOR	8pF 50V D	1	
	C313	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C314	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C315	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C316	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C317	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C318	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C319	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C320	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C321	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C322	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C324	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C329	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C330	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C331	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C335	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	E1,X1,M1,M2
	C339	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C340	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C341	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C342	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C343	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C344	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C345	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C346	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C501	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C502	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C503	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C504	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C505	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C506	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C507	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C512	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C513	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C514	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C515	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C520	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C521	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C522	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C523	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C524	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C525	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C526	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C527	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C528	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C529	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C530	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C531	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C532	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C533	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C534	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C535	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C536	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C537	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C538	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C539	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C540	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C541	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C542	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C543	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C544	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C545	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C549	CC73HCH1H120J	C CAPACITOR	12pF 50V J	1	
	C550	CC73HCH1H120J	C CAPACITOR	12pF 50V J	1	
	C551	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C552	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C553	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C554	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C558	CK73HXR1H332K	C CAPACITOR	3300pF 50V K	1	
	C559	CK73HXR1H332K	C CAPACITOR	3300pF 50V K	1	
	C560	CK73HXR1H332K	C CAPACITOR	3300pF 50V K	1	
	C561	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C562	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C563	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C564	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C565	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C566	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C567	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C568	CK73HXR1H222K	C CAPACITOR	2200pF 50V K	1	
	C569	CK73HXR0J474K	C CAPACITOR	0.47uF 6.3V K	1	
	C571	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	
	C603	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C605	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C606	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C607	CC73HCH1H220J	C CAPACITOR	22pF 50V J	1	
	C609	CC73HCH1H220J	C CAPACITOR	22pF 50V J	1	
	C611	CK73HXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C613	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C615	CK73HXR1A683K	C CAPACITOR	0.068uF 10V K	1	
	C616	CK73HXR1A683K	C CAPACITOR	0.068uF 10V K	1	
	C617	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C621	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C622	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C623	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C721	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C722	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C723	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C734	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	K0
	C736	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	K0
	C737	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	K0
	C739	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	K0
	C751	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C752	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C753	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C760	CK73HXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C761	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C791	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C792	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C793	CK73HXR1E223K	C CAPACITOR	0.022uF 25V K	1	
	C794	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C795	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C801	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	E1,X1,M1,M2
	C821	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C832	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C833	CK73HXR1E224K	C CAPACITOR	0.22uF 25V K	1	
	C879	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C881	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C882	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C884	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C885	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C887	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C888	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C890	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C891	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C892	CE32BJ1C470M	E CAPACITOR	47uF 16V M	1	
	C893	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C895	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C896	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C897	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C898	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C899	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C921	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C922	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C923	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C924	CC730BP1H1R8B	C CAPACITOR	1.8pF 50V M	1	
	C925	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C926	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C927	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C930	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C931	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C932	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C933	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C934	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C936	CC73HCH1H070D	C CAPACITOR	7pF 50V D	1	
	C937	CC73HCH1H060D	C CAPACITOR	6pF 50V D	1	
	C938	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C940	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C941	CC73HCH1H120J	C CAPACITOR	12pF 50V J	1	
	C942	CC73HCH1H120J	C CAPACITOR	12pF 50V J	1	
	C943	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C951	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C952	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C953	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C954	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C955	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C956	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C957	CC73HCH1H020C	C CAPACITOR	2pF 50V C	1	
	C958	CC73HCH1H040C	C CAPACITOR	4pF 50V C	1	
	C960	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C961	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C962	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C963	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C964	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C965	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C966	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C967	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C968	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C969	CC73HCH1H150J	C CAPACITOR	15pF 50V J	1	
	C970	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C971	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C972	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C973	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C974	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C975	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C976	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	R1	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	
	R2	RK73GB2A202J	MG RESISTOR	2kΩ 1/10W J	1	
	R3	RK73HB1J334J	MG RESISTOR	330kΩ 1/16W J	1	
	R4	RK73HH1J753D	MG RESISTOR	75kΩ 1/16W D	1	
	R5	RK73HH1J753D	MG RESISTOR	75kΩ 1/16W D	1	
	R6	RK73HH1J333D	MG RESISTOR	33kΩ 1/16W D	1	
	R7	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R8	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R9	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R10	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R11	RK73HH1J134D	MG RESISTOR	130kΩ 1/16W D	1	
	R12	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R13	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R14	RK73HH1J304D	MG RESISTOR	300kΩ 1/16W D	1	
	R15	RK73HH1J304D	MG RESISTOR	300kΩ 1/16W D	1	
	R16	RK73HH1J822D	MG RESISTOR	8.2kΩ 1/16W D	1	
	R17	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R18	RK73HH1J683D	MG RESISTOR	68kΩ 1/16W D	1	
	R19	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R20	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R31	RK73GB2A200J	MG RESISTOR	20Ω 1/10W J	1	
	R33	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R34	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R35	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R36	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R37	RK73HH1J222D	MG RESISTOR	2.2kΩ 1/16W D	1	
	R38	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	
	R39	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R40	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R51	RK73GB2A200J	MG RESISTOR	20Ω 1/10W J	1	
	R53	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R54	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R55	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R56	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R57	RK73HH1J222D	MG RESISTOR	2.2kΩ 1/16W D	1	
	R58	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	
	R59	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R60	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R62	RK73HH1J100D	MG RESISTOR	10Ω 1/16W D	1	
	R64	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R65	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R66	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R91	RK73GB2A200J	MG RESISTOR	20Ω 1/10W J	1	
	R92	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R94	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R95	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R96	RK73HH1J100D	MG RESISTOR	10Ω 1/16W D	1	
	R97	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R98	RK73HH1J222D	MG RESISTOR	2.2kΩ 1/16W D	1	
	R99	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	
	R100	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R101	RK73EB2E151J	MG RESISTOR	150Ω 1/4W J	1	
	R102	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R104	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R105	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R106	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R107	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R110	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R111	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R112	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R113	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R114	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R115	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R116	RK73HH1J363D	MG RESISTOR	36kΩ 1/16W D	1	
	R117	RK73HH1J564D	MG RESISTOR	560kΩ 1/16W D	1	
	R118	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R119	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R120	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R121	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R122	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R123	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R125	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R126	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R127	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R131	RK73GB2A200J	MG RESISTOR	20Ω 1/10W J	1	
	R132	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R134	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R135	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R136	RK73HH1J100D	MG RESISTOR	10Ω 1/16W D	1	
	R137	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R138	RK73HH1J222D	MG RESISTOR	2.2kΩ 1/16W D	1	
	R139	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	
	R140	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R141	RK73EB2E151J	MG RESISTOR	150Ω 1/4W J	1	
	R142	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R144	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R145	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R146	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R147	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R150	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R151	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R152	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R153	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R154	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R155	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R156	RK73HH1J363D	MG RESISTOR	36kΩ 1/16W D	1	
	R157	RK73HH1J564D	MG RESISTOR	560kΩ 1/16W D	1	
	R158	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R159	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R160	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R161	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R162	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R165	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R166	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R167	RZ73F0CH30LJ	RESISTOR	0.03Ω 1/3W J	1	
	R188	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R189	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R202	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R203	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R206	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R207	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R208	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R209	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R210	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R211	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R215	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R216	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R261	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R262	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R263	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R264	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R265	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R266	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R301	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R306	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R307	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R308	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R309	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R310	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R311	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R312	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R313	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R314	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R315	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R316	RK73HB1J154J	MG RESISTOR	150kΩ 1/16W J	1	
	R317	RK73HB1J154J	MG RESISTOR	150kΩ 1/16W J	1	
	R318	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R320	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R321	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R322	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R323	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R324	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R325	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R326	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R327	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R329	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R330	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R331	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R332	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R333	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R334	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R335	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R337	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R338	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R339	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R340	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R341	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R342	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R343	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R344	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R347	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R348	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R349	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R352	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R355	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R357	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R358	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R359	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R360	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R361	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R362	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R363	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R365	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R366	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R367	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R368	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R369	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R370	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R371	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R372	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R373	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R374	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R375	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R376	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R378	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R379	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R380	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R381	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R382	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R383	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R384	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R385	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R386	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R387	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R388	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R389	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R390	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R391	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R392	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R393	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R394	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R396	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R397	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R398	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R399	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R400	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R401	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R403	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R404	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R405	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R407	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R409	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R410	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R411	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R412	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R413	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R415	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R417	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R420	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R421	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	
	R422	RK73HB1J821J	MG RESISTOR	820Ω 1/16W J	1	
	R423	RK73HB1J271J	MG RESISTOR	270Ω 1/16W J	1	
	R424	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R425	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R426	RK73HB1J823J	MG RESISTOR	82kΩ 1/16W J	1	
	R427	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R428	RK73HB1J124J	MG RESISTOR	120kΩ 1/16W J	1	
	R429	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R430	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R431	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R432	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R433	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R434	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R437	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R439	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1,X1,M1,M2
	R440	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1,X1,M1,M2
	R443	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R444	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R446	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R447	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R448	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R449	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R450	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R503	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R504	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R506	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R507	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R510	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R511	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R512	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R513	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R514	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R515	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R518	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R519	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R520	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R521	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R522	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R523	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R524	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R531	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R532	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R533	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R534	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R535	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R536	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R538	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R539	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R540	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R541	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R542	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R543	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R544	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R545	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R546	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R547	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R548	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E1,X1,M1,M2
	R549	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E1,X1,M1,M2
	R550	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R551	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R552	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R553	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R554	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R555	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R556	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R557	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E1,X1,M1,M2
	R558	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R559	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R560	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R561	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R562	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R563	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R564	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R565	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R566	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R567	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R568	RK73HB1J181J	MG RESISTOR	180Ω 1/16W J	1	
	R569	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R570	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R573	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R574	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R575	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R576	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R577	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R578	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R579	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R582	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0
	R583	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0
	R584	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0
	R585	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R586	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R588	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R589	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R590	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R591	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R592	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R593	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R594	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R595	RK73HH1J221D	MG RESISTOR	220Ω 1/16W D	1	
	R596	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R599	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R600	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R604	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R609	RK73HB1J203J	MG RESISTOR	20kΩ 1/16W J	1	
	R610	RK73HB1J203J	MG RESISTOR	20kΩ 1/16W J	1	
	R611	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R612	RK73HB1J304J	MG RESISTOR	300kΩ 1/16W J	1	
	R614	RK73HB1J304J	MG RESISTOR	300kΩ 1/16W J	1	
	R615	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R616	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R617	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R618	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R620	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R621	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R622	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R624	RK73HB1J752J	MG RESISTOR	7.5kΩ 1/16W J	1	
	R625	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R638	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R721	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R722	RK73GB2A220J	MG RESISTOR	22Ω 1/10W J	1	
	R724	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R725	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R726	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R727	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R728	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R734	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0
	R735	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	K0
	R741	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	K0
	R743	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R750	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	K0
	R754	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R755	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R756	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R757	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R758	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R759	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R760	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R791	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R792	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R793	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R794	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R795	RK73HB1J4R7J	MG RESISTOR	4.7Ω 1/16W J	1	
	R796	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R801	RK73GB2A470J	MG RESISTOR	47Ω 1/10W J	1	E1,X1,M1,M2
	R802	RK73GB2A470J	MG RESISTOR	47Ω 1/10W J	1	E1,X1,M1,M2
	R803	RK73GH2A472D	MG RESISTOR	4.7kΩ 1/10W D	1	
	R804	RK73GH2A472D	MG RESISTOR	4.7kΩ 1/10W D	1	
	R805	RK73EB2E511J	MG RESISTOR	510Ω 1/4W J	1	E1,X1,M1,M2
	R806	RK73EB2E511J	MG RESISTOR	510Ω 1/4W J	1	E1,X1,M1,M2
	R807	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	
	R808	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	
	R809	RK73HB1J681J	MG RESISTOR	680Ω 1/16W J	1	
	R810	RK73HB1J681J	MG RESISTOR	680Ω 1/16W J	1	
	R811	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	E1,X1,M1,M2
	R812	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	E1,X1,M1,M2
	R813	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	E1,X1,M1,M2
	R814	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	E1,X1,M1,M2
	R823	RK73HB1J303J	MG RESISTOR	30kΩ 1/16W J	1	
	R824	RK73HH1J750D	MG RESISTOR	75Ω 1/16W D	1	
	R825	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R826	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R827	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R829	RK73HB1J303J	MG RESISTOR	30kΩ 1/16W J	1	
	R839	RK73HB1J750J	MG RESISTOR	75Ω 1/16W J	1	
	R871	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R873	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R874	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R876	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R877	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R878	RK73HH1J391D	MG RESISTOR	390Ω 1/16W D	1	
	R879	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R884	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R886	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R887	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R888	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R889	RK73HH1J683D	MG RESISTOR	68kΩ 1/16W D	1	
	R890	RK73HH1J683D	MG RESISTOR	68kΩ 1/16W D	1	
	R891	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R921	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R922	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R923	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R926	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R929	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R930	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R938	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R939	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R940	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R951	RK73HH1J753D	MG RESISTOR	75kΩ 1/16W D	1	
	R952	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R953	RK73HH1J303D	MG RESISTOR	30kΩ 1/16W D	1	
	R954	RK73GB2A330J	MG RESISTOR	33Ω 1/10W J	1	
	R955	RK73GB2A391J	MG RESISTOR	390Ω 1/10W J	1	
	R956	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R957	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R958	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R959	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R960	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R961	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R962	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	
	R964	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R967	RK73HB1J820J	MG RESISTOR	82Ω 1/16W J	1	
	R969	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R971	RK73HB1J820J	MG RESISTOR	82Ω 1/16W J	1	
	R973	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R975	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R976	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R977	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R979	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R980	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R981	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R982	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R983	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R984	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R985	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R986	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R997	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	RA791	RK74GB1J301J	NET RESISTOR	300Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	RA821	RK74GB1J301J	NET RESISTOR	300Ω 1/16W J	1	
	RA822	RK74GB1J301J	NET RESISTOR	300Ω 1/16W J	1	
	L32	NQR0723-001X	CHOKO COIL	10uF	1	
	L52	NQR0723-001X	CHOKO COIL	10uF	1	
	L92	NQR0723-001X	CHOKO COIL	10uF	1	
	L132	NQR0723-001X	CHOKO COIL	10uF	1	
	L301	LB73G0FK-001	CHIP FERRITE		1	
	L751	LR79Z0AG100M	CHIP INDUCTOR	10uH	1	
	L871	LR73Z0AC100K	CHIP INDUCTOR	10uH	1	
	L921	LK73H0AM27NJ	M.CHIP INDUCTOR	27nH	1	
	L922	LR79H0HU7N5G	CHIP INDUCTOR		1	
	L925	LB73H0DZ-001	CHIP FERRITE		1	
	L951	LB73G0AM-004	CHIP FERRITE		1	
	L952	LK73H0AM2N2S	M.CHIP INDUCTOR		1	
	L953	LB73G0AM-004	CHIP FERRITE		1	
	L954	LB73G0AM-004	CHIP FERRITE		1	
	L955	LB73G0AM-004	CHIP FERRITE		1	
	L956	LB73G0AM-004	CHIP FERRITE		1	
	A951	W0C-0191-00	CIRCUIT MODULE		1	
	AT951	T9A-0052-00	CHIP ANTENNA		1	
	CN1	QGA2001F1-04	W TO B CONNE	W-B (1-4)	1	
	CN201	QGA1002C1-04X	W TO B CONNE	W-B (1-4)	1	
	CN251	QGA2001C1-04	W TO B CONNE	W-B (1-4)	1	
	CN261	EC710AM-0515A	FFC FPC CONNE	15P	1	
	CN301	QGA1002F1-08X	W TO B CONNE	W-B (1-8)	1	
	CN601	EB770AX-05C0A	B TO B CONNE	120P	1	
	CN602	EC720AA-0550A	FFC FPC CONNE	50P	1	
	CN603	EC720AA-0560A	FFC FPC CONNE	60P	1	
	CN721	EA120CE-2503A	W TO B CONNE	3P	1	
	CN731	QGA2021F1-04	W TO B CONNE	W-B (1-4)	1	K0
	CN751	EC710AM-0535A	FFC FPC CONNE	35P	1	
	CN802	QGA2001C1-04	W TO B CONNE	W-B (1-4)	1	
	CN951	EC710AM-0512A	FFC FPC CONNE		1	
△	F1	FZA10BZ-7R0	FUSE (CC)	63A	1	
△	F721	F53-0513-08	PATTERN FUSE	4A	1	
△	F731	F53-0513-08	PATTERN FUSE	4A	1	
△	F732	F53-0513-08	PATTERN FUSE	4A	1	
△	F751	FZA10BF-1R0	FUSE (CC)	1A	1	
△	F791	F53-0513-08	PATTERN FUSE	4A	1	
△	F801	F53-0513-08	PATTERN FUSE	4A	1	
△	F832	F53-0513-08	PATTERN FUSE	4A	1	
	J261	NNZ0256-001X	SD CARD CONNE		1	
	J601	QNS0307-001	3.5 JACK		1	
	J791	QNS0291-001	3.5 JACK		1	
	J801	QNS0307-001	3.5 JACK		1	E1,X1,M1,M2
	J921	E5J-0023-00	R.RECEPTACLE	3P	1	
	VA721	SDV1005A14//0	VARIISTOR		1	
	VA722	SDV1005A14//0	VARIISTOR		1	
	VA734	SDV1005A14//0	VARIISTOR		1	K0
	VA735	SDV1005A14//0	VARIISTOR		1	K0
	VA791	SDV1005A14//0	VARIISTOR		1	
	VA792	SDV1005A14//0	VARIISTOR		1	
	VA793	SDV1005E18//1	VARIISTOR		1	
	VA794	SDV1005E18//1	VARIISTOR		1	
	VA801	SDV1005E18//2	VARIISTOR		1	E1,X1,M1,M2
	VA802	SDV1005E18//2	VARIISTOR		1	E1,X1,M1,M2
	VA803	SDV1005E18//2	VARIISTOR		1	E1,X1,M1,M2
	VA823	SDV1005E18//1	VARIISTOR		1	
	VA824	SDV1005E18//1	VARIISTOR		1	
	VA835	SDV1005E18//1	VARIISTOR		1	
	VA922	F0K-0040-00	SURGE ABSORBER		1	
	X301	NAX1248-001X	CRYSTAL		1	
	X302	NAX1137-001X	CRYSTAL		1	
	X501	NAX1204-001X	CRYSTAL		1	
	X921	L7H-0098-00	TCXO		1	
	X922	NAX1248-001X	CRYSTAL		1	
	X951	L7H-0052-00	SPXO		1	
SUB PWB ASSY(XJ4-008E-00) <XJ4>						
	IC106	BD12KA5WFP	ANALOG IC		1	E1,X1,M1,M2
	IC701	IT68013FN/BX	MOS IC		1	E1,X1,M1,M2
	Q702	2SK3019	FET		1	E1,X1,M1,M2
	D701	DA2J101	DIODE		1	E1,X1,M1,M2
	C117	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	E1,X1,M1,M2
	C118	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	E1,X1,M1,M2
	C119	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	E1,X1,M1,M2
	C121	CK73GXR0J106K	C CAPACITOR	10uF 6.3V K	1	E1,X1,M1,M2
	C139	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C140	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	E1,X1,M1,M2
	C146	CK73HXR1H473K	C CAPACITOR	0.047uF 50V K	1	E1,X1,M1,M2
	C700	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C702	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C703	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	E1,X1,M1,M2
	C704	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C705	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C706	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	E1,X1,M1,M2
	C707	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C708	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C709	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C710	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C711	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C712	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C713	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C714	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C715	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C716	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C717	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C718	CC73HCH1H080D	C CAPACITOR	8pF 50V D	1	E1,X1,M1,M2
	C719	CC73HCH1H080D	C CAPACITOR	8pF 50V D	1	E1,X1,M1,M2
	C720	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C721	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C722	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1,M1,M2
	C723	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	E1,X1,M1,M2
	C724	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	E1,X1,M1,M2
	C725	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	E1,X1,M1,M2
	C726	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	E1,X1,M1,M2
	C727	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	E1,X1,M1,M2
	C728	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	E1,X1,M1,M2
	R4	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	E1,X1,M1,M2
	R122	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E1,X1,M1,M2
	R150	RK73HB1J225J	MG RESISTOR	2.2MΩ 1/16W J	1	E1,X1,M1,M2
	R154	RK73FB2B000J	MG RESISTOR	0Ω 1/8W J	1	E1,X1,M1,M2
	R169	RK73HB1J304J	MG RESISTOR	300kΩ 1/16W J	1	E1,X1,M1,M2
	R186	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E1,X1,M1,M2
	R187	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E1,X1,M1,M2
	R188	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E1,X1,M1,M2
	R189	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E1,X1,M1,M2
	R195	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E1,X1,M1,M2
	R196	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E1,X1,M1,M2
	R701	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R702	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R703	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R705	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E1,X1,M1,M2
	R706	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1,X1,M1,M2
	R708	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R710	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R711	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R713	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R715	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R716	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1,X1,M1,M2
	R717	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1,X1,M1,M2
	R718	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R719	RK73HB1J302J	MG RESISTOR	3kΩ 1/16W J	1	E1,X1,M1,M2
	R720	RK73HB1J152J	MG RESISTOR	1.5kΩ 1/16W J	1	E1,X1,M1,M2
	R731	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R732	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R735	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E1,X1,M1,M2
	R741	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	E1,X1,M1,M2
	R750	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	E1,X1,M1,M2
	R776	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1,M1,M2
	R778	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	E1,X1,M1,M2
	R779	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	E1,X1,M1,M2
	RA700	RK74HB1J330J	NET RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	RA701	RK74HB1J330J	NET RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	RA702	RK74HB1J330J	NET RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	RA703	RK74HB1J330J	NET RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	RA704	RK74HB1J330J	NET RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	RA705	RK74HB1J330J	NET RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	L1	LB73G0ED-004	CHIP FERRITE		1	E1,X1,M1,M2
	L2	LB73G0ED-004	CHIP FERRITE		1	E1,X1,M1,M2
	CN100	QGB0803J2-40X	B TO B CONNE	B-B (1-40)	1	E1,X1,M1,M2
	J100	NNZ0292-001X	HDMI CONNECTOR		1	E1,X1,M1,M2
	VA103	EZJP0270EA	VARIATOR		1	E1,X1,M1,M2
	VA104	AVRL101A1R1NB	VARIATOR		1	E1,X1,M1,M2
	VA106	EZJP0270EA	VARIATOR		1	E1,X1,M1,M2
	VA107	AVRL101A1R1NB	VARIATOR		1	E1,X1,M1,M2
	VA108	AVRL101A1R1NB	VARIATOR		1	E1,X1,M1,M2
	VA109	AVRL101A1R1NB	VARIATOR		1	E1,X1,M1,M2
	VA110	NAF0031-001X	ESD SUPPRESSOR		1	E1,X1,M1,M2
	VA111	NAF0031-001X	ESD SUPPRESSOR		1	E1,X1,M1,M2
	X700	L7J-0052-00	QUARTZ CRYSTAL		1	E1,X1,M1,M2
DIGITAL IO PWB ASSY(XJA-055x-0x) <XJA>						
	IC501	TCC8974F-0AX1	MPU IC	BGA	1	
	IC503	-----	ROM IC	NO SERVICE PART	1	
	IC525	-----	ROM IC	NO SERVICE PART	1	E1
	IC525	-----	ROM IC	NO SERVICE PART	1	X1,M1,M2
	IC525	-----	ROM IC	NO SERVICE PART	1	K0
	IC531	K4B4G0846EBCA	DRAM IC	BGA	1	
	IC532	K4B4G0846EBCA	DRAM IC	BGA	1	
	IC541	ML86251LAZ07F	MOS IC		1	
	IC543	TC7WBL3305CFK	MOS IC		1	
	IC544	TC7SH08FUJC	MOS IC		1	
	IC563	MF1337S395901	MCU IC		1	
	IC571	TPS2543RTE	MOS IC		1	
	IC573	CYUSB230268LI	MOS IC		1	
	IC574	XC6223B121P-G	ANALOG IC		1	
	IC591	MP9943AGQ	ANALOG IC		1	
	IC592	MP9943AGQ	ANALOG IC		1	
	IC593	BD33KA5WFP	MOS IC		1	
	IC594	TC7SH08FUJC	MOS IC		1	
	IC595	BU18TD3WG	MOS IC		1	
	IC597	BD15KA5WFP	MOS IC		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
		IC601	MP9943AGQ	ANALOG IC	1	
		IC602	MP9942AGJ	ANALOG IC	1	
		IC631	NJM2561F1	BIPOLAR IC	1	
		IC701	K4B4G0846EBCA	DRAM IC	1	
		IC702	K4B4G0846EBCA	DRAM IC	1	
		Q5401	LSCR523EBFS8	TRANSISTOR	1	
		Q5402	LSCR523EBFS8	TRANSISTOR	1	
		Q5403	LSCR523EBFS8	TRANSISTOR	1	
		Q5404	LSCR523EBFS8	TRANSISTOR	1	
		Q5603	LTC014YEBFS8	DIGI TRANSISTOR	1	
		Q5604	LTC014YEBFS8	DIGI TRANSISTOR	1	
		Q5605	LTC014YEBFS8	DIGI TRANSISTOR	1	
		Q5606	LTC014YEBFS8	DIGI TRANSISTOR	1	
		Q5607	LSAR523EBFS8	TRANSISTOR	1	
		Q5608	2SC4617EB/QR/	TRANSISTOR	1	
		Q5801	LTA014YEBFS8	DIGI TRANSISTOR	1	E1,X1,M1,M2
		Q5871	LTA014YEBFS8	DIGI TRANSISTOR	1	
		Q5872	LTC014YEBFS8	DIGI TRANSISTOR	1	
		Q5901	LTA014EEBFS8	DIGI TRANSISTOR	1	
		Q5902	LSCR523EBFS8	TRANSISTOR	1	
		Q6001	LTC014YEBFS8	DIGI TRANSISTOR	1	
		Q6301	LTC014YEBFS8	DIGI TRANSISTOR	1	
		D5871	QSMR-C13SBCMN	LED	1	
		C631	CK73HXR1C105K	C CAPACITOR	1	
		C632	CK73HXR1A104K	C CAPACITOR	1	
		C633	CK73FXR1C106K	C CAPACITOR	1	
		C5001	CK73HXR1A104K	C CAPACITOR	1	
		C5002	CK73HXR1A104K	C CAPACITOR	1	
		C5003	CK73HXR1A104K	C CAPACITOR	1	
		C5004	CK73HXR1A104K	C CAPACITOR	1	
		C5005	CK73HXR1A104K	C CAPACITOR	1	
		C5006	CK73HXR1A104K	C CAPACITOR	1	
		C5007	CK73HXR1A104K	C CAPACITOR	1	
		C5008	CK73HXR1A104K	C CAPACITOR	1	
		C5009	CK73HXR1A104K	C CAPACITOR	1	
		C5010	CK73HXR1A104K	C CAPACITOR	1	
		C5011	CK73HXR1A104K	C CAPACITOR	1	
		C5012	CK73HXR1A104K	C CAPACITOR	1	
		C5013	CK73HXR1A104K	C CAPACITOR	1	
		C5014	CK73HXR1A104K	C CAPACITOR	1	
		C5015	CK73HXR1A104K	C CAPACITOR	1	
		C5016	CK73HXR1A104K	C CAPACITOR	1	
		C5017	CK73HXR1A104K	C CAPACITOR	1	
		C5018	CK73HXR1A104K	C CAPACITOR	1	
		C5019	CK73HXR1A104K	C CAPACITOR	1	
		C5020	CK73HXR1A104K	C CAPACITOR	1	
		C5021	CK73HXR1A104K	C CAPACITOR	1	
		C5022	CK73HXR1A104K	C CAPACITOR	1	
		C5023	CK73HXR1A104K	C CAPACITOR	1	
		C5024	CK73HXR1A104K	C CAPACITOR	1	
		C5025	CK73HXR1A104K	C CAPACITOR	1	
		C5026	CK73HXR1A104K	C CAPACITOR	1	
		C5027	CK73HXR1A104K	C CAPACITOR	1	
		C5028	CK73HXR1A104K	C CAPACITOR	1	
		C5029	CK73HXR1A104K	C CAPACITOR	1	
		C5030	CK73HXR1A104K	C CAPACITOR	1	
		C5031	CK73HXR1A104K	C CAPACITOR	1	
		C5032	CK73HXR1A104K	C CAPACITOR	1	
		C5033	CK73HXR1A104K	C CAPACITOR	1	
		C5034	CK73HXR1A104K	C CAPACITOR	1	
		C5035	CK73HXR1A104K	C CAPACITOR	1	
		C5036	CK73HXR1A104K	C CAPACITOR	1	
		C5037	CK73HXR1A104K	C CAPACITOR	1	
		C5038	CK73HXR1A104K	C CAPACITOR	1	
		C5039	CC73HCH1H060D	C CAPACITOR	1	
		C5040	CC73HCH1H060D	C CAPACITOR	1	
		C5041	CK73HXR1A104K	C CAPACITOR	1	
		C5042	CK73HXR1A104K	C CAPACITOR	1	
		C5043	CK73HXR1A104K	C CAPACITOR	1	
		C5045	CK73HXR1A104K	C CAPACITOR	1	
		C5046	CK73HXR1A104K	C CAPACITOR	1	
		C5050	CK73HXR1A104K	C CAPACITOR	1	
		C5051	CK73HXR1A104K	C CAPACITOR	1	
		C5052	CK73HXR1A104K	C CAPACITOR	1	
		C5053	CK73HXR1A104K	C CAPACITOR	1	
		C5054	CK73HXR1A104K	C CAPACITOR	1	
		C5055	CK73HXR1A104K	C CAPACITOR	1	
		C5056	CK73HXR1A104K	C CAPACITOR	1	
		C5057	CK73HXR1A104K	C CAPACITOR	1	
		C5058	CK73HXR1A104K	C CAPACITOR	1	
		C5059	CK73HXR1A104K	C CAPACITOR	1	
		C5060	CK73HXR1A104K	C CAPACITOR	1	
		C5061	CK73HXR1A104K	C CAPACITOR	1	
		C5066	CK73HXR1A104K	C CAPACITOR	1	
		C5067	CK73HXR1A104K	C CAPACITOR	1	
		C5068	CK73HXR1A104K	C CAPACITOR	1	
		C5069	CK73HXR1A104K	C CAPACITOR	1	
		C5070	CK73HXR1A104K	C CAPACITOR	1	
		C5071	CK73HXR1A104K	C CAPACITOR	1	
		C5072	CK73HXR1A104K	C CAPACITOR	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C5073	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5074	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5075	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5076	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5077	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5078	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5079	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5080	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5081	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5083	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5084	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5085	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5086	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5087	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5088	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5089	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5090	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5091	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5092	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5093	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5094	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5095	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5096	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5097	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5098	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5099	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5100	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5101	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5102	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5103	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5104	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5105	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5106	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5107	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5108	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5109	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5110	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5111	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5112	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5113	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5114	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5115	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5116	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5117	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5118	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5119	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5120	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5121	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5122	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5123	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5124	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5126	CS77FBK0J101M	TA E CAPACITOR	100uF 6.3V M	1	
	C5128	CS77FBK0J101M	TA E CAPACITOR	100uF 6.3V M	1	
	C5132	CS77FBK0J101M	TA E CAPACITOR	100uF 6.3V M	1	
	C5133	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5134	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5201	CS77FBK0J101M	TA E CAPACITOR	100uF 6.3V M	1	
	C5202	CC73HCH1H102J	C CAPACITOR	1000pF 50V J	1	
	C5203	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5204	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5251	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5252	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5253	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5255	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5259	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5263	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5269	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5302	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5305	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5306	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5307	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5308	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5309	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5313	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5314	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5315	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5316	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5317	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5318	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5319	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5320	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5321	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5322	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5323	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5324	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5326	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5328	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5329	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5330	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5333	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C5334	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5335	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5336	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5337	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5338	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5339	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5340	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5341	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5342	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5343	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5344	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5345	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5346	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5353	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5354	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5355	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5356	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5357	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5358	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5359	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5360	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5361	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5362	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5363	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5364	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5369	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5370	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5374	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5375	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5376	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5377	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5378	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5379	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5380	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5381	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5382	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C5383	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5385	CC73HCH1H102J	C CAPACITOR	1000pF 50V J	1	
	C5386	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C5387	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C5401	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C5471	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5472	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5475	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C5477	CK73HXR0J474K	C CAPACITOR	0.47uF 6.3V K	1	
	C5479	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5480	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5481	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5482	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5484	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5485	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5486	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5487	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5488	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5489	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5490	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5491	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5493	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5494	CK73GXR0J106M	C CAPACITOR	10uF 6.3V M	1	
	C5495	CK73GXR0J106M	C CAPACITOR	10uF 6.3V M	1	
	C5496	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5497	CK73GXR0J106M	C CAPACITOR	10uF 6.3V M	1	
	C5498	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5499	CK73GXR0J106M	C CAPACITOR	10uF 6.3V M	1	
	C5500	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C5501	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C5502	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C5503	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C5504	CC73HCH1H102J	C CAPACITOR	1000pF 50V J	1	
	C5505	CC73HCH1H102J	C CAPACITOR	1000pF 50V J	1	
	C5506	CC73HCH1H102J	C CAPACITOR	1000pF 50V J	1	
	C5507	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5508	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5509	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5510	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5511	CC73HCH1H100D	C CAPACITOR	10pF 50V D	1	
	C5512	CC73HCH1H120J	C CAPACITOR	12pF 50V J	1	
	C5513	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5514	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5515	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5516	CK73GXR0J106M	C CAPACITOR	10uF 6.3V M	1	
	C5517	CK73GXR0J106M	C CAPACITOR	10uF 6.3V M	1	
	C5518	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5519	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5521	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5523	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5524	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5531	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5532	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5534	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5535	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5536	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C5537	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5538	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5632	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5684	CC73HCH1H120J	C CAPACITOR	12pF 50V J	1	
	C5701	CK73HXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C5704	CK73HCH1H080D	C CAPACITOR	8pF 50V D	1	
	C5705	CK73HCH1H080D	C CAPACITOR	8pF 50V D	1	
	C5710	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5711	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5712	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5713	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5714	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5715	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5716	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5717	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5718	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5719	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5720	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5721	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5722	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5723	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5724	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5725	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5726	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5727	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5728	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5729	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5730	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5731	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5740	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5741	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5903	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C5904	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C5905	CK73GXR1E224K	C CAPACITOR	0.022uF 25V K	1	
	C5907	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C5908	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C5910	CC73HCH1H560J	C CAPACITOR	56pF 50V J	1	
	C5911	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C5912	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C5913	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C5916	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C5917	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C5918	CK73GXR1E224K	C CAPACITOR	0.022uF 25V K	1	
	C5920	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C5921	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C5923	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C5924	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C5925	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C5926	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C5927	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5928	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5933	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5934	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C5940	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5941	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C5951	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C5961	CC73HCH1H220J	C CAPACITOR	22pF 50V J	1	
	C5972	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C5973	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C5974	CK73GXR1E224K	C CAPACITOR	0.022uF 25V K	1	
	C5975	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C5976	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C5979	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C5980	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C5981	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C5982	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C5983	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C5984	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C5985	CK73GXR1E224K	C CAPACITOR	0.022uF 25V K	1	
	C5991	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C5993	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C5995	CC73HCH1H470J	C CAPACITOR	47pF 50V J	1	
	C5996	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C5997	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C5998	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C6025	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C6026	CK73FXR1C106K	C CAPACITOR	10uF 16V K	1	
	C6027	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C6028	CK73HXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C6029	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C6030	CK73HXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C6301	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C7001	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7002	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7003	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7004	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7005	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7006	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7007	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7008	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C7011	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7012	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7013	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7014	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7015	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7016	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7017	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7018	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7023	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7024	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7025	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7026	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7027	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7028	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7029	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7030	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7035	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7036	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7037	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7038	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7039	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7040	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7051	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7052	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7053	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7054	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7055	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7056	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7057	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7058	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7061	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7062	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7063	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7064	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7065	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7066	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7067	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7068	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7073	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7074	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7075	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7076	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7077	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7078	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7079	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7080	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7085	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7086	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7087	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7088	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7089	CC73HCH1H121J	C CAPACITOR	120pF 50V J	1	
	C7090	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C7092	CC73HCH1H102J	C CAPACITOR	1000pF 50V J	1	
	C7093	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	C7094	CK73EXR1A476K	C CAPACITOR	47uF 10V K	1	
	R632	RK73HH1J271D	MG RESISTOR	270Ω 1/16W D	1	
	R633	RK73HH1J750D	MG RESISTOR	75Ω 1/16W D	1	
	R5003	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5004	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5005	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5006	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R5007	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5008	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5012	RK73HB1J752J	MG RESISTOR	7.5kΩ 1/16W J	1	
	R5016	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5017	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5018	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5021	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5023	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5024	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R5025	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R5026	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R5027	RK73HH1J432D	MG RESISTOR	4.3kΩ 1/16W D	1	
	R5028	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5029	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R5030	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R5031	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R5032	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R5034	RK73HB1J182J	MG RESISTOR	1.8kΩ 1/16W J	1	
	R5036	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5037	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R5038	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R5039	RK73HB1J182J	MG RESISTOR	1.8kΩ 1/16W J	1	
	R5040	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5041	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5042	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5043	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5044	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5046	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R5047	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5048	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R5049	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R5050	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R5051	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5052	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5053	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5054	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5055	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5056	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5058	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5059	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5060	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5062	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5064	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5067	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5070	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5071	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5073	RK73HB1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R5074	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5075	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5076	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5077	RK73HB1J241D	MG RESISTOR	240Ω 1/16W D	1	
	R5081	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5090	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5091	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5092	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5094	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5095	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5097	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R5098	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5100	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5101	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5102	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5103	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5104	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5105	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	X1,K0
	R5106	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5109	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5111	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5112	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5113	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5114	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5115	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5116	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5117	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5118	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5119	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5120	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5121	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5122	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5123	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5124	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5126	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5127	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5128	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5137	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5145	RK73HB1J123D	MG RESISTOR	12kΩ 1/16W D	1	
	R5146	RK73HB1J243D	MG RESISTOR	24kΩ 1/16W D	1	
	R5147	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5148	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5151	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5203	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5204	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5205	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R5206	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5207	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5220	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5221	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5222	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5223	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5224	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5225	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5226	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5227	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5231	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5232	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5233	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5234	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5236	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5237	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5238	RK73HB1J680J	MG RESISTOR	68Ω 1/16W J	1	
	R5265	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5266	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5268	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5269	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5270	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R5271	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5272	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5273	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5274	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5275	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5276	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R5277	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5278	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5301	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5302	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5303	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5304	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5305	RK73HH1J241D	MG RESISTOR	240Ω 1/16W D	1	
	R5306	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5307	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5308	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5309	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5310	RK73HH1J241D	MG RESISTOR	240Ω 1/16W D	1	
	R5311	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R5401	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R5402	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R5403	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R5404	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R5405	RK73HH1J101D	MG RESISTOR	100Ω 1/16W D	1	
	R5407	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5413	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R5422	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R5424	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R5425	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R5428	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5429	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R5430	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R5434	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5435	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5444	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5445	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5450	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5451	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5452	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5453	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5471	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5473	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5474	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5477	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5478	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5481	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5482	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5484	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5485	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5486	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5487	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5488	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5489	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5490	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5491	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5498	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5501	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R5502	RK73HB1J823J	MG RESISTOR	82kΩ 1/16W J	1	
	R5503	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R5504	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R5505	RK73HB1J823J	MG RESISTOR	82kΩ 1/16W J	1	
	R5506	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R5507	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R5508	RK73HB1J823J	MG RESISTOR	82kΩ 1/16W J	1	
	R5509	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R5510	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R5511	RK73HB1J823J	MG RESISTOR	82kΩ 1/16W J	1	
	R5512	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R5641	RK73HB1J122J	MG RESISTOR	1.2kΩ 1/16W J	1	
	R5643	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5644	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5645	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5646	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5647	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5648	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5649	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5650	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5651	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5652	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5653	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5654	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5655	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5656	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5657	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R5658	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5659	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5660	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5661	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5662	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5663	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5665	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5666	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5667	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R5668	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5669	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5670	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R5674	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5675	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R5676	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5677	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5678	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5680	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5681	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5682	RK73HB1J820J	MG RESISTOR	82Ω 1/16W J	1	
	R5683	RK73HB1J820J	MG RESISTOR	82Ω 1/16W J	1	
	R5684	RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
	R5685	RK73HB1J820J	MG RESISTOR	82Ω 1/16W J	1	
	R5686	RK73HB1J820J	MG RESISTOR	82Ω 1/16W J	1	
	R5687	RK73HB1J820J	MG RESISTOR	82Ω 1/16W J	1	
	R5688	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5703	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5704	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5705	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5707	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5709	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5713	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5714	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5717	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5718	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5719	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5723	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5724	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R5727	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5729	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5731	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5732	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5733	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R5734	RK73HH1J362D	MG RESISTOR	3.6kΩ 1/16W D	1	
	R5735	RK73HH1J222D	MG RESISTOR	2.2kΩ 1/16W D	1	
	R5736	RK73HH1J241D	MG RESISTOR	240Ω 1/16W D	1	
	R5737	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5738	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5739	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5740	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5790	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5791	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5801	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	E1,X1,M1,M2
	R5802	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1,M1,M2
	R5804	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5805	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5806	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5808	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5809	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5810	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5811	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5812	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1,X1,M1,M2
	R5813	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5815	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5816	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5817	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5828	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5830	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5831	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5832	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5833	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5834	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5836	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	
	R5838	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5839	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5840	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5841	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5842	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5843	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5844	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5845	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5846	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5847	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5853	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5855	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5857	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5858	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5859	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5861	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1,M1,M2
	R5862	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E1,M1,M2
	R5869	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5871	RK73GB2A271J	MG RESISTOR	270Ω 1/10W J	1	
	R5887	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5911	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5912	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5913	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5915	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R5918	RK73GB2A200J	MG RESISTOR	20Ω 1/10W J	1	
	R5920	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	
	R5921	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5922	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R5923	RK73HH1J222D	MG RESISTOR	2.2kΩ 1/16W D	1	
	R5924	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R5925	RK73HH1J123D	MG RESISTOR	12kΩ 1/16W D	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R5926	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	
	R5927	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5928	RK73GB2A200J	MG RESISTOR	20Ω 1/10W J	1	
	R5930	RK73HH1J273D	MG RESISTOR	27kΩ 1/16W D	1	
	R5931	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5932	RK73HH1J563D	MG RESISTOR	56kΩ 1/16W D	1	
	R5933	RK73HH1J222D	MG RESISTOR	2.2kΩ 1/16W D	1	
	R5934	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R5935	RK73HH1J823D	MG RESISTOR	82kΩ 1/16W D	1	
	R5937	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R5938	RK73HB1J104J	MG RESISTOR	100kΩ 1/16W J	1	
	R5940	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5942	RK73GB2A200J	MG RESISTOR	20Ω 1/10W J	1	
	R5943	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5944	RK73HH1J222D	MG RESISTOR	2.2kΩ 1/16W D	1	
	R5945	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R5946	RK73HH1J823D	MG RESISTOR	82kΩ 1/16W D	1	
	R5947	RK73HH1J243D	MG RESISTOR	24kΩ 1/16W D	1	
	R5948	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5949	RK73HH1J203D	MG RESISTOR	20kΩ 1/16W D	1	
	R5960	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R5961	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R5962	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R5964	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R5965	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R5966	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
	R5970	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	
	R5971	RK73GB2A331J	MG RESISTOR	330Ω 1/10W J	1	
	R5975	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5988	RK73GB2A200J	MG RESISTOR	20Ω 1/10W J	1	
	R5990	RK73HH1J203D	MG RESISTOR	20kΩ 1/16W D	1	
	R5991	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R5992	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R5993	RK73HH1J222D	MG RESISTOR	2.2kΩ 1/16W D	1	
	R5994	RK73HH1J393D	MG RESISTOR	39kΩ 1/16W D	1	
	R5995	RK73HH1J682D	MG RESISTOR	6.8kΩ 1/16W D	1	
	R6001	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R6002	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6003	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6004	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6005	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6009	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6010	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6011	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6012	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6013	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6014	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6015	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6016	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6075	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6081	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R6082	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R6215	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6216	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6217	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6218	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1,X1,M1,M2
	R6219	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1,X1,M1,M2
	R6220	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1,X1,M1,M2
	R6233	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6234	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6236	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6240	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6241	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6242	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6243	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6244	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6245	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6246	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6247	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6248	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6249	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6250	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6251	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6252	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6253	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6254	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6255	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6256	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6257	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6258	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6259	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6260	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6261	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6262	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6263	RK73HB1J330J	MG RESISTOR	33Ω 1/16W J	1	E1,X1,M1,M2
	R6270	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0
	R6271	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0
	R6272	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0
	R6301	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R6302	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R6303	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6304	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R6305	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6306	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R6307	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R6309	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R6310	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R6311	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R6312	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R6313	RK73HB1J220J	MG RESISTOR	22Ω 1/16W J	1	
	R6314	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R6315	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R6317	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R6318	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R6320	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R6321	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R6322	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R6323	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R6324	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R6327	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R6330	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R6331	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	
	R7001	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R7002	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R7003	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R7004	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R7005	RK73HH1J241D	MG RESISTOR	240Ω 1/16W D	1	
	R7006	RK73HH1J201D	MG RESISTOR	200Ω 1/16W D	1	
	R7051	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R7052	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R7053	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R7054	RK73HH1J102D	MG RESISTOR	1kΩ 1/16W D	1	
	R7055	RK73HH1J241D	MG RESISTOR	240Ω 1/16W D	1	
	RA5201	RK74HB1J473J	NET RESISTOR	47kΩ 1/16W J	1	
	RA5202	RK74HB1J473J	NET RESISTOR	47kΩ 1/16W J	1	
	RA5403	RK74HB1J000J	NET RESISTOR	0Ω 1/16W J	1	K0
	RA5404	RK74HB1J000J	NET RESISTOR	0Ω 1/16W J	1	K0
	RA5405	RK74HB1J000J	NET RESISTOR	0Ω 1/16W J	1	K0
	RA5406	RK74HB1J000J	NET RESISTOR	0Ω 1/16W J	1	K0
	RA5407	RK74HB1J000J	NET RESISTOR	0Ω 1/16W J	1	K0
	RA5408	RK74HB1J000J	NET RESISTOR	0Ω 1/16W J	1	K0
	L631	LB73G0ED-004	CHIP FERRITE		1	
	L5001	LB73G0ED-003	CHIP FERRITE		1	
	L5002	LB73G0ED-003	CHIP FERRITE		1	
	L5402	LB73G0ED-004	CHIP FERRITE		1	
	L5403	LB73G0ED-004	CHIP FERRITE		1	
	L5405	LB73G0ED-004	CHIP FERRITE		1	
	L5406	LB73G0ED-004	CHIP FERRITE		1	
	L5501	LB73G0ED-004	CHIP FERRITE		1	
	L5704	LB73G0ED-004	CHIP FERRITE		1	
	L5705	LB73G0ED-004	CHIP FERRITE		1	
	L5706	LB73G0ED-004	CHIP FERRITE		1	
	L5901	LR79Z0EW5R1N	CHIP INDUCTOR	5.1uF	1	
	L5902	LR79Z0EW5R1N	CHIP INDUCTOR	5.1uF	1	
	L5903	LR79Z0EW5R1N	CHIP INDUCTOR	5.1uF	1	
	L5904	LB73G0ED-004	CHIP FERRITE		1	
	L5908	LR79Z0FB220M	CHIP INDUCTOR	22uF	1	
	L6025	LR79Z0JP5R1N	CHIP INDUCTOR	5.1uF	1	
	CN527	EC720AT-0516A	FFC FPC CONNE		1	
	CN561	EC720AA-0515A	FFC FPC CONNE	15P	1	
	CN562	EC720AA-0512A	FFC FPC CONNE		1	
	CN571	QGA2001F6-05X	W TO B CONNE	W-B (1-5)	1	
	CN572	QGA1501F4-03W	W TO B CONNE	W-B (1-3)	1	
	CN581	EB760AX-05C0B	B TO B CONNE	120P	1	
	CN601	EC720CF-0560A	FFC FPC CONNE		1	
△	CN621	QGB0811L2-40X	B TO B CONNE	B-B (1-40)	1	E1,X1,M1,M2
	F5901	FZA10BF-R50	FUSE (CC)	0.5A	1	
	VA5730	SDV1005H26//0	VARISTOR		1	
	VA5731	SDV1005H26//0	VARISTOR		1	
	VA5732	SDV1005H26//0	VARISTOR		1	
	VA5733	SDV1005H26//0	VARISTOR		1	
	VA6301	SDV1005H26//0	VARISTOR		1	
	VA6302	SDV1005H26//0	VARISTOR		1	
	VA6303	SDV1005H26//0	VARISTOR		1	
	X5001	L7J-0138-00	QUARTZ CRYSTAL		1	
	X5401	L7J-0146-00	QUARTZ CRYSTAL		1	
	X5701	L7J-0156-00	QUARTZ CRYSTAL		1	
		B4C-0636-00	SERIAL STICKER		2	X1,M1,M2
AUDIO PWB ASSY(XJ6-119x-0x) <XJ6>						
	IC1	LV5680NPVC-H	MOS IC		1	
	IC41	XC6223B331P-G	ANALOG IC		1	
	IC42	XC6216B852P-G	ANALOG IC		1	
	IC101	JCV8031	IC		1	
	IC201	TDA7715	ANALOG IC		1	
	IC260	TC74HCT4053FT	MOS IC		1	K0
	IC261	NJM2794RB2	BIPOLAR IC		1	K0
	IC301	XC6223B331P-G	ANALOG IC		1	
	IC361	W3F-0174-00	MCU IC		1	E1,X1
	IC401	SI4706-D50-GM	MOS IC		1	E1,M1,M2
	IC511	TC7SET32FUJC	MOS IC		1	E1,K0
	IC512	TC7SH17FUJC	MOS IC		1	E1,K0
	IC590	TC7SZ125FUJC	MOS IC		1	E1,X1,M1,M2
	IC601	NJW1240V	MOS IC		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	IC781	BA6956AN	IC		1	
	IC790	BD00C0AWFP	MOS IC		1	
	IC801	ML22Q394714MB	ANALOG IC		1	
	IC802	BU7241G	MOS IC		1	
	IC900	BD00C0AWFP	MOS IC		1	E1,X1
	IC1101	NJM2746V	ANALOG IC		1	
	IC1102	NJM2746V	ANALOG IC		1	
	Q31	LSCR523EBFS8	TRANSISTOR		1	
	Q32	LSAR523EBFS8	TRANSISTOR		1	
	Q51	LSCR523EBFS8	TRANSISTOR		1	
	Q60	LSAR523EBFS8	TRANSISTOR		1	
	Q61	LSCR523EBFS8	TRANSISTOR		1	
	Q62	LSAR523EBFS8	TRANSISTOR		1	
	Q63	LSCR523EBFS8	TRANSISTOR		1	
	Q80	LTA014YEBFS8	DIGI TRANSISTOR		1	
	Q81	LSAR523EBFS8	TRANSISTOR		1	
	Q82	LSCR523EBFS8	TRANSISTOR		1	
	Q90	LTC024EEBFS8	DIGI TRANSISTOR		1	
	Q96	LSCR523EBFS8	TRANSISTOR		1	
	Q151	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q152	LTA043ZEBFS8	DIGI TRANSISTOR		1	
	Q155	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q156	LTA043ZEBFS8	DIGI TRANSISTOR		1	
	Q161	LTC043TEBFS8	DIGI TRANSISTOR		1	
	Q162	LTC043TEBFS8	DIGI TRANSISTOR		1	
	Q163	LTC043TEBFS8	DIGI TRANSISTOR		1	
	Q164	LTC043TEBFS8	DIGI TRANSISTOR		1	
	Q165	LTC043TEBFS8	DIGI TRANSISTOR		1	
	Q191	LTA043ZEBFS8	DIGI TRANSISTOR		1	
	Q193	LTC043TEBFS8	DIGI TRANSISTOR		1	
	Q194	LTC043TEBFS8	DIGI TRANSISTOR		1	
	Q391	2SB1424/R/	TRANSISTOR		1	X1
	Q392	LTC014YEBFS8	DIGI TRANSISTOR		1	X1
	Q451	3SK291F	FET		1	E1,M1,M2
	Q781	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q801	LTC014YEBFS8	DIGI TRANSISTOR		1	
	D1	1N5402-BPC07	DIODE		1	
	D11	RB161MM-20	SCHOTTKY DIODE		1	
	D32	UDZV11B	ZENER DIODE		1	
	D41	GS1J-LTP	DIODE		1	
	D42	GS1J-LTP	DIODE		1	X1,M1,M2,K0
	D43	GS1J-LTP	DIODE		1	
	D44	GS1J-LTP	DIODE		1	X1,M1,M2,K0
	D55	UDZV6.2B	ZENER DIODE		1	
	D60	1SS355VM	DIODE		1	
	D61	1SS355VM	DIODE		1	
	D71	DAP202UM	DIODE		1	
	D80	1SS355VM	DIODE		1	
	D90	1SS355VM	DIODE		1	
	D96	UDZV16B	ZENER DIODE		1	
	D101	DAP202UM	DIODE		1	
	D151	DAP202UM	DIODE		1	
	D155	DAP202UM	DIODE		1	
	D191	DAP202UM	DIODE		1	
	D202	1SS355VM	DIODE		1	
	D203	DAP202UM	DIODE		1	
	D204	DAP202UM	DIODE		1	
	D205	DAP202UM	DIODE		1	
	D260	1SS355VM	DIODE		1	K0
	D261	UDZV4.7B	ZENER DIODE		1	K0
	D302	GS1J-LTP	DIODE		1	
	D381	UDZV3.3B	ZENER DIODE		1	E1,X1
	D591	UDZV5.6B	ZENER DIODE		1	E1,X1,M1,M2
	D781	UDZV5.1B	ZENER DIODE		1	
	C1	CD04EW1C332M2	E CAPACITOR	3300uF 16V M	1	
	C2	CK730MF2W104K	C CAPACITOR	0.1uF 450V K	1	E1,M1,M2
	C11	CE32CB1V101M	E CAPACITOR	100uF 35V M	1	
	C12	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C13	CE32CB1C470M	E CAPACITOR	47uF 16V M	1	
	C14	CE32CB1C470M	E CAPACITOR	47uF 16V M	1	
	C15	CE32CB1A101M	E CAPACITOR	100uF 10V M	1	
	C16	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C18	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C19	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C20	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C21	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C23	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C24	CK73HXR1E104K	C CAPACITOR	0.1uF 25V K	1	
	C25	CK73HXR1E224K	C CAPACITOR	0.22uF 25V K	1	
	C26	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C27	CE32CC1C221M	E CAPACITOR	220uF 16V M	1	
	C31	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C32	CK73HXR1E333K	C CAPACITOR	0.033uF 25V K	1	
	C41	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C42	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C43	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C44	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C51	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C52	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C60	CC73HCH1H101J	C CAPACITOR	100pF 50V J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C71	CK73HXR1H104K	C CAPACITOR	0.1uF 50V K	1	
	C80	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C90	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C96	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C97	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C100	CE32CB1C100M	E CAPACITOR	10uF 16V M	1	
	C101	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C102	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C103	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C104	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C105	CC73HCH1H050C	C CAPACITOR	5pF 50V C	1	
	C106	CC73HCH1H050C	C CAPACITOR	5pF 50V C	1	
	C109	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C110	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C111	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C112	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C113	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C114	CK73HXR1E474K	C CAPACITOR	0.47uF 25V K	1	
	C121	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C122	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C123	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C124	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C125	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C126	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C127	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C128	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C131	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C132	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C133	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C134	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C135	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C136	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C137	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C138	CC73HCH1H221J	C CAPACITOR	220pF 50V J	1	
	C145	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C146	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C151	CE32CB1C100M	E CAPACITOR	10uF 16V M	1	
	C152	CE32CB1C100M	E CAPACITOR	10uF 16V M	1	
	C153	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C154	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C155	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C171	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C172	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C173	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C174	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C175	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C177	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C191	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C192	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C195	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C196	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C197	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C201	CE32CB1C470M	E CAPACITOR	47uF 16V M	1	
	C202	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C203	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C205	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C206	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C207	CK73HXR0J474K	C CAPACITOR	0.47uF 6.3V K	1	
	C208	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C209	CK73HXR0J474K	C CAPACITOR	0.47uF 6.3V K	1	
	C211	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C212	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C215	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C216	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C217	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C218	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C219	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C220	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C223	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C224	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C225	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C227	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C228	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C229	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C234	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C235	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C264	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	K0
	C265	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	K0
	C266	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	K0
	C267	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0
	C268	CK73HXR1E104K	C CAPACITOR	0.1uF 25V K	1	K0
	C272	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0
	C273	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0
	C274	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0
	C275	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	K0
	C276	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	K0
	C277	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	K0
	C278	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	K0
	C279	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	K0
	C280	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0
	C281	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0
	C282	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C283	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	K0
	C284	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	K0
	C285	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	K0
	C286	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	K0
	C302	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	
	C303	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C304	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C305	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C306	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C308	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C309	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C321	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C322	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C358	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1
	C359	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	E1,X1
	C361	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	E1,X1
	C362	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,X1
	C363	CK73HXR0J474K	C CAPACITOR	0.47uF 6.3V K	1	E1,X1
	C371	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	E1,X1
	C402	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	E1,M1,M2
	C403	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	E1,M1,M2
	C404	CK73HXR1E223K	C CAPACITOR	0.022uF 25V K	1	E1,M1,M2
	C405	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	E1,M1,M2
	C406	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,M1,M2
	C407	CC73HCH1H330J	C CAPACITOR	33pF 50V J	1	E1,M1,M2
	C411	CC73HCH1H150J	C CAPACITOR	15pF 50V J	1	E1,M1,M2
	C421	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,M1,M2
	C431	CC73HCH1H220J	C CAPACITOR	22pF 50V J	1	E1,M1,M2
	C432	CC73HCH1H220J	C CAPACITOR	22pF 50V J	1	E1,M1,M2
	C451	CC73HCH1H060D	C CAPACITOR	6pF 50V D	1	E1,M1,M2
	C452	CC73HCH1H040C	C CAPACITOR	4pF 50V C	1	E1,M1,M2
	C453	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	E1,M1,M2
	C454	CC73HCH1H560J	C CAPACITOR	56pF 50V J	1	E1,M1,M2
	C462	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	E1,M1,M2
	C463	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	E1,M1,M2
	C464	CC73HCH1H030C	C CAPACITOR	3pF 50V C	1	E1,M1,M2
	C501	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0
	C502	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0
	C503	CK73GXR1E225K	C CAPACITOR	2.2uF 25V K	1	K0
	C511	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,K0
	C512	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	E1,K0
	C590	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	E1,X1,M1,M2
	C591	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	E1,X1,M1,M2
	C601	CE32CB1C100M	E CAPACITOR	10uF 16V M	1	
	C602	CE32CB1C100M	E CAPACITOR	10uF 16V M	1	
	C603	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C604	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C605	CK73EXR1E106K	C CAPACITOR	10uF 25V K	1	
	C610	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C611	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C612	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C613	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C614	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C616	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C618	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C619	CK73HXR1H102K	C CAPACITOR	1000pF 50V K	1	
	C715	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C716	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C721	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C722	CK73GXR1C475K	C CAPACITOR	4.7uF 16V K	1	
	C781	CE32CB1V101M	E CAPACITOR	100uF 35V M	1	
	C790	CK73EXR1H106K	C CAPACITOR	10uF 50V K	1	
	C791	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C792	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	
	C802	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C803	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	
	C804	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C805	CK73HXR1H103K	C CAPACITOR	0.01uF 50V K	1	
	C806	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C807	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C808	CK73HXR1A104K	C CAPACITOR	0.1uF 10V K	1	
	C809	CC73HCH1H681J	C CAPACITOR	680pF 50V J	1	
	C810	CC73HCH1H471J	C CAPACITOR	470pF 50V J	1	
	C811	CC73HCH1H471J	C CAPACITOR	470pF 50V J	1	
	C812	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C813	CK73HXR1C105K	C CAPACITOR	1uF 16V K	1	
	C822	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C900	CK73FXR1E106K	C CAPACITOR	10uF 25V K	1	E1,X1
	C901	CK73GXR1A106K	C CAPACITOR	10uF 10V K	1	E1,X1
	C1204	CB73QAD1C106M	FILM CAPACITOR	10uF 16V M	1	
	C1711	CB73QAD1C106M	FILM CAPACITOR	10uF 16V M	1	
	C1712	CB73QAD1C106M	FILM CAPACITOR	10uF 16V M	1	
	C1713	CB73QAD1C106M	FILM CAPACITOR	10uF 16V M	1	
	C1714	CB73QAD1C106M	FILM CAPACITOR	10uF 16V M	1	
	R15	RK73HH1J273D	MG RESISTOR	27kΩ 1/16W D	1	
	R17	RK73HH1J472D	MG RESISTOR	4.7kΩ 1/16W D	1	
	R18	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R19	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R23	RK73FB2B000J	MG RESISTOR	0Ω 1/8W J	1	
	R24	RK73FB2B000J	MG RESISTOR	0Ω 1/8W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R25	RK73FB2B000J	MG RESISTOR	0Ω 1/8W J	1	
	R27	RK73FB2B000J	MG RESISTOR	0Ω 1/8W J	1	
	R31	RK73EB2E622J	MG RESISTOR	6.2kΩ 1/4W J	1	
	R32	RK73EB2E622J	MG RESISTOR	6.2kΩ 1/4W J	1	
	R33	RK73HH1J753D	MG RESISTOR	75kΩ 1/16W D	1	
	R34	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R35	RK73HH1J474D	MG RESISTOR	470kΩ 1/16W D	1	
	R36	RK73HB1J224J	MG RESISTOR	220kΩ 1/16W J	1	
	R37	RK73EB2E153J	MG RESISTOR	15kΩ 1/4W J	1	
	R38	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R40	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E1
	R41	RK73FB2B472J	MG RESISTOR	4.7kΩ 1/8W J	1	
	R42	RK73FB2B472J	MG RESISTOR	4.7kΩ 1/8W J	1	X1,M1,M2,K0
	R50	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R51	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	
	R52	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	
	R53	RK73GB2A223J	MG RESISTOR	22kΩ 1/10W J	1	
	R54	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R55	RK73GB2A152J	MG RESISTOR	1.5kΩ 1/10W J	1	
	R60	RK73HB1J182J	MG RESISTOR	1.8kΩ 1/16W J	1	
	R61	RK73GB2A111J	MG RESISTOR	110Ω 1/10W J	1	
	R62	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R63	RK73HB1J243J	MG RESISTOR	24kΩ 1/16W J	1	
	R64	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R65	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R66	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R67	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R68	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R69	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R70	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R72	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R73	RK73HB1J683J	MG RESISTOR	68kΩ 1/16W J	1	
	R74	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R80	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R81	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R82	RK73FB2B103J	MG RESISTOR	10kΩ 1/8W J	1	
	R83	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R84	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R90	RK73GB2A272J	MG RESISTOR	2.7kΩ 1/10W J	1	
	R91	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R96	RK73FB2B752J	MG RESISTOR	7.5kΩ 1/8W J	1	
	R97	RK73HB1J753J	MG RESISTOR	75kΩ 1/16W J	1	
	R98	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R100	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R101	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	
	R102	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	
	R103	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	
	R104	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	
	R142	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	
	R143	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R145	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R146	RK73HB1J1R0J	MG RESISTOR	1Ω 1/16W J	1	
	R147	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R148	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R151	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R152	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R153	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R154	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R155	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R156	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R157	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R159	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R161	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R162	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R163	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R164	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R165	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R171	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R172	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R173	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R174	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R175	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R191	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R192	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R193	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R194	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R195	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R196	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R201	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R202	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R204	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R205	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R206	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R209	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R264	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R265	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R266	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R274	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R275	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R276	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R279	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R280	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R281	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R283	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R284	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R285	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R290	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	K0
	R291	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	K0
	R293	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	K0
	R294	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	K0
	R301	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R331	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0
	R332	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0
	R333	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0
	R334	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	K0
	R361	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	E1,X1
	R362	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R363	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	E1,X1
	R364	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R365	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R366	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R367	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,X1
	R371	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E1,X1
	R372	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E1,X1
	R373	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	E1,X1
	R374	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E1,X1
	R375	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E1,X1
	R377	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	E1,X1
	R378	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E1,X1
	R379	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	E1,X1
	R383	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E1,X1
	R385	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E1,X1
	R387	RK73HB1J562J	MG RESISTOR	5.6kΩ 1/16W J	1	E1,X1
	R390	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	X1
	R391	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	E1
	R392	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	X1
	R393	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	X1
	R394	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	X1
	R402	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	E1,M1,M2
	R421	RK73HB1J202J	MG RESISTOR	2kΩ 1/16W J	1	E1,M1,M2
	R422	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	E1,M1,M2
	R423	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	E1,M1,M2
	R424	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	E1,M1,M2
	R425	RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	E1,M1,M2
	R426	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	E1,M1,M2
	R432	RK73HB1J202J	MG RESISTOR	2kΩ 1/16W J	1	E1,M1,M2
	R452	RK73HB1J683J	MG RESISTOR	68kΩ 1/16W J	1	E1,M1,M2
	R453	RK73HB1J153J	MG RESISTOR	15kΩ 1/16W J	1	E1,M1,M2
	R454	RK73HB1J393J	MG RESISTOR	39kΩ 1/16W J	1	E1,M1,M2
	R455	RK73HB1J623J	MG RESISTOR	62kΩ 1/16W J	1	E1,M1,M2
	R456	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	E1,M1,M2
	R457	RK73HB1J200J	MG RESISTOR	20Ω 1/16W J	1	E1,M1,M2
	R500	RK73EB2E000J	MG RESISTOR	0Ω 1/4W J	1	K0
	R501	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	K0
	R502	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	K0
	R503	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	K0
	R511	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E1,K0
	R512	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E1,K0
	R513	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	E1,K0
	R514	RK73HB1J2R2J	MG RESISTOR	2.2Ω 1/16W J	1	E1,K0
	R515	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	E1,K0
	R516	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	E1,K0
	R517	RK73HB1J272J	MG RESISTOR	2.7kΩ 1/16W J	1	E1,K0
	R581	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	K0
	R582	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	K0
	R583	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	K0
	R591	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	E1
	R592	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	X1,M1,M2
	R593	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	E1,X1,M1,M2
	R611	RK73GB2A2R2J	MG RESISTOR	2.2Ω 1/10W J	1	
	R612	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R614	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R615	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R616	RK73HB1J684J	MG RESISTOR	680kΩ 1/16W J	1	
	R781	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R782	RK73HB1J222J	MG RESISTOR	2.2kΩ 1/16W J	1	
	R784	RK73FB2B000J	MG RESISTOR	0Ω 1/8W J	1	
	R787	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R788	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R789	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R792	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	
	R793	RK73HH1J823D	MG RESISTOR	82kΩ 1/16W D	1	
	R794	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	
	R795	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R801	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R802	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R803	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R804	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R805	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R806	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R807	RK73HB1J153J	MG RESISTOR	15kΩ 1/16W J	1	
	R808	RK73HB1J153J	MG RESISTOR	15kΩ 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R809	RK73HB1J752J	MG RESISTOR	7.5kΩ 1/16W J	1	
	R810	RK73HB1J752J	MG RESISTOR	7.5kΩ 1/16W J	1	
	R811	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R812	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R813	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R814	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R815	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R826	RK73HB1J162J	MG RESISTOR	1.6kΩ 1/16W J	1	
	R900	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	E1,X1
	R901	RK73HH1J183D	MG RESISTOR	18kΩ 1/16W D	1	E1,X1
	R902	RK73HH1J752D	MG RESISTOR	7.5kΩ 1/16W D	1	E1,X1
	R1101	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	
	R1102	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	
	R1103	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	
	R1104	RK73HH1J680D	MG RESISTOR	68Ω 1/16W D	1	
	R1146	RK73HH1J160D	MG RESISTOR	16Ω 1/16W D	1	
	L1	QQR1909-001	CHOKE COIL		1	E1,M1,M2
	L1	QQR1927-001	CHOKE COIL		1	X1,K0
	L301	LR73Z0AD4R7M	CHIP INDUCTOR	4.7uH	1	
	L401	LB73G0BF-002	CHIP FERRITE		1	E1,M1,M2
	L411	LR73Z0AER15J	CHIP INDUCTOR		1	E1,M1,M2
	L412	NQLQ3DG-22NX	INDUCTOR	22nH G	1	E1,M1,M2
	L451	LR73Z0AER56J	CHIP INDUCTOR		1	E1,M1,M2
	L452	LR73Z0AER15J	CHIP INDUCTOR		1	E1,M1,M2
	L461	LB73G0BF-002	CHIP FERRITE		1	E1,M1,M2
	L601	LK73G0AQ1R0K	M.CHIP INDUCTOR	1uH	1	
	CN201	EC720AA-0560A	FFC FPC CONNE	60P	1	
	CN301	EC720AA-0550A	FFC FPC CONNE	50P	1	
	CN302	QGA2001C1-04	W TO B CONNE	W-B (1-4)	1	
	CN781	QGA1201F2-05X	W TO B CONNE	W-B (1-5)	1	
△	F6	F53-0513-08	PATTERN FUSE	4A	1	
△	F7	F53-0513-08	PATTERN FUSE	4A	1	
△	F171	F53-0513-08	PATTERN FUSE	4A	1	
△	F191	F53-0513-08	PATTERN FUSE	4A	1	
△	F500	FZA10BZ-2R5	FUSE (CC)		1	E1
△	F581	F53-0513-08	PATTERN FUSE	4A	1	
	J1	E5J-0022-00	R.RECEPTACLE	24P	1	
	J151	QNN0888-001	PIN JACK		1	
	J191	QNS0307-001	3.5 JACK		1	
	J351	QNB0353-001	ANT TERMINAL		1	E1,X1
	J501	QNZ0907-001	CIR CONNECTOR		1	E1,K0
	J581	QNS0307-001	3.5 JACK		1	
	VA52	SDV1005E18//2	VARISTOR		1	
	VA60	SDV1005E18//2	VARISTOR		1	
	VA62	SDV1005E18//2	VARISTOR		1	
	VA72	SDV1005E18//2	VARISTOR		1	
	VA74	SDV1005E18//2	VARISTOR		1	
	VA75	SDV1005E18//2	VARISTOR		1	
	VA96	SDV1005E18//2	VARISTOR		1	
	VA171	SDV1005A14//0	VARISTOR		1	
	VA172	SDV1005A14//0	VARISTOR		1	
	VA173	SDV1005A14//0	VARISTOR		1	
	VA174	SDV1005A14//0	VARISTOR		1	
	VA175	SDV1005A14//0	VARISTOR		1	
	VA177	SDV1005A14//0	VARISTOR		1	
	VA195	SDV1005A14//0	VARISTOR		1	
	VA196	SDV1005A14//0	VARISTOR		1	
	VA197	SDV1005A14//0	VARISTOR		1	
	VA301	F0K-0010-00	SURGE ABSORBER		1	
	VA351	F0K-0010-00	SURGE ABSORBER		1	E1,X1
	VA501	SDV1005A14//0	VARISTOR		1	K0
	VA502	SDV1005A14//0	VARISTOR		1	K0
	VA503	SDV1005A14//0	VARISTOR		1	K0
	VA511	SDV1005E18//2	VARISTOR		1	E1,K0
	VA512	SDV1005E18//2	VARISTOR		1	E1,K0
	VA513	SDV1005E18//2	VARISTOR		1	E1,K0
	VA581	SDV1005A14//0	VARISTOR		1	
	VA582	SDV1005A14//0	VARISTOR		1	
	VA583	SDV1005A14//0	VARISTOR		1	
	W301	QAM1484-001	CAR CABLE		1	
	X431	NAX1256-001X	CRYSTAL		1	E1,M1,M2
VIDEO PWB ASSY(XJ8-044K-00) <XJ8>						
	IC100	W3F-0375-00	MCU IC		1	
	IC102	BU4228F	ANALOG IC		1	
	IC103	XC6223B331P-G	ANALOG IC		1	
	IC105	74AHC1G32GW	MOS IC		1	
	IC106	TC7SH17FUJC	MOS IC		1	
	IC200	LM3481MMXNOPB	ANALOG IC		1	
	IC201	TC7SH17FUJC	MOS IC		1	
	IC202	XC6213B332N-G	MOS IC		1	
	IC502	-----	MOS IC	NO SERVICE PART	1	
	IC503	XC6223B331P-G	ANALOG IC		1	
	Q100	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q101	LTC014YEBFS8	DIGI TRANSISTOR		1	
	Q200	LTA043ZEBFS8	DIGI TRANSISTOR		1	
	Q201	LSAR523UBFS8	TRANSISTOR		1	
	Q202	RTQ035N03	FET		1	
	Q203	LSAR523UBFS8	TRANSISTOR		1	
	Q204	LSCR523UBFS8	TRANSISTOR		1	
	Q205	LSCR523UBFS8	TRANSISTOR		1	
	Q206	LSCR523UBFS8	TRANSISTOR		1	
	Q207	LSAR523UBFS8	TRANSISTOR		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
		Q208	LSCR523UBFS8	TRANSISTOR	1	
		Q209	LSCR523UBFS8	TRANSISTOR	1	
		Q210	LSCR523UBFS8	TRANSISTOR	1	
		Q211	LSCR523UBFS8	TRANSISTOR	1	
		Q212	LSCR523UBFS8	TRANSISTOR	1	
		Q213	LTC043ZEBFS8	DIGI TRANSISTOR	1	
		Q214	LTC043ZEBFS8	DIGI TRANSISTOR	1	
		Q600	LSCR523UBFS8	TRANSISTOR	1	
		Q601	LSCR523UBFS8	TRANSISTOR	1	
		Q602	LSCR523UBFS8	TRANSISTOR	1	
		D100	RB521SM-30	DIODE	1	
		D200	SJPB-L4	SCHOTTKY DIODE	1	
		D705	DAN217UM	DIODE	1	
		C100	CC73HCH1H221J	C CAPACITOR	1	
		C101	CC73HCH1H101J	C CAPACITOR	1	
		C102	CC73HCH1H101J	C CAPACITOR	1	
		C103	CC73HCH1H101J	C CAPACITOR	1	
		C104	CC73HCH1H101J	C CAPACITOR	1	
		C105	CC73HCH1H221J	C CAPACITOR	1	
		C106	CK73HXR1H473K	C CAPACITOR	1	
		C107	CK73HXR1A104K	C CAPACITOR	1	
		C108	CK73HXR1A104K	C CAPACITOR	1	
		C109	CK73HXR1A104K	C CAPACITOR	1	
		C111	CK73HXR1C105K	C CAPACITOR	1	
		C112	CK73HXR1C105K	C CAPACITOR	1	
		C113	CK73HXR1C105K	C CAPACITOR	1	
		C114	CK73EXR1E106K	C CAPACITOR	1	
		C115	CK73HXR1C105K	C CAPACITOR	1	
		C116	CK73HXR1A104K	C CAPACITOR	1	
		C117	CK73HXR1A104K	C CAPACITOR	1	
		C119	CK73HXR1H472K	C CAPACITOR	1	
		C120	CK73HXR1H102K	C CAPACITOR	1	
		C121	CK73HXR1C105K	C CAPACITOR	1	
		C127	CK73GXR1A475K	C CAPACITOR	1	
		C200	CK73HXR1C105K	C CAPACITOR	1	
		C205	CK73HXR1H103K	C CAPACITOR	1	
		C206	CK73HXR1H104K	C CAPACITOR	1	
		C207	CK73EXR1H106K	C CAPACITOR	1	
		C208	CK73EXR1H106K	C CAPACITOR	1	
		C209	CK73HXR1A104K	C CAPACITOR	1	
		C210	CK73HXR1C105K	C CAPACITOR	1	
		C211	CC73HCH1H391J	C CAPACITOR	1	
		C212	CK73HXR1C105K	C CAPACITOR	1	
		C213	CK73EXR1E106K	C CAPACITOR	1	
		C214	CK73HXR1A104K	C CAPACITOR	1	
		C215	CK73HXR1A104K	C CAPACITOR	1	
		C216	CK73HXR1C105K	C CAPACITOR	1	
		C217	CK73GXR1A106K	C CAPACITOR	1	
		C218	CK73HXR1H103K	C CAPACITOR	1	
		C219	CK73EXR1H106K	C CAPACITOR	1	
		C220	CK73EXR1H106K	C CAPACITOR	1	
		C221	CK73HXR1C105K	C CAPACITOR	1	
		C222	CK73GXR1A106K	C CAPACITOR	1	
		C400	CK73GXR1C225K	C CAPACITOR	1	
		C403	CK73HXR1C105K	C CAPACITOR	1	
		C509	CK73HXR1C105K	C CAPACITOR	1	
		C510	CK73HXR1C105K	C CAPACITOR	1	
		C511	CK73HXR1H103K	C CAPACITOR	1	
		C512	CK73HXR1E223K	C CAPACITOR	1	
		C513	CK73HXR1E223K	C CAPACITOR	1	
		C514	CK73GXR1C225K	C CAPACITOR	1	
		C515	CK73HXR1E223K	C CAPACITOR	1	
		C517	CK73HXR1E223K	C CAPACITOR	1	
		C518	CK73HXR1C105K	C CAPACITOR	1	
		C520	CK73GXR1C225K	C CAPACITOR	1	
		C521	CK73GXR1A475K	C CAPACITOR	1	
		C539	CK73GXR1C225K	C CAPACITOR	1	
		C540	CK73HXR1E223K	C CAPACITOR	1	
		C600	CK73HXR1A104K	C CAPACITOR	1	
		C601	CK73HXR1A104K	C CAPACITOR	1	
		C602	CK73HXR1A104K	C CAPACITOR	1	
		C603	CK73GXR1A106K	C CAPACITOR	1	
		C604	CK73HXR1H102K	C CAPACITOR	1	
		C605	CK73HXR1H104K	C CAPACITOR	1	
		C606	CK73HXR1H103K	C CAPACITOR	1	
		C607	CK73HXR1H102K	C CAPACITOR	1	
		C608	CK73HXR1H102K	C CAPACITOR	1	
		C609	CK73HXR1H102K	C CAPACITOR	1	
		C611	CK73EXR1E106K	C CAPACITOR	1	
		C612	CK73GXR1A106K	C CAPACITOR	1	
		C701	CK73HXR1H103K	C CAPACITOR	1	
		C702	CK73FXR1C106K	C CAPACITOR	1	
		R35	RK73HB1J000J	MG RESISTOR	1	
		R36	RK73HB1J000J	MG RESISTOR	1	
		R100	RK73HB1J101J	MG RESISTOR	1	
		R101	RK73HB1J473J	MG RESISTOR	1	
		R102	RK73HB1J473J	MG RESISTOR	1	
		R103	RK73HB1J473J	MG RESISTOR	1	
		R104	RK73HB1J473J	MG RESISTOR	1	
		R105	RK73HB1J101J	MG RESISTOR	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R106	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R107	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R108	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R109	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R110	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R111	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R112	RK73HB1J123J	MG RESISTOR	12kΩ 1/16W J	1	
	R115	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R116	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R117	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R120	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R122	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R124	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R125	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R126	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R127	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R128	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R129	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R130	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R131	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R132	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R136	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R137	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R138	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R139	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R140	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R141	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R142	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R143	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R144	RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
	R145	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R146	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R148	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R149	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R150	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R151	RK73HB1J331J	MG RESISTOR	330Ω 1/16W J	1	
	R200	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R201	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R203	RK73GB2A511J	MG RESISTOR	510Ω 1/10W J	1	
	R204	RK73GB2A511J	MG RESISTOR	510Ω 1/10W J	1	
	R207	RK73HH1J104D	MG RESISTOR	100kΩ 1/16W D	1	
	R208	RK73HH1J563D	MG RESISTOR	56kΩ 1/16W D	1	
	R209	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R210	RK73HH1J152D	MG RESISTOR	1.5kΩ 1/16W D	1	
	R211	RK73HH1J164D	MG RESISTOR	160kΩ 1/16W D	1	
	R212	RK73HH1J103D	MG RESISTOR	10kΩ 1/16W D	1	
	R213	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R214	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R215	RK73HH1J563D	MG RESISTOR	56kΩ 1/16W D	1	
	R216	RK73HB1J4R7J	MG RESISTOR	4.7Ω 1/16W J	1	
	R217	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R218	RZ73F0AK33LJ	RESISTOR	0.033Ω 1/3W J	1	
	R219	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R220	RK73GH2A271D	MG RESISTOR	270Ω 1/10W D	1	
	R221	RK73GH2A271D	MG RESISTOR	270Ω 1/10W D	1	
	R222	RK73GH2A271D	MG RESISTOR	270Ω 1/10W D	1	
	R223	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R224	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R225	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R227	RK73GB2A511J	MG RESISTOR	510Ω 1/10W J	1	
	R228	RK73GB2A511J	MG RESISTOR	510Ω 1/10W J	1	
	R229	RK73GH2A271D	MG RESISTOR	270Ω 1/10W D	1	
	R230	RK73GH2A271D	MG RESISTOR	270Ω 1/10W D	1	
	R231	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R232	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R233	RK73GH2A561D	MG RESISTOR	560Ω 1/10W D	1	
	R234	RK73GH2A271D	MG RESISTOR	270Ω 1/10W D	1	
	R235	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R236	RK73GB2A511J	MG RESISTOR	510Ω 1/10W J	1	
	R237	RK73GH2A271D	MG RESISTOR	270Ω 1/10W D	1	
	R238	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R239	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R240	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R241	RK73GH2A561D	MG RESISTOR	560Ω 1/10W D	1	
	R242	RK73GH2A561D	MG RESISTOR	560Ω 1/10W D	1	
	R243	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R244	RK73GH2A561D	MG RESISTOR	560Ω 1/10W D	1	
	R245	RK73GB2A511J	MG RESISTOR	510Ω 1/10W J	1	
	R247	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R248	RK73GH2A561D	MG RESISTOR	560Ω 1/10W D	1	
	R249	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R250	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R251	RK73GH2A561D	MG RESISTOR	560Ω 1/10W D	1	
	R252	RK73GH2A561D	MG RESISTOR	560Ω 1/10W D	1	
	R253	RK73GH2A271D	MG RESISTOR	270Ω 1/10W D	1	
	R254	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R255	RK73GH2A561D	MG RESISTOR	560Ω 1/10W D	1	
	R256	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R257	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R402	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R403	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R404	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R405	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R538	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R539	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R540	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R541	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R542	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R543	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R544	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R545	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R546	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R547	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R548	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R549	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R550	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R551	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R552	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R553	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R554	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R555	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R556	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R557	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R558	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R559	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R560	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R561	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R562	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R563	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R564	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R565	RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	
	R566	RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	
	R567	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R568	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R569	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R571	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R572	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R573	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R574	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R575	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R576	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R577	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R578	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R579	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R580	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R581	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R582	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R583	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R584	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R585	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R586	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R587	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R588	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R589	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R590	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R591	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R592	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R593	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R594	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R595	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R596	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R597	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R598	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R600	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R601	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R603	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R604	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R605	RK73HB1J473J	MG RESISTOR	47kΩ 1/16W J	1	
	R606	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R607	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R608	RK73GB2A101J	MG RESISTOR	100Ω 1/10W J	1	
	R609	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R610	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R611	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R612	RK73GB2A100J	MG RESISTOR	10Ω 1/10W J	1	
	R613	RK73GB2A221J	MG RESISTOR	220Ω 1/10W J	1	
	R614	RK73HH1J301D	MG RESISTOR	300Ω 1/16W D	1	
	R615	RK73HH1J301D	MG RESISTOR	300Ω 1/16W D	1	
	R616	RK73HH1J301D	MG RESISTOR	300Ω 1/16W D	1	
	R617	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R618	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R619	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R621	RK73EB2E151J	MG RESISTOR	150Ω 1/4W J	1	
	R625	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	R626	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
	R630	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R631	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R632	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R633	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R722	RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
	L100	LB73G0BF-002	CHIP FERRITE		1	
	L102	LB73G0BF-003	CHIP FERRITE		1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	L200	LR7920FB220M	CHIP INDUCTOR	22uF	1	
	L201	NQR0716-001X	FERRITE CORE		1	
	L502	LB73G0BF-003	CHIP FERRITE		1	
	L600	LB73G0BF-003	CHIP FERRITE		1	
	L602	LB73G0BF-002	CHIP FERRITE		1	
	CN1	EC720CF-0560A	FFC FPC CONNE		1	
	CN100	EC720AA-0510A	FFC FPC CONNE	10P	1	
	CN400	EC720AA-0540A	FFC FPC CONNE		1	
	CN501	EC720AA-0550A	FFC FPC CONNE	50P	1	
	CN502	EC720AA-0508A	FFC FPC CONNE		1	
	CN600	EC720AA-0522A	FFC FPC CONNE		1	
	VA601	SDV1005E18//2	VARIATOR		1	
	VA602	EZJP0080MA	VARIATOR		1	
	VA603	EZJP0080MA	VARIATOR		1	
	VA604	EZJP0080MA	VARIATOR		1	

OPERATION PWB ASSY(XJ7-042K-00) <XJ7>

IC1	PICA38603-NV	IR DETECT UNIT		1	
D1	NSSM124	LED		1	
D2	NSSM124	LED		1	
D3	NSSM124	LED		1	
D4	NSSM124	LED		1	
C1	CK73GXR1A105K	C CAPACITOR	1uF 10V K	1	
C2	CK73HXR1C104K	C CAPACITOR	0.1uF 16V K	1	
R1	RK73GB2A333J	MG RESISTOR	33kΩ 1/10W J	1	
R2	RK73GB2A103J	MG RESISTOR	10kΩ 1/10W J	1	
R3	RK73GB2A472J	MG RESISTOR	4.7kΩ 1/10W J	1	
R4	RK73GB2A332J	MG RESISTOR	3.3kΩ 1/10W J	1	
R5	RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
CN1	QGF0545F2-13X	FFC/FPC CONNE	FFC/FPC (1-13)	1	
S1	S7A-0001-00	TACTILE PUSH SW		1	
S2	S7A-0001-00	TACTILE PUSH SW		1	
S3	S7A-0001-00	TACTILE PUSH SW		1	
S4	S7A-0001-00	TACTILE PUSH SW		1	
S5	S7A-0001-00	TACTILE PUSH SW		1	
S6	S7A-0001-00	TACTILE PUSH SW		1	
S7	S7A-0001-00	TACTILE PUSH SW		1	

DVD MECHA PWB ASSY (LVA11172-04A) <L17>

IC1	AN41250A	ANALOG IC		1	
IC2	M12L1281686TN	DRAM IC		1	
IC3	WZZ-0025-00	PROGRAMMED IC		1	
IC4	MN2DS0041MD	IC		1	
IC5	BD12KA5FP	ANALOG IC		1	
IC6	XC6120N282N-G	IC		1	
IC8	MM1663DTE	MOS IC		1	
Q1	2SK3019	FET		1	
Q2	2SK3019	FET		1	
Q3	LSCR523EBFS8	TRANSISTOR		1	
Q4	2SB1709MG	TRANSISTOR		1	
Q5	LSCR523EBFS8	TRANSISTOR		1	
Q6	2SB1709MG	TRANSISTOR		1	
Q11	LTA014TEBFS8	DIGI TRANSISTOR		1	
Q12	LTA014TEBFS8	DIGI TRANSISTOR		1	
D1	TAN1102W-22	INFRARED LED		1	
D4	TAN1102W-22	INFRARED LED		1	
D5	1SS355VM	DIODE		1	
C1	CK73HBB1E103K	C CAPACITOR	0.01uF 25V K	1	
C2	NCJ20JK-106X-R	C CAPACITOR	10uF 6.3V K	1	
C6	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
C7	CK73HBB1E103K	C CAPACITOR	0.01uF 25V K	1	
C8	CK73HBB1E103K	C CAPACITOR	0.01uF 25V K	1	
C10	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
C12	NCJ20JK-106X-R	C CAPACITOR	10uF 6.3V K	1	
C13	NCJ20JK-106X-R	C CAPACITOR	10uF 6.3V K	1	
C14	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
C16	CK73HBB1C333K	C CAPACITOR	0.033uF 16V K	1	
C17	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
C18	CC73HCH1H120J	C CAPACITOR	12pF 50V J	1	
C19	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
C20	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
C21	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
C22	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
C23	CC73HCH1H120J	C CAPACITOR	12pF 50V J	1	
C24	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
C25	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
C26	CC73HCH1H102J	C CAPACITOR	1000pF 50V J	1	
C28	NCJ20JK-106X-R	C CAPACITOR	10uF 6.3V K	1	
C29	NCJ20JK-106X-R	C CAPACITOR	10uF 6.3V K	1	
C31	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
C33	CK73HBB1H682K	C CAPACITOR	6800pF 50V K	1	
C34	CK73HBB1H682K	C CAPACITOR	6800pF 50V K	1	
C35	CC73HCH1H681J	C CAPACITOR	680pF 50V J	1	
C36	CC73HCH1H471J	C CAPACITOR	470pF 50V J	1	
C37	NCJ20JK-106X-R	C CAPACITOR	10uF 6.3V K	1	
C38	NCJ20JK-106X-R	C CAPACITOR	10uF 6.3V K	1	
C45	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
C47	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
C48	CK73HBB1H222K	C CAPACITOR	2200pF 50V K	1	
C49	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
C50	CK73HBB1H222K	C CAPACITOR	2200pF 50V K	1	
C51	CK73HBB1H472K	C CAPACITOR	4700pF 50V K	1	
C52	CK73HBB1E103K	C CAPACITOR	0.01uF 25V K	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C53	CK73HBB1H222K	C CAPACITOR	2200pF 50V K	1	
	C55	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C56	CK73HBB1H222K	C CAPACITOR	2200pF 50V K	1	
	C57	CK73HBB1E103K	C CAPACITOR	0.01uF 25V K	1	
	C58	CK73HBB1E103K	C CAPACITOR	0.01uF 25V K	1	
	C59	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C60	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C61	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C62	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C63	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C64	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C65	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C66	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C67	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C68	CK73HBB1E103K	C CAPACITOR	0.01uF 25V K	1	
	C70	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
	C71	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C74	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C75	CC73HCH1H101J	C CAPACITOR	100pF 50V J	1	
	C76	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C77	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C78	CK73GXR0J475K	C CAPACITOR	4.7uF 6.3V K	1	
	C79	CK73HBB1H222K	C CAPACITOR	2200pF 50V K	1	
	C80	CK73HBB1H222K	C CAPACITOR	2200pF 50V K	1	
	C81	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
	C82	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
	C83	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
	C84	NCJ20JK-106X-R	C CAPACITOR	10uF 6.3V K	1	
	C85	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C86	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C87	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C88	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C89	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C90	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C91	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C92	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C93	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C94	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C95	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C96	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C101	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C102	CK73FXR0J226M	C CAPACITOR	22uF 6.3V M	1	
	C103	CK73HBB1H222K	C CAPACITOR	2200pF 50V K	1	
	C104	CK73HBB1H222K	C CAPACITOR	2200pF 50V K	1	
	C105	CC73HCH1H150J	C CAPACITOR	15pF 50V J	1	
	C112	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C115	CK73HXR0J105K	C CAPACITOR	1uF 6.3V K	1	
	C120	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	C121	CK73HBB1A104K	C CAPACITOR	0.1uF 10V K	1	
	R1	RK73GB2A561J	MG RESISTOR	560Ω 1/10W J	1	
	R2	RK73HB1J271J	MG RESISTOR	270Ω 1/16W J	1	
	R3	RK73HB1J301J	MG RESISTOR	300Ω 1/16W J	1	
	R4	RK73GB2A561J	MG RESISTOR	560Ω 1/10W J	1	
	R5	RK73HB1J163J	MG RESISTOR	16kΩ 1/16W J	1	
	R6	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R7	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R8	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R9	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R10	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R11	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R12	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R15	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R16	RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
	R17	RK73HB1J105J	MG RESISTOR	1MΩ 1/16W J	1	
	R18	RK73HH1J303D	MG RESISTOR	30kΩ 1/16W D	1	
	R19	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R20	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R21	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R22	RK73HB1J560J	MG RESISTOR	56Ω 1/16W J	1	
	R23	RK73HB1J2R2J	MG RESISTOR	2.2Ω 1/16W J	1	
	R25	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R27	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R28	RK73HB1J100J	MG RESISTOR	10Ω 1/16W J	1	
	R29	RK73HB1J560J	MG RESISTOR	56Ω 1/16W J	1	
	R30	RK73HB1J2R2J	MG RESISTOR	2.2Ω 1/16W J	1	
	R31	RK73PB2H270J	MG RESISTOR	27Ω 1/2W J	1	
	R32	RK73HB1J203J	MG RESISTOR	20kΩ 1/16W J	1	
	R33	RK73HB1J333J	MG RESISTOR	33kΩ 1/16W J	1	
	R34	RK73HB1J471J	MG RESISTOR	470Ω 1/16W J	1	
	R35	RK73PB2H270J	MG RESISTOR	27Ω 1/2W J	1	
	R51	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R52	RK73HB1J223J	MG RESISTOR	22kΩ 1/16W J	1	
	R53	RK73POCMR27J	MG RESISTOR	0.27Ω 1/2W J	1	
	R54	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R55	RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
	R56	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R57	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R58	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R59	RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
	R60	RK73HB1J821J	MG RESISTOR	820Ω 1/16W J	1	

MODEL	MARK	MODEL	MARK	MODEL	MARK	MODEL	MARK
DNX9180DABS	E1	DNX9180DABS	X1	DNX9180S	M1	DNX9180SM	M2
DNX995S	K0						

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
R61		RK73HB1J242J	MG RESISTOR	2.4kΩ 1/16W J	1	
R62		RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
R63		RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	
R64		RK73HB1J202J	MG RESISTOR	2kΩ 1/16W J	1	
R65		RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
R66		RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
R69		RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
R70		RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
R73		RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
R74		RK73HB1J4R7J	MG RESISTOR	4.7Ω 1/16W J	1	
R75		RK73HB1J000J	MG RESISTOR	0Ω 1/16W J	1	
R76		RK73HB1J472J	MG RESISTOR	4.7kΩ 1/16W J	1	
R77		RK73HB1J4R7J	MG RESISTOR	4.7Ω 1/16W J	1	
R78		RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
R79		RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
R80		RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
R81		RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
R82		RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
R86		RK73HB1J102J	MG RESISTOR	1kΩ 1/16W J	1	
R92		RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
R95		RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
R96		RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
R105		RK73HB1J101J	MG RESISTOR	100Ω 1/16W J	1	
R106		RK73HB1J103J	MG RESISTOR	10kΩ 1/16W J	1	
R107		RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
R108		RK73HB1J221J	MG RESISTOR	220Ω 1/16W J	1	
R113		RK73HB1J470J	MG RESISTOR	47Ω 1/16W J	1	
R114		RK73HB1J5901D	MG RESISTOR	5.90kΩ 1/16W D	1	
R120		RK73HB1J432J	MG RESISTOR	4.3kΩ 1/16W J	1	
R121		RK73HB1J242J	MG RESISTOR	2.4kΩ 1/16W J	1	
R122		RK73HB1J162J	MG RESISTOR	1.6kΩ 1/16W J	1	
R123		RK73HB1J332J	MG RESISTOR	3.3kΩ 1/16W J	1	
R125		RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
R128		RK73GB2A000J	MG RESISTOR	0Ω 1/10W J	1	
CN1		EC720AA-0526A	FFC/FPC CONNE		1	
CN4		EC720AA-0535A	FFC FPC CONNE		1	
CN5		EC720AA-0518A	FFC FPC CONNE		1	
CN9		QGA1501F4-03W	W TO B CONNE	W-B (1-3)	1	
PH1		PS1192HB-22-X	OPT TRANSMITTER		1	
PH2		PS1192HB-22-X	OPT TRANSMITTER		1	
S1		NSW0351-001X	LEVER SWITCH		1	
TH1		TH05-3H103F	N THERMISTOR		1	
X1		NAX1135-001X	CRYSTAL		1	