



MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
<b>EXPLODED VIEW(UNIT) &lt;200&gt;</b>						
	F1	F52-0046-05	FUSE (40A)		3	
	FC1	E39-1301-05	FLAT CABLE (18P)		1	
	FC2	E39-1302-05	FLAT CABLE (10P)		1	
	A	N09-6931-05	SEMS (TAPTITE SCREW)		9	
	B	N09-6932-15	DRESSED SCREW		2	
	C	N89-3006-43	BINDING HEAD		4	
	D	N09-6944-05	TAPTITE SCREW		11	
	E	N80-3010-43	PAN HEAD TAPTITE SCREW		7	
	G	N09-6365-05	SEMS (TAPTITE SCREW)		4	
	H	N09-6947-08	THICK HEXAGONAL SCREW		2	
	J	N09-6948-08	THIN HEXAGONAL SCREW		11	
	K	N09-6447-05	TAPTITE SCREW		2	
	L	N09-6865-05	MACHINE SCREW		2	
	M	N89-3008-48	BINDING HEAD		10	
	N	N09-6135-05	TAPTITE SCREW (3X8)		4	
	P	N10-2030-48	HEXAGON NUT (M3)		2	
	Q	N09-6945-05	SEMS (TAPTITE SCREW)		4	
	201	A21-6882-03	DRESSING PANEL		1	
	203	A64-5406-02	PANEL (REAR)		1	
	204	A64-5407-02	PANEL (FRONT)		1	
	205	B07-3374-13	ESCUTCHEON		1	
	206	B07-3384-03	ESCUTCHEON		1	
	207	B19-2623-04	LIGHTING BOARD		1	
	208	B07-3381-03	ESCUTCHEON (FOOT)		2	
	209	B43-1553-04	BADGE		1	
	210	F09-2974-05	FAN		1	
	220	N99-1843-05	WRENCH KEY SET		1	
	501	B64-5062-00	INSTRUCTION MANUAL ENG FRE SPA		1	
	502	B64-5063-00	INSTRUCTION MANUAL GER DUT ITA		1	W1
	503	B64-5064-00	INSTRUCTION MANUAL POR RUS UKR		1	W1
	504	B64-5065-00	INSTRUCTION MANUAL ENG CHI		1	W1
	505	H54-5261-13	ITEM CARTON CASE		1	K0
	505	H54-5262-13	ITEM CARTON CASE		1	W1

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
<b>AUDIO UNIT(X09-9160-10) &lt;X09&gt;</b>						
	IC11	TL494IDR	ANALOGUE IC		1	
	IC101	BA4560RF	ANALOGUE IC		1	
	IC111	BA4560RF	ANALOGUE IC		1	
	IC131	BA4560RF	ANALOGUE IC		1	
	IC141	BA4560RF	ANALOGUE IC		1	
	IC161	BA4560RF	ANALOGUE IC		1	
	IC171	BA4560RF	ANALOGUE IC		1	
	IC211	BA4560RF	ANALOGUE IC		1	
	IC221	BA4564RFV	ANALOGUE IC		1	
	IC241	BA4560RF	ANALOGUE IC		1	
	IC251	NJM4565E-ZB	ANALOGUE IC		1	
	IC281	BA4560RF	ANALOGUE IC		1	
	IC291	BA4564RFV	ANALOGUE IC		1	
	IC311	BA4560RF	ANALOGUE IC		1	
	IC321	NJM4565E-ZB	ANALOGUE IC		1	
	IC361	BA4560RF	ANALOGUE IC		1	
	IC371	BA4560RF	ANALOGUE IC		1	
	IC381	BA4564RFV	ANALOGUE IC		1	
	IC501	IRS2092STRPBF	MOS-IC		1	
	IC502	IRS2092STRPBF	MOS-IC		1	
	IC581	BA4560RF	ANALOGUE IC		1	
	IC601	IRS2092STRPBF	MOS-IC		1	
	IC602	IRS2092STRPBF	MOS-IC		1	
	IC701	IRS2092STRPBF	MOS-IC		1	
	IC702	IRS2092STRPBF	MOS-IC		1	
	IC781	BA4560RF	ANALOGUE IC		1	
	IC851	BA2903F	ANALOGUE IC		1	
	IC911	BA2902FV	ANALOGUE IC		1	
	IC921	BA4564RFV	ANALOGUE IC		1	
	Q20	RT1P141M-T111	TRANSISTOR		1	
	Q21	RT1N141M-T111	TRANSISTOR		1	
	Q22	RT1N141M-T111	TRANSISTOR		1	
	Q23	RT1N141M-T111	TRANSISTOR		1	
	Q25	2SAR293P	TRANSISTOR		1	
	Q27	2SC4154(F)	TRANSISTOR		1	
	Q28	2SC4154(F)	TRANSISTOR		1	
	Q35	RT1N141M-T111	TRANSISTOR		1	
	Q37	2SA1577	TRANSISTOR		1	
	Q38	2SA1577	TRANSISTOR		1	
	Q41	STP60NF06FP	FET		1	
	Q42	STP60NF06FP	FET		1	
	Q43	STP60NF06FP	FET		1	
	Q44	STP60NF06FP	FET		1	
	Q45	STP60NF06FP	FET		1	
	Q46	STP60NF06FP	FET		1	
	Q65	KTC2026-P	TRANSISTOR		1	
	Q66	KTA1046-P	TRANSISTOR		1	
	Q69	2SC4154(F)	TRANSISTOR		1	
	Q70	2SC4154(F)	TRANSISTOR		1	
	Q75	KTC2026-P	TRANSISTOR		1	
	Q79	2SCR533D	TRANSISTOR		1	
	Q81	ISA1602AM1(F)	TRANSISTOR		1	
	Q84	2SC4154(F)	TRANSISTOR		1	
	Q89	RT1P141M-T111	TRANSISTOR		1	
	Q91	ISA1602AM1(F)	TRANSISTOR		1	
	Q96	2SC4097	TRANSISTOR		1	
	Q97	RT1P141M-T111	TRANSISTOR		1	
	Q99	RT1N141M-T111	TRANSISTOR		1	
	Q231	2SC4154(F)	TRANSISTOR		1	
	Q232	2SC4154(F)	TRANSISTOR		1	
	Q235	2SA1576A	TRANSISTOR		1	
	Q236	2SA1576A	TRANSISTOR		1	
	Q301	2SC4154(F)	TRANSISTOR		1	
	Q302	2SC4154(F)	TRANSISTOR		1	
	Q305	2SA1576A	TRANSISTOR		1	
	Q306	2SA1576A	TRANSISTOR		1	
	Q351	RT1P141M-T111	TRANSISTOR		1	
	Q352	RT1N141M-T111	TRANSISTOR		1	
	Q355	RT1N141M-T111	TRANSISTOR		1	
	Q356	RT1N141M-T111	TRANSISTOR		1	
	Q391	2SC4154(F)	TRANSISTOR		1	
	Q392	RT1P141M-T111	TRANSISTOR		1	
	Q511	IRFR4615PBF	FET		1	
	Q512	IRFR4615PBF	FET		1	
	Q513	IRFR4615PBF	FET		1	
	Q514	IRFR4615PBF	FET		1	
	Q541	2SC4154(F)	TRANSISTOR		1	
	Q542	2SC4154(F)	TRANSISTOR		1	
	Q571	2SC4154(F)	TRANSISTOR		1	
	Q572	ISA1602AM1(F)	TRANSISTOR		1	
	Q611	IRFR4615PBF	FET		1	
	Q612	IRFR4615PBF	FET		1	
	Q613	IRFR4615PBF	FET		1	
	Q614	IRFR4615PBF	FET		1	
	Q641	2SC4154(F)	TRANSISTOR		1	
	Q642	2SC4154(F)	TRANSISTOR		1	
	Q671	2SC4154(F)	TRANSISTOR		1	
	Q672	ISA1602AM1(F)	TRANSISTOR		1	
	Q711	AUIRFS4410Z	FET		1	
	Q712	AUIRFS4410Z	FET		1	
	Q713	AUIRFS4410Z	FET		1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	Q714	AUIRFS4410Z	FET		1	
	Q741	2SC4154(F)	TRANSISTOR		1	
	Q742	2SC4154(F)	TRANSISTOR		1	
	Q801	2SA1163-F	TRANSISTOR		1	
	Q802	2SA1163-F	TRANSISTOR		1	
	Q805	2SA1163-F	TRANSISTOR		1	
	Q806	2SA1163-F	TRANSISTOR		1	
	Q809	2SC2713-F	TRANSISTOR		1	
	Q810	2SC2713-F	TRANSISTOR		1	
	Q842	2SC4154(F)	TRANSISTOR		1	
	Q843	ISA1602AM1(F)	TRANSISTOR		1	
	Q853	RT1N141M-T111	TRANSISTOR		1	
	Q854	RT1N141M-T111	TRANSISTOR		1	
	Q855	RT1N141M-T111	TRANSISTOR		1	
	Q856	RT1N141M-T111	TRANSISTOR		1	
	Q867	2SC4154(F)	TRANSISTOR		1	
	Q868	2SC4154(F)	TRANSISTOR		1	
	Q871	2SC4154(F)	TRANSISTOR		1	
	Q872	2SC4154(F)	TRANSISTOR		1	
	Q894	2SC4154(F)	TRANSISTOR		1	
	Q895	RT1N141M-T111	TRANSISTOR		1	
	Q896	2SD1766	TRANSISTOR		1	
	Q941	RT1P141M-T111	TRANSISTOR		1	
	Q942	RT1N141M-T111	TRANSISTOR		1	
	Q943	RT1N141M-T111	TRANSISTOR		1	
	Q961	2SCR293P	TRANSISTOR		1	
	Q962	2SAR293P	TRANSISTOR		1	
	Q981	2SCR533D	TRANSISTOR		1	
	Q982	2SAR533D	TRANSISTOR		1	
	D15	HSU119TRF-E	DIODE		1	
	D28	RKZ15KG(B2)	ZENER DIODE		1	
	D29	RKZ6.2KG(B2)	ZENER DIODE		1	
	D31	HSU119TRF-E	DIODE		1	
	D35	RKZ5.1KG(B2)	ZENER DIODE		1	
	D36	B30-1743-05	LED(RED LED)		1	
	D37	HSU119TRF-E	DIODE		1	
	D38	HSU119TRF-E	DIODE		1	
	D51	FCH10A20	SCHOTTKY BARRIER DIODE		1	
	D52	FRH10A20	SCHOTTKY BARRIER DIODE		1	
	D55	FCH20A15	SCHOTTKY BARRIER DIODE		1	
	D56	FRH20A15	SCHOTTKY BARRIER DIODE		1	
	D65	RKZ15KG(B2)	ZENER DIODE		1	
	D66	RKZ15KG(B2)	ZENER DIODE		1	
	D75	RKZ12KG(B2)	ZENER DIODE		1	
	D79	RKZ12KG(B2)	ZENER DIODE		1	
	D83	LM1MA142WA-G	DIODE		1	
	D84	LM1MA142WK-G	DIODE		1	
	D87	HSU119TRF-E	DIODE		1	
	D97	HSU119TRF-E	DIODE		1	
	D99	HSU119TRF-E	DIODE		1	
	D101	HSU119TRF-E	DIODE		1	
	D102	HSU119TRF-E	DIODE		1	
	D103	HSU119TRF-E	DIODE		1	
	D104	HSU119TRF-E	DIODE		1	
	D131	HSU119TRF-E	DIODE		1	
	D132	HSU119TRF-E	DIODE		1	
	D133	HSU119TRF-E	DIODE		1	
	D134	HSU119TRF-E	DIODE		1	
	D161	LM1MA142WK-G	DIODE		1	
	D162	LM1MA142WA-G	DIODE		1	
	D191	RKZ6.8KG(B2)	ZENER DIODE		1	
	D192	RKZ6.8KG(B2)	ZENER DIODE		1	
	D221	HSU119TRF-E	DIODE		1	
	D222	HSU119TRF-E	DIODE		1	
	D223	HSU119TRF-E	DIODE		1	
	D224	HSU119TRF-E	DIODE		1	
	D231	HSU119TRF-E	DIODE		1	
	D232	HSU119TRF-E	DIODE		1	
	D235	HSU119TRF-E	DIODE		1	
	D236	HSU119TRF-E	DIODE		1	
	D241	RKZ27KG(B)	ZENER DIODE		1	
	D242	RKZ27KG(B)	ZENER DIODE		1	
	D291	HSU119TRF-E	DIODE		1	
	D292	HSU119TRF-E	DIODE		1	
	D293	HSU119TRF-E	DIODE		1	
	D294	HSU119TRF-E	DIODE		1	
	D301	HSU119TRF-E	DIODE		1	
	D302	HSU119TRF-E	DIODE		1	
	D305	HSU119TRF-E	DIODE		1	
	D306	HSU119TRF-E	DIODE		1	
	D311	RKZ27KG(B)	ZENER DIODE		1	
	D312	RKZ27KG(B)	ZENER DIODE		1	
	D381	HSU119TRF-E	DIODE		1	
	D382	HSU119TRF-E	DIODE		1	
	D535	HSU119TRF-E	DIODE		1	
	D536	HSU119TRF-E	DIODE		1	
	D537	HSU119TRF-E	DIODE		1	
	D538	HSU119TRF-E	DIODE		1	
	D553	HSU119TRF-E	DIODE		1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	D554	HSU119TRF-E	DIODE		1	
	D559	RF101L2S	DIODE		1	
	D560	RF101L2S	DIODE		1	
	D575	HSU119TRF-E	DIODE		1	
	D576	HSU119TRF-E	DIODE		1	
	D581	HSU119TRF-E	DIODE		1	
	D635	HSU119TRF-E	DIODE		1	
	D636	HSU119TRF-E	DIODE		1	
	D637	HSU119TRF-E	DIODE		1	
	D638	HSU119TRF-E	DIODE		1	
	D653	HSU119TRF-E	DIODE		1	
	D654	HSU119TRF-E	DIODE		1	
	D659	RF101L2S	DIODE		1	
	D660	RF101L2S	DIODE		1	
	D675	HSU119TRF-E	DIODE		1	
	D676	HSU119TRF-E	DIODE		1	
	D681	HSU119TRF-E	DIODE		1	
	D711	RF101L2S	DIODE		1	
	D712	RF101L2S	DIODE		1	
	D713	RF101L2S	DIODE		1	
	D714	RF101L2S	DIODE		1	
	D737	HSU119TRF-E	DIODE		1	
	D738	HSU119TRF-E	DIODE		1	
	D753	HSU119TRF-E	DIODE		1	
	D754	HSU119TRF-E	DIODE		1	
	D759	RF101L2S	DIODE		1	
	D760	RF101L2S	DIODE		1	
	D781	HSU119TRF-E	DIODE		1	
	D851	HSU119TRF-E	DIODE		1	
	D852	HSU119TRF-E	DIODE		1	
	D853	RKZ11KG(B2)	ZENER DIODE		1	
	D855	RKZ12KG(B2)	ZENER DIODE		1	
	D891	HSU119TRF-E	DIODE		1	
	D892	HSU119TRF-E	DIODE		1	
	D893	HSU119TRF-E	DIODE		1	
	D895	1SR154-400	DIODE		1	
	D896	RKZ12KG(B2)	ZENER DIODE		1	
	D897	HSU119TRF-E	DIODE		1	
	D898	RKZ8.2KG(B2)	ZENER DIODE		1	
	D901	HSU119TRF-E	DIODE		1	
	D902	LM1MA142WA-G	DIODE		1	
	D920	RKZ5.1KG(B2)	ZENER DIODE		1	
	D931	HSU119TRF-E	DIODE		1	
	D963	RKZ5.6KG(B2)	ZENER DIODE		1	
	D964	RKZ5.6KG(B2)	ZENER DIODE		1	
	D981	RKZ13KG(B2)	ZENER DIODE		1	
	D982	RKZ13KG(B2)	ZENER DIODE		1	
	C1	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C2	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C3	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C4	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C5	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C6	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C7	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C12	CK73GB1C105K	CHIP C	1.0UF 16V K	1	
	C13	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C15	CE32CL0J470M	ELECTRO	47UF 6.3V M	1	
	C16	CC73GCH1H102J	CHIP C	1000PF J	1	
	C17	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C18	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C19	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C20	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C21	CC73GCH1H102J	CHIP C	1000PF J	1	
	C22	CK73GB1C105K	CHIP C	1.0UF 16V K	1	
	C24	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C28	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C29	CC73GCH1H102J	CHIP C	1000PF J	1	
	C30	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C31	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C32	CK73EB1E106K	CHIP C	10UF 25V K	1	
	C33	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C41	C90-6936-05	ELECTRO	3900UF 16WV	1	
	C42	C90-6936-05	ELECTRO	3900UF 16WV	1	
	C47	CK73GB1H222K	CHIP C	2200PF 50V K	1	
	C48	CK73GB1H222K	CHIP C	2200PF 50V K	1	
	C49	CK73GB1H222K	CHIP C	2200PF 50V K	1	
	C51	C90-7002-05	ELECTRO	2200UF 35WV	1	
	C52	C90-7002-05	ELECTRO	2200UF 35WV	1	
	C53	CC73GCH1H102J	CHIP C	1000PF J	1	
	C54	CC73GCH1H102J	CHIP C	1000PF J	1	
	C55	C90-6929-05	ELECTRO	3300UF 50WV	1	
	C56	C90-6929-05	ELECTRO	3300UF 50WV	1	
	C57	CC73GCH1H102J	CHIP C	1000PF J	1	
	C58	CC73GCH1H102J	CHIP C	1000PF J	1	
	C65	CK73EB1E106K	CHIP C	10UF 25V K	1	
	C66	CK73EB1E106K	CHIP C	10UF 25V K	1	
	C69	CE32CL1C470M	ELECTRO	47UF 16V M	1	
	C70	CE32CL1C470M	ELECTRO	47UF 16V M	1	
	C71	CC73GCH1H020C	CHIP C	2.0PF 50V C	1	
	C72	CC73GCH1H020C	CHIP C	2.0PF 50V C	1	
	C73	CC73GCH1H020C	CHIP C	2.0PF 50V C	1	
	C74	CC73GCH1H020C	CHIP C	2.0PF 50V C	1	
	C75	CK73EB1E106K	CHIP C	10UF 25V K	1	
	C76	CE32CL1C470M	ELECTRO	47UF 16V M	1	
	C79	CK73EB1E106K	CHIP C	10UF 25V K	1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C80	CE32CL1C470M	ELECTRO	47UF 16V M	1	
	C81	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C82	CK73EB1E106K	CHIP C	10UF 25V K	1	
	C86	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C96	CE32BR1E101M	ELECTRO	100UF 25V M	1	
	C101	CC73GCH1H102J	CHIP C	1000PF J	1	
	C102	CC73GCH1H102J	CHIP C	1000PF J	1	
	C103	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C104	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C105	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C106	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C111	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C112	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C115	CC73GCH1H560J	CHIP C	56PF 50V J	1	
	C116	CC73GCH1H560J	CHIP C	56PF 50V J	1	
	C117	CC73GCH1H560J	CHIP C	56PF 50V J	1	
	C118	CC73GCH1H560J	CHIP C	56PF 50V J	1	
	C119	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C120	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C127	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C128	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C131	CC73GCH1H102J	CHIP C	1000PF J	1	
	C132	CC73GCH1H102J	CHIP C	1000PF J	1	
	C133	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C134	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C135	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C136	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C141	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C142	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C145	CC73GCH1H560J	CHIP C	56PF 50V J	1	
	C146	CC73GCH1H560J	CHIP C	56PF 50V J	1	
	C147	CC73GCH1H560J	CHIP C	56PF 50V J	1	
	C148	CC73GCH1H560J	CHIP C	56PF 50V J	1	
	C149	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C150	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C157	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C158	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C161	CC73GCH1H102J	CHIP C	1000PF J	1	
	C162	CC73GCH1H102J	CHIP C	1000PF J	1	
	C163	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C164	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C165	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C167	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C171	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C173	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C174	CC73GCH1H330J	CHIP C	33PF 50V J	1	
	C175	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C179	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C180	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C191	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C196	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C211	CC73GCH1H470J	CHIP C	47PF 50V J	1	
	C212	CC73GCH1H470J	CHIP C	47PF 50V J	1	
	C219	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C220	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C221	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C222	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C223	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C224	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C229	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C230	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C241	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C242	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C243	CK73GB1C224K	CHIP C	0.22UF 16V K	1	
	C244	CK73GB1C224K	CHIP C	0.22UF 16V K	1	
	C245	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C249	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C250	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C253	CC73GCH1H821J	CHIP C	820PF 50V J	1	
	C254	CC73GCH1H821J	CHIP C	820PF 50V J	1	
	C255	CC73GCH1H681J	CHIP C	680PF 50V J	1	
	C256	CC73GCH1H681J	CHIP C	680PF 50V J	1	
	C259	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C260	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C275	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C281	CC73GCH1H470J	CHIP C	47PF 50V J	1	
	C282	CC73GCH1H470J	CHIP C	47PF 50V J	1	
	C289	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C290	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C291	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C292	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C293	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C294	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C299	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C300	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C311	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C312	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C313	CK73GB1C224K	CHIP C	0.22UF 16V K	1	
	C314	CK73GB1C224K	CHIP C	0.22UF 16V K	1	
	C319	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C320	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C323	CC73GCH1H821J	CHIP C	820PF 50V J	1	
	C324	CC73GCH1H821J	CHIP C	820PF 50V J	1	
	C325	CC73GCH1H681J	CHIP C	680PF 50V J	1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C326	CC73GCH1H681J	CHIP C	680PF 50V J	1	
	C339	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C340	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C351	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C352	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C364	CC73GCH1H221J	CHIP C	220PF 50V J	1	
	C369	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C370	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C371	CE32CL1V4R7M	ELECTRO	4.7UF 35VW M	1	
	C372	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C377	CC73GCH1H101J	CHIP C	100PF 50V J	1	
	C379	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C380	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C382	CK73GB1H683K	CHIP C	0.068UF 50V K	1	
	C383	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C385	CK73GB1H223K	CHIP C	0.022UF 50V K	1	
	C386	CK73GB1C224K	CHIP C	0.22UF 16V K	1	
	C387	CK73GB1H223K	CHIP C	0.022UF 50V K	1	
	C389	CK73GB1H333K	CHIP C	0.033UF 50V K	1	
	C393	CC73GCH1H101J	CHIP C	100PF 50V J	1	
	C395	CC73GCH1H101J	CHIP C	100PF 50V J	1	
	C399	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C400	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C501	CE32CL1C470M	ELECTRO	47UF 16V M	1	
	C502	CE32CL1C470M	ELECTRO	47UF 16V M	1	
	C503	CC73GCH1H331J	CHIP C	330PF 50V J	1	
	C504	CC73GCH1H331J	CHIP C	330PF 50V J	1	
	C505	CC73GCH1H102J	CHIP C	1000PF J	1	
	C506	CC73GCH1H102J	CHIP C	1000PF J	1	
	C507	CC73GCH1H102J	CHIP C	1000PF J	1	
	C508	CC73GCH1H102J	CHIP C	1000PF J	1	
	C509	CC73GCH1H102J	CHIP C	1000PF J	1	
	C510	CC73GCH1H102J	CHIP C	1000PF J	1	
	C511	CC73GCH1H102J	CHIP C	1000PF J	1	
	C512	CC73GCH1H102J	CHIP C	1000PF J	1	
	C513	CC73GCH1H102J	CHIP C	1000PF J	1	
	C514	CC73GCH1H102J	CHIP C	1000PF J	1	
	C515	CC73GCH1H102J	CHIP C	1000PF J	1	
	C516	CC73GCH1H102J	CHIP C	1000PF J	1	
	C517	CC73GCH1H102J	CHIP C	1000PF J	1	
	C518	CC73GCH1H102J	CHIP C	1000PF J	1	
	C519	CC73GCH1H151J	CHIP C	150PF 50V J	1	
	C520	CC73GCH1H151J	CHIP C	150PF 50V J	1	
	C521	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C522	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C523	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C524	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C525	CF92JV1H105J	FILM C	1UF 50V J	1	
	C526	CF92JV1H105J	FILM C	1UF 50V J	1	
	C527	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C528	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C529	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C530	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C531	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C532	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C533	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C534	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C535	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C536	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C541	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C542	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C543	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C544	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C545	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C546	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C551	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C552	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C557	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C558	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C559	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C560	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C561	CE32CC1V220M	ELECTRO	22UF 35V M	1	
	C562	CE32CC1V220M	ELECTRO	22UF 35V M	1	
	C563	CE32CC1V220M	ELECTRO	22UF 35V M	1	
	C564	CE32CC1V220M	ELECTRO	22UF 35V M	1	
	C565	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C566	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C567	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C568	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C571	CK73GB1H102K	CHIP C	1000PF 50V K	1	
	C576	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C589	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C590	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C601	CE32CL1C470M	ELECTRO	47UF 16V M	1	
	C602	CE32CL1C470M	ELECTRO	47UF 16V M	1	
	C603	CC73GCH1H331J	CHIP C	330PF 50V J	1	
	C604	CC73GCH1H331J	CHIP C	330PF 50V J	1	
	C605	CC73GCH1H102J	CHIP C	1000PF J	1	
	C606	CC73GCH1H102J	CHIP C	1000PF J	1	
	C607	CC73GCH1H102J	CHIP C	1000PF J	1	
	C608	CC73GCH1H102J	CHIP C	1000PF J	1	
	C609	CC73GCH1H102J	CHIP C	1000PF J	1	
	C610	CC73GCH1H102J	CHIP C	1000PF J	1	
	C611	CC73GCH1H102J	CHIP C	1000PF J	1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C612	CC73GCH1H102J	CHIP C	1000PF J	1	
	C613	CC73GCH1H102J	CHIP C	1000PF J	1	
	C614	CC73GCH1H102J	CHIP C	1000PF J	1	
	C615	CC73GCH1H102J	CHIP C	1000PF J	1	
	C616	CC73GCH1H102J	CHIP C	1000PF J	1	
	C617	CC73GCH1H102J	CHIP C	1000PF J	1	
	C618	CC73GCH1H102J	CHIP C	1000PF J	1	
	C619	CC73GCH1H151J	CHIP C	150PF 50V J	1	
	C620	CC73GCH1H151J	CHIP C	150PF 50V J	1	
	C621	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C622	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C623	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C624	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C625	CF92JV1H105J	FILM C	1UF 50V J	1	
	C626	CF92JV1H105J	FILM C	1UF 50V J	1	
	C627	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C628	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C629	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C630	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C631	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C632	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C633	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C634	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C635	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C636	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C641	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C642	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C643	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C644	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C645	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C646	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C651	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C652	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C657	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C658	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C659	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C660	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C661	CE32CC1V220M	ELECTRO	22UF 35V M	1	
	C662	CE32CC1V220M	ELECTRO	22UF 35V M	1	
	C663	CE32CC1V220M	ELECTRO	22UF 35V M	1	
	C664	CE32CC1V220M	ELECTRO	22UF 35V M	1	
	C665	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C666	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C667	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C668	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C671	CK73GB1H102K	CHIP C	1000PF 50V K	1	
	C676	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C701	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C702	CE32CL1C220M	ELECTRO	22UF 16V M	1	
	C703	CC73GCH1H331J	CHIP C	330PF 50V J	1	
	C704	CC73GCH1H331J	CHIP C	330PF 50V J	1	
	C705	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C706	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C707	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C708	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C709	CC73GCH1H102J	CHIP C	1000PF J	1	
	C710	CC73GCH1H102J	CHIP C	1000PF J	1	
	C711	CC73GCH1H102J	CHIP C	1000PF J	1	
	C712	CC73GCH1H102J	CHIP C	1000PF J	1	
	C713	CC73GCH1H102J	CHIP C	1000PF J	1	
	C714	CC73GCH1H102J	CHIP C	1000PF J	1	
	C715	CK73GB1H472K	CHIP C	4700PF 50V K	1	
	C716	CK73GB1H472K	CHIP C	4700PF 50V K	1	
	C717	CK73GB1H472K	CHIP C	4700PF 50V K	1	
	C718	CK73GB1H472K	CHIP C	4700PF 50V K	1	
	C719	CK73GB1H472K	CHIP C	4700PF 50V K	1	
	C720	CK73GB1H472K	CHIP C	4700PF 50V K	1	
	C721	CK73GB1H472K	CHIP C	4700PF 50V K	1	
	C722	CK73GB1H472K	CHIP C	4700PF 50V K	1	
	C723	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C724	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C725	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C726	CK73FB1H224K	CHIP C	0.22UF 50V K	1	
	C727	CC73GCH1H471J	CHIP C	470PF 50V J	1	
	C728	CC73GCH1H471J	CHIP C	470PF 50V J	1	
	C731	CK73EB1C226M	CHIP C	22UF 16V M	1	
	C732	CK73EB1C226M	CHIP C	22UF 16V M	1	
	C733	CK73EB1C226M	CHIP C	22UF 16V M	1	
	C734	CK73EB1C226M	CHIP C	22UF 16V M	1	
	C735	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C736	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C737	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C738	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C741	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C742	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C743	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C744	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C745	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C746	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C751	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C752	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C753	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C754	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C757	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C758	CK73FB1C106K	CHIP C	10UF 16V K	1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	C759	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C760	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C761	CK73GB1H152K	CHIP C	1500PF 50V K	1	
	C762	CK73GB1H152K	CHIP C	1500PF 50V K	1	
	C763	C91-2290-05	CHIP C	4.7UF 250V	1	
	C764	C91-2290-05	CHIP C	4.7UF 250V	1	
	C765	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C766	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C767	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C768	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C769	C91-2290-05	CHIP C	4.7UF 250V	1	
	C770	C91-2290-05	CHIP C	4.7UF 250V	1	
	C771	CE32BF1H220M	ELECTRO	22UF 50WV M	1	
	C772	CE32BF1H220M	ELECTRO	22UF 50WV M	1	
	C773	CE32BF1H220M	ELECTRO	22UF 50WV M	1	
	C774	CE32BF1H220M	ELECTRO	22UF 50WV M	1	
	C775	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C776	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C777	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C778	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C784	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C789	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C790	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C803	CK73GB1H102K	CHIP C	1000PF 50V K	1	
	C804	CK73GB1H102K	CHIP C	1000PF 50V K	1	
	C807	CK73GB1H102K	CHIP C	1000PF 50V K	1	
	C808	CK73GB1H102K	CHIP C	1000PF 50V K	1	
	C842	CC73GCH1H681J	CHIP C	680PF 50V J	1	
	C846	CC73GCH1H681J	CHIP C	680PF 50V J	1	
	C851	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C856	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C867	CE32CL0J101M	ELECTRO	100UF 6.3V M	1	
	C873	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C891	CC73GCH1H151J	CHIP C	150PF 50V J	1	
	C892	CC73GCH1H151J	CHIP C	150PF 50V J	1	
	C893	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C894	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C895	CK73EB1E105K	CHIP C	1.0UF 25V K	1	
	C896	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C897	CK73FB1C106K	CHIP C	10UF 16V K	1	
	C909	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C915	CC73GCH1H101J	CHIP C	100PF 50V J	1	
	C920	CK73GB1H104K	CHIP C	0.10UF 50V K	1	
	C922	CC73GCH1H102J	CHIP C	1000PF J	1	
	C926	CC73GCH1H102J	CHIP C	1000PF J	1	
	C931	CC73GCH1H101J	CHIP C	100PF 50V J	1	
	C935	CC73GCH1H101J	CHIP C	100PF 50V J	1	
	C939	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C940	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C941	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C942	CK73GB1H103K	CHIP C	0.010UF 50V K	1	
	C965	CK73FB1E475K	CHIP C	4.7UF 25V K	1	
	C966	CK73FB1E475K	CHIP C	4.7UF 25V K	1	
	C967	CE32CL1V100M	ELECTRO	10UF 35WV M	1	
	C968	CE32CL1V100M	ELECTRO	10UF 35WV M	1	
	C981	CK73GB1C105K	CHIP C	1.0UF 16V K	1	
	C982	CK73GB1C105K	CHIP C	1.0UF 16V K	1	
	C983	CK73GB1C105K	CHIP C	1.0UF 16V K	1	
	C984	CK73GB1C105K	CHIP C	1.0UF 16V K	1	
	R11	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R12	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R13	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R14	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R15	RK73GB2A154J	CHIP R	150K J 1/10W	1	
	R16	RK73GB2A682J	CHIP R	6.8K J 1/10W	1	
	R17	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R20	RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
	R21	RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
	R22	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R23	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R24	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R25	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R26	RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
	R27	RK73GB2A682J	CHIP R	6.8K J 1/10W	1	
	R28	RK73GB2A392J	CHIP R	3.9K J 1/10W	1	
	R29	RK73GB2A152J	CHIP R	1.5K J 1/10W	1	
	R30	RK73GB2A272J	CHIP R	2.7K J 1/10W	1	
	R31	RK73EB2E122J	CHIP R	1.2K J 1/4W	1	
	R35	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R36	RK73EB2E152J	CHIP R	1.5K J 1/4W	1	
	R37	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R38	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R39	RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
	R40	RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
	R41	RK73GB2A680J	CHIP R	68 J 1/10W	1	
	R42	RK73GB2A680J	CHIP R	68 J 1/10W	1	
	R43	RK73GB2A680J	CHIP R	68 J 1/10W	1	
	R44	RK73GB2A680J	CHIP R	68 J 1/10W	1	
	R45	RK73GB2A680J	CHIP R	68 J 1/10W	1	
	R46	RK73GB2A680J	CHIP R	68 J 1/10W	1	
	R47	RK73PB2H100J	CHIP R	10 J 1/2W	1	
	R48	RK73PB2H100J	CHIP R	10 J 1/2W	1	
	R49	RK73PB2H100J	CHIP R	10 J 1/2W	1	
	R51	RK73EB2E153J	CHIP R	15K J 1/4W	1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
R52		RK73EB2E153J	CHIP R	15K J 1/4W	1	
R53		RK73PB2H100J	CHIP R	10 J 1/2W	1	
R54		RK73PB2H100J	CHIP R	10 J 1/2W	1	
R55		RK73EB2E153J	CHIP R	15K J 1/4W	1	
R56		RK73EB2E153J	CHIP R	15K J 1/4W	1	
R57		RK73PB2H220J	CHIP R	22 J 1/2W	1	
R58		RK73PB2H220J	CHIP R	22 J 1/2W	1	
R59		RK73GB2A101J	CHIP R	100 J 1/10W	1	
R60		RK73GB2A101J	CHIP R	100 J 1/10W	1	
R61		RK73EB2E4R7J	CHIP R	4.7 J 1/4W	1	
R62		RK73EB2E4R7J	CHIP R	4.7 J 1/4W	1	
R63		RK73EB2E332J	CHIP R	3.3K J 1/4W	1	
R64		RK73EB2E332J	CHIP R	3.3K J 1/4W	1	
R65		RK73GB2A101J	CHIP R	100 J 1/10W	1	
R66		RK73GB2A101J	CHIP R	100 J 1/10W	1	
R67		RK73GB2A100J	CHIP R	10 J 1/10W	1	
R68		RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
R69		RK73GB2A153J	CHIP R	15K J 1/10W	1	
R70		RK73GB2A103J	CHIP R	10K J 1/10W	1	
R72		RK73GB2A821J	CHIP R	820 J 1/10W	1	
R73		RK73GB2A300J	CHIP R	30 J 1/10W	1	
R74		RK73GB2A300J	CHIP R	30 J 1/10W	1	
R75		RK73EB2E4R7J	CHIP R	4.7 J 1/4W	1	
R76		RK73EB2E472J	CHIP R	4.7K J 1/4W	1	
R77		RK73GB2A101J	CHIP R	100 J 1/10W	1	
R78		RK73GB2A101J	CHIP R	100 J 1/10W	1	
R79		RK73EB2E4R7J	CHIP R	4.7 J 1/4W	1	
R80		RK73EB2E472J	CHIP R	4.7K J 1/4W	1	
R81		RK73GB2A333J	CHIP R	33K J 1/10W	1	
R82		RK73GB2A124J	CHIP R	120K J 1/10W	1	
R83		RK73GB2A273J	CHIP R	27K J 1/10W	1	
R84		RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
R85		RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
R86		RK73GB2A103J	CHIP R	10K J 1/10W	1	
R87		RK73GB2A103J	CHIP R	10K J 1/10W	1	
R88		RK73GB2A333J	CHIP R	33K J 1/10W	1	
R91		RK73GB2A103J	CHIP R	10K J 1/10W	1	
R92		RK73GB2A223J	CHIP R	22K J 1/10W	1	
R93		RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
R94		RK73GB2A123J	CHIP R	12K J 1/10W	1	
R95		RK73GB2A223J	CHIP R	22K J 1/10W	1	
R96		RK73GB2A470J	CHIP R	47 J 1/10W	1	
R97		RK73GB2A103J	CHIP R	10K J 1/10W	1	
R98		RK73GB2A103J	CHIP R	10K J 1/10W	1	
R101		RK73EB2E102J	CHIP R	1.0K J 1/4W	1	
R102		RK73EB2E102J	CHIP R	1.0K J 1/4W	1	
R103		RK73GB2A912J	CHIP R	9.1K J 1/10W	1	
R104		RK73GB2A912J	CHIP R	9.1K J 1/10W	1	
R105		RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
R106		RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
R111		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R112		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R113		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R114		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R115		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R116		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R117		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R118		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R119		RK73GB2A104J	CHIP R	100K J 1/10W	1	
R120		RK73GB2A104J	CHIP R	100K J 1/10W	1	
R125		RK73EB2E474J	CHIP R	470K J 1/4W	1	
R131		RK73EB2E102J	CHIP R	1.0K J 1/4W	1	
R132		RK73EB2E102J	CHIP R	1.0K J 1/4W	1	
R133		RK73GB2A912J	CHIP R	9.1K J 1/10W	1	
R134		RK73GB2A912J	CHIP R	9.1K J 1/10W	1	
R135		RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
R136		RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
R141		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R142		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R143		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R144		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R145		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R146		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R147		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R148		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R149		RK73GB2A104J	CHIP R	100K J 1/10W	1	
R150		RK73GB2A104J	CHIP R	100K J 1/10W	1	
R161		RK73EB2E102J	CHIP R	1.0K J 1/4W	1	
R162		RK73EB2E102J	CHIP R	1.0K J 1/4W	1	
R163		RK73GB2A123J	CHIP R	12K J 1/10W	1	
R164		RK73GB2A123J	CHIP R	12K J 1/10W	1	
R165		RK73GB2A273J	CHIP R	27K J 1/10W	1	
R166		RK73GB2A273J	CHIP R	27K J 1/10W	1	
R167		RK73GB2A153J	CHIP R	15K J 1/10W	1	
R168		RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
R169		RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
R171		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R172		RK73GH2A103D	CHIP R	10K D 1/10W	1	
R173		RK73GH2A473D	CHIP R	47K D 1/10W	1	
R174		RK73GH2A473D	CHIP R	47K D 1/10W	1	
R175		RK73GB2A104J	CHIP R	100K J 1/10W	1	
R201		RK73GB2A431J	CHIP R	430 J 1/10W	1	
R202		RK73GB2A431J	CHIP R	430 J 1/10W	1	
R203		RK73GB2A152J	CHIP R	1.5K J 1/10W	1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R204	RK73GB2A152J	CHIP R	1.5K J 1/10W	1	
	R205	RK73GB2A470J	CHIP R	47 J 1/10W	1	
	R206	RK73GB2A470J	CHIP R	47 J 1/10W	1	
	R207	RK73GB2A471J	CHIP R	470 J 1/10W	1	
	R208	RK73GB2A471J	CHIP R	470 J 1/10W	1	
	R209	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R210	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R211	RK73GB2A123J	CHIP R	12K J 1/10W	1	
	R212	RK73GB2A123J	CHIP R	12K J 1/10W	1	
	R213	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R214	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R231	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R232	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R233	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R234	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R235	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R236	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R237	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R238	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R241	RK73GB2A822J	CHIP R	8.2K J 1/10W	1	
	R242	RK73GB2A822J	CHIP R	8.2K J 1/10W	1	
	R243	RK73GB2A912J	CHIP R	9.1K J 1/10W	1	
	R244	RK73GB2A912J	CHIP R	9.1K J 1/10W	1	
	R245	RK73GB2A563J	CHIP R	56K J 1/10W	1	
	R246	RK73GB2A563J	CHIP R	56K J 1/10W	1	
	R251	RK73GB2A104J	CHIP R	100K J 1/10W	1	
	R252	RK73GB2A104J	CHIP R	100K J 1/10W	1	
	R253	RK73GB2A622J	CHIP R	6.2K J 1/10W	1	
	R254	RK73GB2A622J	CHIP R	6.2K J 1/10W	1	
	R255	RK73GB2A682J	CHIP R	6.8K J 1/10W	1	
	R256	RK73GB2A682J	CHIP R	6.8K J 1/10W	1	
	R271	RK73GB2A431J	CHIP R	430 J 1/10W	1	
	R272	RK73GB2A431J	CHIP R	430 J 1/10W	1	
	R273	RK73GB2A152J	CHIP R	1.5K J 1/10W	1	
	R274	RK73GB2A152J	CHIP R	1.5K J 1/10W	1	
	R275	RK73GB2A470J	CHIP R	47 J 1/10W	1	
	R276	RK73GB2A470J	CHIP R	47 J 1/10W	1	
	R277	RK73GB2A471J	CHIP R	470 J 1/10W	1	
	R278	RK73GB2A471J	CHIP R	470 J 1/10W	1	
	R279	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R280	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R281	RK73GB2A123J	CHIP R	12K J 1/10W	1	
	R282	RK73GB2A123J	CHIP R	12K J 1/10W	1	
	R283	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R284	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R301	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R302	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R303	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R304	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R305	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R306	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R307	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R308	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R311	RK73GB2A822J	CHIP R	8.2K J 1/10W	1	
	R312	RK73GB2A822J	CHIP R	8.2K J 1/10W	1	
	R313	RK73GB2A912J	CHIP R	9.1K J 1/10W	1	
	R314	RK73GB2A912J	CHIP R	9.1K J 1/10W	1	
	R315	RK73GB2A563J	CHIP R	56K J 1/10W	1	
	R316	RK73GB2A563J	CHIP R	56K J 1/10W	1	
	R321	RK73GB2A104J	CHIP R	100K J 1/10W	1	
	R322	RK73GB2A104J	CHIP R	100K J 1/10W	1	
	R323	RK73GB2A622J	CHIP R	6.2K J 1/10W	1	
	R324	RK73GB2A622J	CHIP R	6.2K J 1/10W	1	
	R325	RK73GB2A682J	CHIP R	6.8K J 1/10W	1	
	R326	RK73GB2A682J	CHIP R	6.8K J 1/10W	1	
	R351	RK73GB2A513J	CHIP R	51K J 1/10W	1	
	R352	RK73GB2A513J	CHIP R	51K J 1/10W	1	
	R353	RK73GB2A152J	CHIP R	1.5K J 1/10W	1	
	R354	RK73GB2A152J	CHIP R	1.5K J 1/10W	1	
	R355	RK73GB2A152J	CHIP R	1.5K J 1/10W	1	
	R356	RK73GB2A152J	CHIP R	1.5K J 1/10W	1	
	R357	RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
	R358	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R361	RK73GB2A431J	CHIP R	430 J 1/10W	1	
	R362	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R363	RK73GB2A104J	CHIP R	100K J 1/10W	1	
	R364	RK73GB2A682J	CHIP R	6.8K J 1/10W	1	
	R365	RK73GB2A152J	CHIP R	1.5K J 1/10W	1	
	R371	RK73GB2A241J	CHIP R	240 J 1/10W	1	
	R372	RK73GB2A154J	CHIP R	150K J 1/10W	1	
	R376	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R377	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R381	RK73GB2A392J	CHIP R	3.9K J 1/10W	1	
	R382	RK73GB2A113J	CHIP R	11K J 1/10W	1	
	R383	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R384	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R385	RK73GB2A153J	CHIP R	15K J 1/10W	1	
	R386	RK73GB2A153J	CHIP R	15K J 1/10W	1	
	R387	RK73GB2A272J	CHIP R	2.7K J 1/10W	1	
	R388	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R389	RK73GB2A153J	CHIP R	15K J 1/10W	1	
	R391	RK73GB2A512J	CHIP R	5.1K J 1/10W	1	
	R392	RK73GB2A153J	CHIP R	15K J 1/10W	1	
	R393	RK73GB2A103J	CHIP R	10K J 1/10W	1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R394	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R395	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R396	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R397	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R398	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R399	RK73GB2A333J	CHIP R	33K J 1/10W	1	
	R503	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R504	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R505	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R506	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R507	RK73GB2A152J	CHIP R	1.5K J 1/10W	1	
	R508	RK73GB2A911J	CHIP R	910 J 1/10W	1	
	R511	RK73FB2B150J	CHIP R	15 J 1/8W	1	
	R512	RK73FB2B150J	CHIP R	15 J 1/8W	1	
	R513	RK73FB2B150J	CHIP R	15 J 1/8W	1	
	R514	RK73FB2B150J	CHIP R	15 J 1/8W	1	
	R515	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R516	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R517	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R518	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R519	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R520	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R521	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R522	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R525	RK73EB2E222J	CHIP R	2.2K J 1/4W	1	
	R526	RK73EB2E222J	CHIP R	2.2K J 1/4W	1	
	R527	RK73EB2E100J	CHIP R	10 J 1/4W	1	
	R528	RK73EB2E100J	CHIP R	10 J 1/4W	1	
	R531	RK73GB2A1R0J	CHIP R	1.0 J 1/10W	1	
	R532	RK73GB2A1R0J	CHIP R	1.0 J 1/10W	1	
	R533	RK73GB2A1R0J	CHIP R	1.0 J 1/10W	1	
	R534	RK73GB2A1R0J	CHIP R	1.0 J 1/10W	1	
	R537	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R538	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R539	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R540	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R541	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R542	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R543	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R544	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R545	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R546	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R547	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R548	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R549	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R550	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R551	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R552	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R553	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R554	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R555	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R556	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R557	RK73GB2A303J	CHIP R	30K J 1/10W	1	
	R558	RK73GB2A303J	CHIP R	30K J 1/10W	1	
	R559	RK73FB2B4R7J	CHIP R	4.7 J 1/8W	1	
	R560	RK73FB2B4R7J	CHIP R	4.7 J 1/8W	1	
	R571	RK73GB2A332J	CHIP R	3.3K J 1/10W	1	
	R572	RK73GB2A333J	CHIP R	33K J 1/10W	1	
	R574	RK73GB2A162J	CHIP R	1.6K J 1/10W	1	
	R575	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R576	RK73GB2A133J	CHIP R	13K J 1/10W	1	
	R577	RK73GB2A393J	CHIP R	39K J 1/10W	1	
	R578	RK73GB2A393J	CHIP R	39K J 1/10W	1	
	R581	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R582	RK73GB2A112J	CHIP R	1.1K J 1/10W	1	
	R591	R92-5211-05	CHIP R	0.022OHM F 1W	1	
	R603	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R604	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R605	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R606	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R607	RK73GB2A681J	CHIP R	680 J 1/10W	1	
	R608	RK73GB2A561J	CHIP R	560 J 1/10W	1	
	R611	RK73FB2B150J	CHIP R	15 J 1/8W	1	
	R612	RK73FB2B150J	CHIP R	15 J 1/8W	1	
	R613	RK73FB2B150J	CHIP R	15 J 1/8W	1	
	R614	RK73FB2B150J	CHIP R	15 J 1/8W	1	
	R615	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R616	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R617	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R618	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R619	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R620	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R621	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R622	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R625	RK73EB2E222J	CHIP R	2.2K J 1/4W	1	
	R626	RK73EB2E222J	CHIP R	2.2K J 1/4W	1	
	R627	RK73EB2E100J	CHIP R	10 J 1/4W	1	
	R628	RK73EB2E100J	CHIP R	10 J 1/4W	1	
	R631	RK73GB2A1R0J	CHIP R	1.0 J 1/10W	1	
	R632	RK73GB2A1R0J	CHIP R	1.0 J 1/10W	1	
	R633	RK73GB2A1R0J	CHIP R	1.0 J 1/10W	1	
	R634	RK73GB2A1R0J	CHIP R	1.0 J 1/10W	1	
	R637	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R638	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R639	RK73GB2A223J	CHIP R	22K J 1/10W	1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R640	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R641	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R642	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R643	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R644	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R645	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R646	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R647	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R648	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R649	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R650	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R651	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R652	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R653	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R654	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R655	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R656	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R657	RK73GB2A303J	CHIP R	30K J 1/10W	1	
	R658	RK73GB2A303J	CHIP R	30K J 1/10W	1	
	R659	RK73FB2B4R7J	CHIP R	4.7 J 1/8W	1	
	R660	RK73FB2B4R7J	CHIP R	4.7 J 1/8W	1	
	R671	RK73GB2A332J	CHIP R	3.3K J 1/10W	1	
	R672	RK73GB2A333J	CHIP R	33K J 1/10W	1	
	R674	RK73GB2A162J	CHIP R	1.6K J 1/10W	1	
	R675	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R676	RK73GB2A133J	CHIP R	13K J 1/10W	1	
	R677	RK73GB2A393J	CHIP R	39K J 1/10W	1	
	R678	RK73GB2A393J	CHIP R	39K J 1/10W	1	
	R681	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R682	RK73GB2A112J	CHIP R	1.1K J 1/10W	1	
	R691	R92-5211-05	CHIP R	0.022OHM F 1W	1	
	R703	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R704	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R705	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R706	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R707	RK73GB2A750J	CHIP R	75 J 1/10W	1	
	R708	RK73GB2A820J	CHIP R	82 J 1/10W	1	
	R711	RK73FB2B270J	CHIP R	27 J 1/8W	1	
	R712	RK73FB2B270J	CHIP R	27 J 1/8W	1	
	R713	RK73FB2B270J	CHIP R	27 J 1/8W	1	
	R714	RK73FB2B270J	CHIP R	27 J 1/8W	1	
	R719	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R720	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R721	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R722	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R723	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R724	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R725	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R726	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R731	RK73GB2A100J	CHIP R	10 J 1/10W	1	
	R732	RK73GB2A100J	CHIP R	10 J 1/10W	1	
	R733	RK73GB2A100J	CHIP R	10 J 1/10W	1	
	R734	RK73GB2A100J	CHIP R	10 J 1/10W	1	
	R737	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R738	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R739	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R740	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R741	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R742	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R747	RK73GB2A822J	CHIP R	8.2K J 1/10W	1	
	R748	RK73GB2A822J	CHIP R	8.2K J 1/10W	1	
	R749	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R750	RK73FB2B100J	CHIP R	10 J 1/8W	1	
	R751	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R752	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R755	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R756	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R757	RK73GB2A303J	CHIP R	30K J 1/10W	1	
	R758	RK73GB2A303J	CHIP R	30K J 1/10W	1	
	R759	RK73FB2B4R7J	CHIP R	4.7 J 1/8W	1	
	R760	RK73FB2B4R7J	CHIP R	4.7 J 1/8W	1	
	R761	RK73PB2H2R4J	CHIP R	2.4 J 1/2W	1	
	R762	RK73PB2H2R4J	CHIP R	2.4 J 1/2W	1	
	R763	RK73PB2H2R4J	CHIP R	2.4 J 1/2W	1	
	R764	RK73PB2H2R4J	CHIP R	2.4 J 1/2W	1	
	R765	RK73EB2E472J	CHIP R	4.7K J 1/4W	1	
	R766	RK73EB2E472J	CHIP R	4.7K J 1/4W	1	
	R767	RK73EB2E100J	CHIP R	10 J 1/4W	1	
	R768	RK73EB2E100J	CHIP R	10 J 1/4W	1	
	R769	RK73EB2E472J	CHIP R	4.7K J 1/4W	1	
	R770	RK73EB2E472J	CHIP R	4.7K J 1/4W	1	
	R771	R92-5576-05	METAL R	0.02OHM 5W	1	
	R772	R92-5576-05	METAL R	0.02OHM 5W	1	
	R777	RK73GB2A393J	CHIP R	39K J 1/10W	1	
	R778	RK73GB2A393J	CHIP R	39K J 1/10W	1	
	R781	RK73GB2A113J	CHIP R	11K J 1/10W	1	
	R782	RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
	R783	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R784	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R801	RK73GB2A123J	CHIP R	12K J 1/10W	1	
	R802	RK73GB2A123J	CHIP R	12K J 1/10W	1	
	R803	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R804	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R805	RK73GB2A123J	CHIP R	12K J 1/10W	1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	R806	RK73GB2A123J	CHIP R	12K J 1/10W	1	
	R807	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R808	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R809	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R810	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R811	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R812	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R813	RK73GB2A333J	CHIP R	33K J 1/10W	1	
	R814	RK73GB2A333J	CHIP R	33K J 1/10W	1	
	R841	R92-5576-05	METAL R	0.02OHM 5W	1	
	R842	RK73GB2A332J	CHIP R	3.3K J 1/10W	1	
	R843	RK73GB2A563J	CHIP R	56K J 1/10W	1	
	R844	RK73GB2A272J	CHIP R	2.7K J 1/10W	1	
	R845	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R846	RK73GB2A393J	CHIP R	39K J 1/10W	1	
	R851	RK73GB2A623J	CHIP R	62K J 1/10W	1	
	R852	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R853	RK73GB2A202J	CHIP R	2.0K J 1/10W	1	
	R854	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R855	RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
	R856	RK73GB2A333J	CHIP R	33K J 1/10W	1	
	R861	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R862	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R863	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R864	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R865	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R866	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R867	RK73GB2A562J	CHIP R	5.6K J 1/10W	1	
	R868	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R871	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R872	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R873	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R874	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R891	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R892	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R893	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R894	RK73GB2A123J	CHIP R	12K J 1/10W	1	
	R896	RK73GB2A681J	CHIP R	680 J 1/10W	1	
	R897	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R898	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R901	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R902	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R903	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R904	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R917	RK73GB2A473J	CHIP R	47K J 1/10W	1	
	R918	RK73GB2A123J	CHIP R	12K J 1/10W	1	
	R919	RK73GB2A474J	CHIP R	470K J 1/10W	1	
	R920	RK73GB2A332J	CHIP R	3.3K J 1/10W	1	
	R922	RK73GB2A623J	CHIP R	62K J 1/10W	1	
	R923	RK73GB2A822J	CHIP R	8.2K J 1/10W	1	
	R925	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R926	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R927	RK73GB2A183J	CHIP R	18K J 1/10W	1	
	R928	RK73GB2A222J	CHIP R	2.2K J 1/10W	1	
	R931	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R935	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R936	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R941	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R943	RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
	R945	RK73GB2A472J	CHIP R	4.7K J 1/10W	1	
	R946	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R951	RK73GB2A103J	CHIP R	10K J 1/10W	1	
	R952	RK73GB2A333J	CHIP R	33K J 1/10W	1	
	R953	RK73GB2A223J	CHIP R	22K J 1/10W	1	
	R961	RK73EB2E470J	CHIP R	47 J 1/4W	1	
	R962	RK73EB2E470J	CHIP R	47 J 1/4W	1	
	R963	RK73GB2A122J	CHIP R	1.2K J 1/10W	1	
	R964	RK73GB2A122J	CHIP R	1.2K J 1/10W	1	
	R965	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R966	RK73GB2A102J	CHIP R	1.0K J 1/10W	1	
	R967	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R968	RK73GB2A101J	CHIP R	100 J 1/10W	1	
	R969	RK73EB2E470J	CHIP R	47 J 1/4W	1	
	R970	RK73EB2E470J	CHIP R	47 J 1/4W	1	
	R981	RK73EB2E4R7J	CHIP R	4.7 J 1/4W	1	
	R982	RK73EB2E4R7J	CHIP R	4.7 J 1/4W	1	
	R983	RK73EB2E472J	CHIP R	4.7K J 1/4W	1	
	R984	RK73EB2E472J	CHIP R	4.7K J 1/4W	1	
	VR201	R31-0264-05	VARIABLE RESISTOR	10K(A)	1	
	VR241	R31-0265-05	VARIABLE RESISTOR	50K(C)	1	
	VR271	R31-0264-05	VARIABLE RESISTOR	10K(A)	1	
	VR311	R31-0265-05	VARIABLE RESISTOR	50K(C)	1	
	VR361	R31-0264-05	VARIABLE RESISTOR	10K(A)	1	
	VR371	R31-0268-05	VARIABLE RESISTOR	10K(15C)	1	
	VR381	R31-0265-05	VARIABLE RESISTOR	50K(C)	1	
	L31	L33-2612-05	CHOKE COIL	90UH EER28	1	
	L41	L19-0853-05	TRANSFORMER FOR CONVERTER		1	
	L521	L33-3210-05	CHOKE COIL	10UH	1	
	L522	L33-3210-05	CHOKE COIL	10UH	1	
	L621	L33-3210-05	CHOKE COIL	10UH	1	
	L622	L33-3210-05	CHOKE COIL	10UH	1	
	L761	L33-3211-05	CHOKE COIL		1	
	L762	L33-3211-05	CHOKE COIL		1	

MODEL	MARK	MODEL	MARK
XR900-5	K0	XR900-5	W1

Safe	Symbol No.	Parts No.	Parts Name	Description	QTY	Local
	J31	E70-0875-15	SCREW TERMINAL BOARD		1	
	CN101	E41-2167-05	FLAT CABLE CONNECTOR	10P	1	
	CN201	E41-2167-05	FLAT CABLE CONNECTOR	10P	1	
	CN301	E41-2175-05	FLAT CABLE CONNECTOR	18P	1	
	CN501	E41-3396-05	FLAT CABLE CONNECTOR	18P TOP	1	
	CN891	E41-1682-05	PIN ASSY		1	
	J32	J13-0611-05	FUSE HOLDER		1	
	J33	J13-0613-05	FUSE HOLDER		1	
	J101	E63-0978-05	PIN JACK	6P W/R	1	
	S251	S62-0842-05	SLIDE SWITCH		1	
	S321	S62-0842-05	SLIDE SWITCH		1	
	TH901	NCP18WB473J0S	THERMISTOR	47KOHM	1	
	TH902	NCP18WB473J0S	THERMISTOR	47KOHM	1	
	TH903	NCP18WB473J0S	THERMISTOR	47KOHM	1	